

ADMIN JOB PERFORMANCE MEASUREUNIT: 2 REV #: 000 DATE: \_\_\_\_\_SYSTEM/DUTY AREA: Plant Monitoring System (PMS)TASK: Setup programmable alarm on PMS.

JTA#: \_\_\_\_\_

KA VALUE RO: 3.0 SRO: 3.0 KA REFERENCE: 2.1.19APPROVED FOR ADMINISTRATION TO: RO: X SRO: XTASK LOCATION: INSIDE CR: X OUTSIDE CR: \_\_\_\_\_ BOTH: \_\_\_\_\_

SUGGESTED TESTING ENVIRONMENT AND METHOD (PERFORM OR SIMULATE):

PLANT SITE: Simulate SIMULATOR: Perform LAB: \_\_\_\_\_

POSITION EVALUATED: RO: \_\_\_\_\_ SRO: \_\_\_\_\_

ACTUAL TESTING ENVIRONMENT: SIMULATOR: \_\_\_\_\_ PLANT SITE: \_\_\_\_\_ LAB: \_\_\_\_\_

TESTING METHOD: SIMULATE: \_\_\_\_\_ PERFORM: \_\_\_\_\_

APPROXIMATE COMPLETION TIME IN MINUTES: 10 MinutesREFERENCE(S): 2106.008 Rev 025-00-0 and skill of craft

EXAMINEE'S NAME: \_\_\_\_\_ SSN: \_\_\_\_\_

EVALUATOR'S NAME: \_\_\_\_\_

THE EXAMINEE'S PERFORMANCE WAS EVALUATED AGAINST THE STANDARDS CONTAINED IN THIS JPM  
AND IS DETERMINED TO BE:

SATISFACTORY: \_\_\_\_\_ UNSATISFACTORY: \_\_\_\_\_

PERFORMANCE CHECKLIST COMMENTS:

Start Time \_\_\_\_\_ Stop Time \_\_\_\_\_ Total Time \_\_\_\_\_

SIGNED: \_\_\_\_\_ DATE: \_\_\_\_\_

SIGNATURE INDICATES THIS JPM HAS BEEN COMPARED TO ITS APPLICABLE PROCEDURE BY A QUALIFIED  
INDIVIDUAL (NOT THE EXAMINEE) AND IS CURRENT WITH THAT REVISION.

ADMIN JOB PERFORMANCE MEASURE

**THE EXAMINER SHALL REVIEW THE FOLLOWING WITH THE EXAMINEE:**

The examiner shall review the "Briefing Checklist - System Walkthrough" portion of OP 1064.023 Attachment 6 with  
the examinee.

**JPM INITIAL TASK CONDITIONS:**

Mode 1 Full Power. Performing initial conditions of 2106.008, Steam Generator Operations section 8.2.

**TASK STANDARD:**

Programmable alarm setup on PMS for blowdown activity (R4425).

**TASK PERFORMANCE AIDS:**

PMS operating

**EXAMINER'S NOTE:**

Check no PMS programmable alarms are set.

ADMIN JOB PERFORMANCE MEASURE**INITIATING CUE:**

The SS/CRS directs, "Place a programmable alarm on 2K01-J9 for blowdown activity (R4425) high of 1.0E3. Use work item number 101010."

**CRITICAL ELEMENTS (C):** 3,4,5,6,7,9,10,and 11

PERFORMANCE CHECKLIST			STANDARDS	(Circle One)
<b>NOTE:</b> <b>Steps 3 through 7 may be performed prior to steps 1 and 2.</b>				
	1.	Select "Programmable Annunciator Assignment Screen for 2K01-J9" on PMS.	At PMS keyboard, typed "J9" and depressed "ENTER" key.  Verified Programmable Annunciator Assignment Screen for 2K01-J9 appears on touch screen.	N/A SAT UNSAT
	2.	Add "R4425" point on Programmable Annunciator Assignment Screen.	At PMS keyboard, selected a point location on Programmable Annunciator Assignment Screen.  Typed "R4425" and depressed "ENTER" key.	N/A SAT UNSAT
(C)	3.	Select Database Management from Programmable Annunciator Assignment Screen.	At Programmable Annunciator Assignment Screen, touched "DBM" touch button on lower portion of touch screen.  Verified Analog Input Point Template Screen appears.	N/A SAT UNSAT
(C)	4.	Select "R4425" on Analog Input Point Template Screen.	At PMS keyboard, typed "R4425" and depressed "ENTER" key.  Verified that point "R4425" is selected.	N/A SAT UNSAT
(C)	5.	Select "Power Operations " alarm setpoint for update.	At PMS keyboard, depressed right or left arrow key to place cursor on either "Power Operations High Alarm" position.	N/A SAT UNSAT
(C)	6.	Change "High" alarm setpoint to "1.0E3".	At PMS keyboard, typed "1.0E3" and depressed "ENTER" key.	N/A SAT UNSAT
(C)	7.	Save changes to alarm setpoint.	At PMS keyboard, depressed "F-3" key to save.	N/A SAT UNSAT

ADMIN JOB PERFORMANCE MEASURE

PERFORMANCE CHECKLIST			STANDARDS		(Circle One)
<b>Examiners Note:</b> Have examinee type “101010” as work item number and press “ENTER” to allow saving on the Simulator PMS.					
	8.	Select “Programmable Annunciator Assignment Screen for 2K01-J9” on PMS.	At PMS keyboard, typed “J9” and depressed “ENTER” key.  Verified Programmable Annunciator Assignment Screen for 2K01-J9 appears on touch screen.	N/A SAT UNSAT	
(C)	9.	Add “R4425”point on Programmable Annunciator Assignment Screen.	At PMS keyboard, selected a point location on Programmable Annunciator Assignment Screen.  Typed “R4425” and depressed “ENTER” key.	N/A SAT UNSAT	
(C)	10.	Type “S” in process code and depress “ENTER”.	At PMS keyboard, typed “S” in process code and depressed “ENTER” key.	N/A SAT UNSAT	
(C)	11.	Save changes to alarm setpoint.	At PMS keyboard, depressed F3 key to save.	N/A SAT UNSAT	
END					

ADMIN JOB PERFORMANCE MEASURE

QUESTION:

ANSWER:

**ADMIN JOB PERFORMANCE MEASURE**

**INITIAL CONDITIONS:**

Mode 1 Full Power. Performing initial conditions of 2106.008, Steam Generator Operations section 8.2.

**INITIATING CUE:**

The SS/CRS directs, "Place a programmable alarm on 2K01-J9 for blowdown activity (R4425) high of 1.0E3. Use work item number 101010."