

SOUTHWEST RESEARCH INSTITUTE

6220 CULEBRA ROAD • POST OFFICE DRAWER 28510 • SAN ANTONIO, TEXAS, 78228-0510 • TEL (210) 522-5215 • FAX (210) 522-3692

To: Ron Green, Div 20, X5305

From: Walt Hill, Metrology Group Leader
Institute Calibration Laboratory

Date: Nov. 29, 2004

Subject: Out-of-tolerance Notice

The purpose of this notice is to alert you of a condition, which may have caused erroneous measurements affecting safety or the quality of products or services your organization provides. The attached as-found readings are provided for your evaluation to determine if the instrument listed below had an impact and if further action is required.

When the as-found results are near the specification limit, +/- a margin less than the measurement uncertainty, it is not possible to state in-tolerance or out-of-tolerance with a 95% level of confidence. It is the Institute Calibration Laboratory policy that the client is made aware of this situation because the end-user is taking some of the risk that the instrument listed below may not meet the end-user measurement requirements.

Your review/evaluation should be conducted in accordance with your organizational quality policy and procedural requirements. If we can be of further assistance, please contact the Calibration Laboratory at 522-5215. x 3046

Manufacturer: Hewlett-Packard **Model:** 34970A

Description: Data Acquisition Switch **Serial Number:** US37011843

Asset Number: 10567 **User ID Number:**

Last Calibration: Nov 14, 2003

Date Received for Service: Nov. 15, 2004 **Work Order Number:** 444061672

Service Requested: Scheduled calibration

Remarks: Exceeds limits, see data sheet.

OUT OF TOLERANCE

Southwest Research Institute
Calibration Laboratory
Measurement Report

| | | | | | |
|-------------|------------|-------|-------------------------|------------|-----------|
| Work Order: | 444061672 | Mfr. | HP | Technician | SRK |
| Asset No. | 010567 | Model | 34970A | Cal Date. | 29-Nov-04 |
| Serial No. | US37011843 | Type. | Data Acquisition Switch | | |
| Remarks: | | | | | |

| Function/Range | Test Point | TI Reading | Difference | +/-Limit | +/-Uncertainty | Found |
|-----------------------|------------|------------|------------|----------|----------------|--------|
| DC CURRENT | mAmp | mAmp | mAmp | mAmp | mAmp | Result |
| 10 mAmp | 0.00000 | -0.00069 | -0.00069 | 0.002 | 0.0012 | Pass |
| 100 mAmp | 0.0000 | -0.0006 | -0.0006 | 0.005 | 0.0012 | Pass |
| 1 A | Amp | Amp | Amp | Amp | Amp | |
| | 0.000000 | -0.000035 | -0.000035 | 0.0001 | 0.0012 | Pass |
| DC Volts | mVolts | mVolts | mVolts | mVolts | mVolts | |
| 100 mVolt | 0.0000 | -0.0005 | -0.0005 | 0.004 | 0.0012 | Pass |
| | Volts | Volts | Volts | Volts | Volts | |
| 1 Volt | 0.000000 | 0.000000 | 0.000000 | 0.000007 | 0.0000012 | Pass |
| 10 Volt | 0.00000 | 0.00000 | 0.00000 | 0.00005 | 0.000012 | Pass |
| 100 Volt | 0.0000 | 0.0000 | 0.0000 | 0.0006 | 0.00012 | Pass |
| 300 Volt | 0.000 | 0.000 | 0.000 | 0.009 | 0.0012 | Pass |
| Ohms 4 Wire | Ohm | Ohm | Ohm | Ohm | Ohm | |
| 100 Ohm | 0.0000 | 0.0012 | 0.0012 | 0.004 | 0.00012 | Pass |
| 1 kOhm | 0.00 | 0.000001 | 0.00 | 0.01 | 0.0012 | Pass |
| 10 kOhm | 0.0 | 0.00001 | 0.0 | 0.1 | 0.012 | Pass |
| 100 kOhm | 0 | 0.0001 | 0 | 1 | 0.12 | Pass |
| 1 MOhm | 0 | 0.000000 | 0 | 10 | 1.2 | Pass |
| 10 MOhm | 0 | 0.00000 | 0 | 100 | 12 | Pass |
| 100 Mohm | 0 | 0.0000 | 0 | 10000 | 120 | Pass |
| Gain Verification DCV | mVolts | mVolts | mVolts | mVolts | mVolts | |
| 100 mVolt | 100.0000 | 99.9969 | -0.0031 | 0.009 | 0.00016 | Pass |
| | Volts | Volts | Volts | Volts | Volts | |
| 1 Volt | 1.000000 | 0.999999 | -0.000001 | 0.000047 | 0.0000042 | Pass |
| 10 Volt | 10.00000 | 10.00002 | 0.00002 | 0.0004 | 0.000030 | Pass |
| 100 Volt | 100.0000 | 99.9998 | -0.0002 | 0.0051 | 0.00040 | Pass |
| 300 Volt | 300.000 | 299.999 | -0.001 | 0.0225 | 0.0018 | Pass |
| Ohms 4 Wire | Ohm | Ohm | Ohm | Ohm | Ohm | |
| 100 Ohm | 100.001310 | 97.8970 | -2.1043 | 0.014 | 0.0049 | Fail |
| | kOhm | kOhm | kOhm | kOhm | kOhm | |
| 1 kOhm | 0.99993220 | 0.979923 | -0.020009 | 0.00011 | 0.000036 | Fail |
| 10 kOhm | 9.9992830 | 9.78533 | -0.21395 | 0.0011 | 0.00036 | Fail |
| 100 kOhm | 99.993970 | 97.6572 | -2.3368 | 0.011 | 0.0036 | Fail |
| | MOhm | MOhm | MOhm | MOhm | MOhm | |
| 1 MOhm | 0.99988310 | 0.982208 | -0.017675 | 0.00011 | 0.00004 | Fail |
| 10 MOhm | 9.9989140 | 9.81541 | -0.18350 | 0.0014 | 0.00032 | Fail |
| 100 Mohm | 99.985260 | 84.1650 | -15.8203 | 0.81 | 0.0036 | Fail |

Southwest Research Institute
Calibration Laboratory
Measurement Report

| | | | | | |
|-------------|------------|-------|-------------------------|------------|-----------|
| Work Order: | 444061672 | Mfr. | HP | Technician | SRK |
| Asset No. | 010567 | Model | 34970A | Cal Date. | 29-Nov-04 |
| Serial No. | US37011843 | Type. | Data Acquisition Switch | | |

| Function/Range | Test Point | TI Reading | Difference | +/-Limit | +/-Uncertainty | Found |
|-----------------|------------|------------|------------|----------|----------------|--------|
| DC CURRENT | mAmp | mAmp | mAmp | mAmp | mAmp | Result |
| 10 mAmp | 10.00000 | 9.98353 | -0.01647 | 0.007 | 0.0014 | Fail |
| 100 mAmp | 100.0000 | 99.9500 | -0.0500 | 0.055 | 0.015 | Pass |
| 1 A | Amp | Amp | Amp | Amp | Amp | Fail |
| | 1.0000 | 0.976557 | -0.0234 | 0.0011 | 0.00030 | |
| AC Volts | mVolts | mVolts | mVolts | mVolts | mVolts | |
| 100 mV @ 1 kHz | 100.0000 | 99.9904 | -0.0096 | 0.1 | 0.015 | Pass |
| 100 mV @ 50 kHz | 100.0000 | 100.0211 | 0.0211 | 0.17 | 0.026 | Pass |
| AC Volts | Volts | Volts | Volts | Volts | Volts | |
| 1 V @ 1 kHz | 1.000000 | 0.999917 | -0.000083 | 0.001 | 0.000050 | Pass |
| 1 V @ 50 kHz | 1.000000 | 1.000353 | 0.000353 | 0.0017 | 0.00010 | Pass |
| 10 V @ 1 kHz | 10.00000 | 9.99943 | -0.00057 | 0.014 | 0.00042 | Pass |
| 10 V @ 50 kHz | 10.00000 | 10.00496 | 0.00496 | 0.017 | 0.00082 | Pass |
| 10 V @ 10 Hz | 10.00000 | 10.00650 | 0.00650 | 0.014 | 0.0026 | Pass |
| 10 mV @ 1 kHz | mVolts | mVolts | mVolts | mVolts | mVolts | Pass |
| | 10.0000 | 10.0021 | 0.0021 | 0.046 | 0.0051 | |
| 100 V @ 1 kHz | Volts | Volts | Volts | Volts | Volts | Pass |
| | 100.0000 | 100.0660 | 0.0660 | 0.1 | 0.0053 | |
| 100 V @ 50 kHz | 100.0000 | 99.9770 | -0.0230 | 0.17 | 0.0085 | Pass |
| 300 V @ 1 kHz | 300.000 | 299.994 | -0.006 | 0.42 | 0.044 | Pass |
| 300 V @ 50 kHz | 200.000 | 199.999 | -0.001 | 0.6 | 0.12 | Pass |
| AC Amp | mAmps | mAmps | mAmps | mAmps | mAmps | |
| 10 mA @ 1 kHz | 10.00000 | 9.98127 | -0.01873 | 0.014 | 0.0014 | Fail |
| 100 mA @ 1 kHz | 100.0000 | 97.6719 | -2.3281 | 0.6 | 0.070 | Fail |
| 1A @ 1 kHz | Amps | Amps | Amps | Amps | Amps | Pass |
| | 0.010000 | 0.009778 | -0.000222 | 0.00051 | 0.000010 | |
| AC Amp | Amps | Amps | Amps | Amps | Amps | Fail |
| 1A @ 1 kHz | 1.000000 | 0.976595 | -0.023405 | 0.0014 | 0.0010 | |
| Frequency | Hz | Hz | Hz | Hz | Hz | |
| 100 mV @ 100 Hz | 100.0000 | 99.99894 | -0.00106 | 0.1 | 0.012 | Pass |
| 1 V @ 100 kHz | kHz | kHz | kHz | kHz | kHz | Pass |
| | 100.0000 | 99.99806 | -0.00194 | 0.01 | 0.012 | |

END OF REPORT



SOUTHWEST RESEARCH INSTITUTE™

6220 Culebra Road, P.O. Drawer 28510
Institute Quality Systems
Institute Calibration Laboratory
Phone: 210-522-5215 Fax 210-522-3692



Certificate of Calibration

Submitted By: DIV20

Address: T1

Contact: RON GREEN

Manufacturer Model: HEWLETT-PACKARD 34970A

Description: DATA ACQUISITION/SWITCH UNIT

Serial No: US37011843

Asset No: 010567

Procedure: MULTIMETERS, JAN/03

Work Order: 444061672

Date Issued: Nov 30, 2004

Calibration Date: Nov 30, 2004

****Calibration Due:** Nov 30, 2005

Calibration Location: Bldg. 64

Environment: Temp. 73.0°F Hum. 40 %RH

***As Found:** OUT OF TOLERANCE

***As Left:** IN TOLERANCE

This certificate documents traceability to the National Institute of Standards and Technology (NIST) and the International System of Units (SI). The Laboratory quality system conforms to ISO/IEC 17025, 1999 and ANSI/NC SL Z540-1-1994 which are equivalent to relevant requirements of the ISO 9000-1994 series of standards. This certificate may not be reproduced, except in full, without the written approval of the Southwest Research Institute Calibration Laboratory. The results of this calibration relate only to the individual instrument described above. This certificate shall not be used to claim product endorsement by the American Association for Laboratory Accreditation (A2LA) or any agency of the U. S. Government

Uncertainty evaluation includes the item under test and is calculated in accordance with the ISO "Guide to the Expression of Uncertainty in Measurement" (GUM). The uncertainty represents an expanded uncertainty using a coverage factor of k=2 to approximate a 95% confidence level. See Remarks or attached Calibration Report with the same Work Order number for calibration data.

*The client has sole responsibility for determination of in/out of tolerance or compliance/noncompliance. An in/out of tolerance opinion is provided for your convenience based only on the Test Instrument (TI) reading(s) and limits as reported. The reported uncertainty relates only to the results at the time of calibration and does not imply any short or long term stability of the TI.

**Calibration interval is determined by the client and does not assure the instrument will remain within tolerance until this date. Any number of factors may cause the instrument to be out of tolerance before the next calibration date.

Remarks: None

Standards Used

| Asset | Manufacturer | Model | Description | Cal Due |
|--------|--------------|----------|-------------|------------|
| 000182 | FLUKE | 5700A/EP | CALIBRATOR | Dec 23, 04 |

Approved by: Walt Hill
Metrology Group Leader
m:\a2la1.rpt Rev date 11, May 04

Measurements by: Scott Kester
Metrology Technician

Southwest Research Institute
Calibration Laboratory
Measurement Report

| | | | | | |
|-------------|------------|-------|-------------------------|------------|-----------|
| Work Order: | 444061672 | Mfr. | HP | Technician | SRK |
| Asset No. | 010567 | Model | 34970A | | |
| Serial No. | US37011843 | Type. | Data Acquisition Switch | Cal Date. | 30-Nov-04 |
| Remarks: | | | | | |

| Function/Range | Test Point | TI Reading | Difference | +/-Limit | +/-Uncertainty | Left |
|-----------------------|------------|------------|------------|----------|----------------|--------|
| DC CURRENT | mAmp | mAmp | mAmp | mAmp | mAmp | Result |
| 10 mAmp | 0.00000 | -0.00065 | -0.00065 | 0.002 | 0.0012 | Pass |
| 100 mAmp | 0.0000 | -0.0006 | -0.0006 | 0.005 | 0.0012 | Pass |
| 1 A | Amp | Amp | Amp | Amp | Amp | |
| | 0.000000 | -0.000034 | -0.000034 | 0.0001 | 0.0012 | Pass |
| DC Volts | mVolts | mVolts | mVolts | mVolts | mVolts | |
| 100 mVolt | 0.0000 | -0.0003 | -0.0003 | 0.004 | 0.0012 | Pass |
| 1 Volt | Volts | Volts | Volts | Volts | Volts | |
| | 0.000000 | 0.000000 | 0.000000 | 0.000007 | 0.0000012 | Pass |
| 10 Volt | 0.00000 | 0.00000 | 0.00000 | 0.00005 | 0.000012 | Pass |
| 100 Volt | 0.0000 | 0.0000 | 0.0000 | 0.0006 | 0.00012 | Pass |
| 300 Volt | 0.000 | 0.000 | 0.000 | 0.009 | 0.0012 | Pass |
| Ohms 4 Wire | Ohm | Ohm | Ohm | Ohm | Ohm | |
| 100 Ohm | 0.0000 | 0.0007 | 0.0007 | 0.004 | 0.00012 | Pass |
| 1 kOhm | 0.00 | 0.000000 | 0.00 | 0.01 | 0.0012 | Pass |
| 10 kOhm | 0.0 | 0.00000 | 0.0 | 0.1 | 0.012 | Pass |
| 100 kOhm | 0 | 0.0000 | 0 | 1 | 0.12 | Pass |
| 1 MOhm | 0 | 0.000000 | 0 | 10 | 1.2 | Pass |
| 10 MOhm | 0 | 0.00000 | 0 | 100 | 12 | Pass |
| 100 Mohm | 0 | 0.0000 | 0 | 10000 | 120 | Pass |
| Gain Verification DCV | mVolts | mVolts | mVolts | mVolts | mVolts | |
| 100 mVolt | 100.0000 | 99.9996 | -0.0004 | 0.009 | 0.00016 | Pass |
| 1 Volt | Volts | Volts | Volts | Volts | Volts | |
| | 1.000000 | 1.000000 | 0.000000 | 0.000047 | 0.0000042 | Pass |
| 10 Volt | 10.00000 | 10.00000 | 0.00000 | 0.0004 | 0.000030 | Pass |
| 100 Volt | 100.0000 | 99.9998 | -0.0002 | 0.0051 | 0.00040 | Pass |
| 300 Volt | 300.000 | 299.999 | -0.001 | 0.0225 | 0.0018 | Pass |
| Ohms 4 Wire | Ohm | Ohm | Ohm | Ohm | Ohm | |
| 100 Ohm | 100.001310 | 100.0010 | -0.0003 | 0.014 | 0.0049 | Pass |
| 1 kOhm | kOhm | kOhm | kOhm | kOhm | kOhm | |
| | 0.99993220 | 0.999932 | 0.000000 | 0.00011 | 0.000036 | Pass |
| 10 kOhm | 9.9992830 | 9.99928 | 0.00000 | 0.0011 | 0.00036 | Pass |
| 100 kOhm | 99.993970 | 99.9939 | -0.0001 | 0.011 | 0.0036 | Pass |
| 1 MOhm | MOhm | MOhm | MOhm | MOhm | MOhm | |
| | 0.99988310 | 0.999880 | -0.000003 | 0.00011 | 0.00004 | Pass |
| 10 MOhm | 9.9989140 | 9.99893 | 0.00002 | 0.0014 | 0.00032 | Pass |
| 100 Mohm | 99.985260 | 99.9882 | 0.0129 | 0.81 | 0.0036 | Pass |

Southwest Research Institute
Calibration Laboratory
Measurement Report

| | | | | | |
|-------------|------------|-------|-------------------------|------------|-----------|
| Work Order: | 444061672 | Mfr. | HP | Technician | SRK |
| Asset No. | 010567 | Model | 34970A | Cal Date. | 30-Nov-04 |
| Serial No. | US37011843 | Type. | Data Acquisition Switch | | |

| Function/Range | Test Point | TI Reading | Difference | +/-Limit | +/-Uncertainty | Left |
|-----------------|------------|------------|------------|----------|----------------|--------|
| DC CURRENT | mAmp | mAmp | mAmp | mAmp | mAmp | Result |
| 10 mAmp | 10.00000 | 9.99995 | -0.00005 | 0.007 | 0.0014 | Pass |
| 100 mAmp | 100.0000 | 99.9999 | -0.0001 | 0.055 | 0.015 | Pass |
| 1 A | Amp | Amp | Amp | Amp | Amp | |
| | 1.0000 | 0.999994 | 0.0000 | 0.0011 | 0.00030 | Pass |
| AC Volts | mVolts | mVolts | mVolts | mVolts | mVolts | |
| 100 mV @ 1 kHz | 100.0000 | 99.9932 | -0.0068 | 0.1 | 0.015 | Pass |
| 100 mV @ 50 kHz | 100.0000 | 100.0139 | 0.0139 | 0.17 | 0.026 | Pass |
| AC Volts | Volts | Volts | Volts | Volts | Volts | |
| 1 V @ 1 kHz | 1.000000 | 0.999943 | -0.000057 | 0.001 | 0.000050 | Pass |
| 1 V @ 50 kHz | 1.000000 | 1.000268 | 0.000268 | 0.0017 | 0.00010 | Pass |
| 10 V @ 1 kHz | 10.00000 | 9.99952 | -0.00048 | 0.014 | 0.00042 | Pass |
| 10 V @ 50 kHz | 10.00000 | 10.00395 | 0.00395 | 0.017 | 0.00082 | Pass |
| 10 V @ 10 Hz | 10.00000 | 9.99994 | -0.00006 | 0.014 | 0.0026 | Pass |
| 10 mV @ 1 kHz | mVolts | mVolts | mVolts | mVolts | mVolts | |
| | 10.0000 | 10.0034 | 0.0034 | 0.046 | 0.0051 | Pass |
| 100 V @ 1 kHz | Volts | Volts | Volts | Volts | Volts | |
| | 100.0000 | 100.0290 | 0.0290 | 0.1 | 0.0053 | Pass |
| 100 V @ 50 kHz | 100.0000 | 99.9590 | -0.0410 | 0.17 | 0.0085 | Pass |
| 300 V @ 1 kHz | 300.000 | 299.970 | -0.030 | 0.42 | 0.044 | Pass |
| 300 V @ 50 kHz | 200.000 | 199.968 | -0.032 | 0.6 | 0.12 | Pass |
| AC Amp | mAmps | mAmps | mAmps | mAmps | mAmps | |
| 10 mA @ 1 kHz | 10.00000 | 9.99791 | -0.00209 | 0.014 | 0.0014 | Pass |
| 100 mA @ 1 kHz | 100.0000 | 100.0089 | 0.0089 | 0.6 | 0.070 | Pass |
| 1A @ 1 kHz | Amps | Amps | Amps | Amps | Amps | |
| | 0.010000 | 0.009993 | -0.000007 | 0.00051 | 0.000010 | Pass |
| AC Amp | Amps | Amps | Amps | Amps | Amps | |
| 1A @ 1 kHz | 1.000000 | 1.000058 | 0.000058 | 0.0014 | 0.0010 | Pass |
| Frequency | Hz | Hz | Hz | Hz | Hz | |
| 100 mV @ 100 Hz | 100.0000 | 99.99813 | -0.00187 | 0.1 | 0.012 | Pass |
| 1 V @ 100 kHz | kHz | kHz | kHz | kHz | kHz | |
| | 100.0000 | 99.99808 | -0.00192 | 0.01 | 0.012 | Pass |

END OF REPORT