

Technical Specification 4.2.b.4

Steam generator tubes found with less than the minimum wall thickness criteria determined by analysis, as described in WCAP-7832⁽¹⁾⁽²⁾, must either be repaired to be kept in service or removed from service by plugging.

Steam generator tube plugging is a common method of preventing primary-to-secondary steam generator tube leakage and has been utilized since the inception of PWR nuclear reactor plants. This method is relatively uncomplicated from a structural/mechanical standpoint as flow is cut off from the affected tube by plugging it in the hot and cold leg faces of the tubesheet.

To determine the basis for the sleeve plugging limit, the minimum sleeve wall thickness was calculated in accordance with the ASME Code and is consistent with Draft Regulatory Guide 1.121 (August 1976).

For the Westinghouse mechanical sleeves, the sleeve plugging limit of 31% is applied to the sleeve as shown on Figure TS 4.2-1. The sleeve plugging limits allow for eddy current testing inaccuracies and continued operational degradation per Draft Regulatory Guide 1.121 (August 1976).

Repair by sleeving, or other methods, has been recognized as a viable alternative for isolating unacceptable tube degradation and preventing tube leakage. Sleeving isolates unacceptable degradation and extends the service life of the tube, and the steam generator. Tube repair, by sleeving in accordance with WCAP-11643⁽³⁾ and WCAP-13088⁽⁴⁾, has been evaluated and analyzed as acceptable. The Westinghouse mechanical hybrid expansion joint (HEJ) sleeve spans the degraded area of the parent tube in the tubesheet region. The sleeves are either 36", 30" or 27" to allow access permitted by channel head bowl geometry. The sleeve is hydraulically expanded and hard rolled into the parent tubing.

⁽¹⁾WCAP 7832, "Evaluation of Steam Generator Tube, Tube Sheet, and Divider Plate Under Combined LOCA Plus SSE Conditions."

⁽²⁾E. W. James, WPSC, to A. Schwencer, NRC, dated September 6, 1977.

⁽³⁾WCAP 11643, Kewaunee Steam Generator Sleeving Report, Revision 1, November 1988 (Proprietary).

⁽⁴⁾WCAP 13088, Revision 3, "Westinghouse Series 44 and 51 Steam Generator Generic Sleeving Report," January 1994.

The pressure boundary for HEJ sleeves is shown on Figure TS 4.2-1. The pressure boundary used to disposition parent tube indications (PTIs) detected in the upper joint of HEJ sleeved tubes is discussed in WCAP-14641⁽⁵⁾. The pressure boundary will allow PTIs located such that there is a minimum diameter change of 0.003 inch (plus an allowance for NDE uncertainty) between the peak diameter of the sleeve hardroll, and the diameter at the elevation of the PTI, to remain in service. The 0.003 inch interference lip is derived from structural and leakage testing. When inspecting and dispositioning the PTIs, the acceptance criteria will be adjusted to account for measurement uncertainties associated with the technique used to measure the relative change in ID sleeve diameters. During field application, the PTI elevation will be measured by comparing the diameter reported at the peak amplitude of the flaw, and the diameter at the center of the plus point coil's field, and using the more conservative of the two diameters to perform the ΔD determination. Application of the pressure boundary for HEJ sleeved tubes provides allowance for leakage in a faulted loop during a postulated steam line break (SLB) event. A SLB leakage of 0.025 gpm is assumed for each applicable indication. Steam line break leakage from all sources must be calculated to be < 34 gpm in the faulted loop. Maintenance of the 34 gpm limit ensures off-site doses will remain within a small fraction of the 10 CFR Part 100 guidelines for a SLB.

Topical CEN-629-P⁽⁶⁾ describes three types of Combustion Engineering leak tight sleeves. The first type, the straight tubesheet sleeve, spans the degraded area of the parent tube in the tubesheet crevice region. The sleeve is welded to the parent tube near each end. The second type of sleeve is a full depth tubesheet sleeve which is welded near the sleeve upper end and hard rolled into the tube and tubesheet at the sleeve lower end. A variation on the tubesheet sleeve design is the use of a pre-curved sleeve which allows access to the outer periphery of the tube bundle. The third type of sleeve, the tube support plate sleeve, spans the degraded area of the tube support plate and is installed up to the sixth support plate. This sleeve is welded to the parent tube near each end of the sleeve. CEN-632-P⁽⁷⁾ describes the steps required to re-sleeve tubes which have existing HEJ sleeves. This report describes the sleeved/tube preparation, re-sleeve installation and the design of a leak tight full depth tubesheet sleeve that is up to 39 inches in length.

Two types of Westinghouse laser welded sleeves can be installed, tube support plate sleeves and tubesheet sleeves.

⁽⁵⁾ WCAP-14641, "HEJ Sleeved Tube Structural Integrity Criteria: Diameter Interference at PTIs," April 1996.

⁽⁶⁾ CEN-629-P Revision 2, "Repair of Westinghouse Series 44 and 51 Steam Generator Tubes Using Leak Tight Sleeves," January 1997.

⁽⁷⁾ CEN-632-P, "Repair of Kewaunee Steam Generator Tubes Using a Resleeving Technique," April 1997.

The tube support plate sleeve is 12" long and spans the degraded area of the tube adjacent to the support plate intersection. The tube support plate sleeve is hydraulically expanded and laser welded at each end. The pressure boundary portion of the tube support plate sleeve is the weld and the sleeve section between the welds. Tubesheet sleeves extend from the tube end to above the top of the tubesheet. Standard and bowed or peripheral tubesheet sleeves can be installed. The upper or free span joint is hydraulically expanded and laser welded. The lower joint is hydraulically expanded and roll expanded. Standard tubesheet sleeves extend from 27" to 36" in length while bowed tubesheet sleeves extend from 30" to 36" in length. The pressure boundary portion of the tubesheet sleeve is the weld and below, down to the tubesheet primary face.

The hydraulic equivalency ratios for the application of normal operating, upset, and accident condition bounding analyses have been evaluated. Design, installation, testing, and inspection of steam generator tube sleeves requires substantially more engineering than plugging, as the tube remains in service. Because of this, the NRC has defined steam generator tube repair to be an Unreviewed Safety Question as described in 10 CFR 50.59(a)(2). As such, other tube repair methods will be submitted under 10 CFR 50.90; and in accordance with 10 CFR 50.91 and 92, the Commission will review the method, issue a significant hazards determination, and amend the facility license accordingly. A 90-day time frame for NRC review and approval is expected.

Technical Specification 4.2.b.5

The repair limit of tubes with degradation attributable to outside diameter stress corrosion cracking contained within the thickness of the tube support plates is conservatively based on the analysis documented in WCAP-12985, "Kewaunee Steam Generator Tube Plugging Criteria for ODSCC at Tube Support Plates" and EPRI Draft Report TR-100407, Rev.1, "PWR Steam Generator Tube Repair Limits - Technical Support Document for Outside Diameter Stress Corrosion Cracking at Tube Support Plates." Application of these criteria is based on limiting primary-to-secondary leakage during a steam line break to ensure the applicable 10 CFR Part 100 limits are not exceeded.

The voltage-based repair limits of TS 4.2.b.5 implement the guidance in Generic Letter 95-05 and are applicable only to Westinghouse-designed steam generators with outside diameter stress corrosion cracking (ODSCC) located at the tube-to-tube support plate intersections. The voltage-based repair limits are not applicable to other forms of tube degradation nor are they applicable to ODSCC that occurs at other locations within the steam generators. Additionally, the repair criteria apply only to indications where the degradation mechanism is predominantly axial ODSCC with no indications extending outside the thickness of the support plate. Refer to GL 95-05 for additional description of the degradation morphology.

Implementation of TS 4.2.b.5 requires a derivation of the voltage structural limit from the burst versus voltage empirical correlation and the subsequent derivation of the voltage repair limit from the structural limit (which is then implemented by this surveillance).

The voltage structural limit is the voltage from the burst pressure/bobbin voltage correlation, at the 95 percent prediction interval curve reduced to account for the lower 95/95 percent tolerance bound for tubing material properties at 650°F (i.e., the 95 percent LTL curve). The voltage structural limit must be adjusted downward to account for potential flaw growth during an operating interval and to account for NDE uncertainty. The upper voltage repair limit, V_{URL} , is determined from the structural voltage limit by applying the following equation:

$$V_{URL} = V_{SL} - V_{GR} - V_{NDE}$$

Where V_{GR} represents the allowance for flaw growth between inspections and V_{NDE} represents the allowance for potential sources of error in the measurement of the bobbin coil voltage. Further discussion of the assumptions necessary to determine the voltage repair limit are discussed in GL 95-05.

The mid-cycle equation should only be used during unplanned inspection in which eddy current data is acquired for indications at the tube support plates.

Technical Specification 4.2.b.6

Tubes with indications of degradation in either the original factory roll expansion in the tubesheet or the unexpanded portion of tube within the tubesheet may be dispositioned for continued service or repaired through application of the F* or EF* criteria. The F* and EF* criteria are described in WCAP-14677⁽⁸⁾. The F* and EF* criteria are established using guidance consistent with RG 1.121. Neither the F* or EF* criteria will significantly contribute to offsite dose following a postulated main steam line break such that contributions from these sources need to be included in offsite dose analyses. Inherent to these criteria is the ability to perform an additional roll expansion of the tube, either as an extension of the original factory roll expansion, in which case F* criteria applies, or in the area starting approximately 4" below the top of the tubesheet, in which case EF* criterion apply. The additional roll expansion procedure can be applied over existing degradation, provided the F* or EF* requirements for non-degraded roll expansion lengths of 1.12" (plus an allowance for NDE uncertainty) and 1.44" (plus an allowance for NDE uncertainty), respectively, are satisfied. The NDE uncertainty applied to the F* and EF* distance is a function of the eddy current probe and technique used. Current state-of-the art inspection technology will be used with implementation of the F* and EF* criteria. The uncertainty in such inspections has been shown to be as small as 0.06", however, for field application, an eddy current uncertainty of 0.20" will be applied. Any and all indications of degradation existing below the F* or EF* distance is acceptable for continued service.

⁽⁸⁾WCAP 14677, F* and Elevated F* Tube Alternate Repair Criteria for Tubes With Degradation Within the Tubesheet Region of the Kewaunee Steam Generators, June 1996 (Proprietary).