

3.8 ELECTRICAL POWER SYSTEMS

3.8.1 AC Sources - Operating

LCO 3.8.1 The following AC electrical sources shall be OPERABLE:

- a. Two qualified circuits between the offsite transmission network and the onsite Class 1E AC Electrical Power Distribution System; and
- b. Four emergency diesel generators (EDGs) capable of supplying the onsite Class 1E power distribution subsystems.

APPLICABILITY: MODES 1, 2, 3, and 4.

ACTIONS

-----NOTE-----
LCO 3.0.4.b is not applicable with two or more EDGs inoperable.

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|------------------------------------|---|---|
| A. One offsite circuit inoperable. | A.1 Perform SR 3.8.1.1 for OPERABLE offsite circuit. | 1 hour |
| | <u>AND</u> | <u>AND</u> |
| | A.2 Declare required feature(s) with no offsite power available inoperable when its redundant feature(s) is inoperable. | Once per 8 hours thereafter |
| | <u>AND</u> | |
| | A.3 Restore offsite circuit to OPERABLE status. | 24 hours from discovery of no offsite power to one division concurrent with inoperability of redundant feature(s) |
| | | 72 hours |

ACTIONS (continued)

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|-------------------------------|---|---|
| <p>B. One EDG inoperable.</p> | <p>B.1 Perform SR 3.8.1.1 for the offsite circuits.</p> | <p>1 hour</p> <p><u>AND</u></p> <p>Once per 8 hours thereafter</p> |
| | <p><u>AND</u></p> <p>B.2 Declare required feature(s) supported by the inoperable EDG inoperable when its required redundant feature(s) is inoperable.</p> | <p>4 hours from discovery of Condition B concurrent with inoperability of redundant required feature(s)</p> |
| | <p><u>AND</u></p> <p>B.3.1 Determine OPERABLE EDGs are not inoperable due to common cause failure.</p> | <p>24 hours</p> |
| | <p><u>OR</u></p> <p>B.3.2 Perform SR 3.8.1.2 for OPERABLE EDGs.</p> | <p>24 hours</p> |
| | <p><u>AND</u></p> <p>B.4 -----NOTE----- Required Action B.4 is not applicable if both EDGs in the same divisional pair are inoperable and Condition C is entered. -----</p> <p>Align the alternate feed from the remaining OPERABLE EDG in the divisional pair.</p> | <p>72 hours</p> |

ACTIONS (continued)

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|-------------------------------------|---|---|
| C. Two EDGs inoperable. | <p>C.1 -----NOTE----- Required Action C.1 is not applicable if both EDGs in the same divisional pair are inoperable. -----</p> <p>Align the alternate feed from the remaining OPERABLE EDG in one divisional pair.</p> <p><u>AND</u></p> <p>C.2 Restore one EDG to OPERABLE status.</p> | <p>2 hours</p> <p>72 hours</p> |
| D. Two offsite circuits inoperable. | <p>D.1 Declare required feature(s) inoperable when its redundant feature(s) is inoperable.</p> <p><u>AND</u></p> <p>D.2 Restore one offsite circuit to OPERABLE status.</p> | <p>12 hours from discovery of Condition D concurrent with inoperability of redundant features</p> <p>24 hours</p> |

ACTIONS (continued)

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|--|---|---------------------------------|
| <p>E. One offsite circuit inoperable.</p> <p><u>AND</u></p> <p>One or two EDGs inoperable.</p> | <p>-----NOTE----- Enter applicable Conditions and Required Actions of LCO 3.8.9, "Distribution Systems - Operating," when condition E is entered with no AC power source to any division. -----</p> <p>E.1 Restore offsite circuit to OPERABLE status.</p> <p><u>OR</u></p> <p>E.2 Restore all EDGs to OPERABLE status.</p> | <p>12 hours</p> <p>12 hours</p> |
| <p>F. Three or more EDGs inoperable.</p> | <p>F.1 Restore to at least two OPERABLE EDGs.</p> | <p>2 hours</p> |
| <p>G. Required Action and associated Completion Time of Condition A, B, C, D, E, or F not met.</p> | <p>G.1 Be in MODE 3.</p> <p><u>AND</u></p> <p>G.2 Be in MODE 5.</p> | <p>6 hours</p> <p>36 hours</p> |
| <p>H. Two offsite circuits and two or more EDGs inoperable.</p> <p><u>OR</u></p> <p>One offsite circuit and three or more EDGs inoperable.</p> | <p>H.1 Enter LCO 3.0.3.</p> | <p>Immediately</p> |

SURVEILLANCE REQUIREMENTS

| SURVEILLANCE | | FREQUENCY |
|--------------|---|-----------|
| SR 3.8.1.1 | Verify correct breaker alignment and indicated power availability for each offsite circuit. | 7 days |
| SR 3.8.1.2 | <p>-----NOTES-----</p> <ol style="list-style-type: none"> All EDG starts may be preceded by an engine prelube period and followed by a warmup period prior to loading. A modified EDG start involving idling and gradual acceleration to synchronous speed may be used for this SR as recommended by the manufacturer. When modified start procedures are not used, the time, voltage, and frequency tolerances of SR 3.8.1.7 must be met. <p>-----</p> <p>Verify each EDG starts from standby conditions and achieves steady state voltage ≥ 6555 V and ≤ 7260 V, and frequency ≥ 58.8 Hz and ≤ 61.2 Hz.</p> | 31 days |
| SR 3.8.1.3 | <p>-----NOTES-----</p> <ol style="list-style-type: none"> EDG loadings may include gradual loading as recommended by the manufacturer. Momentary transients outside the load range do not invalidate this test. This Surveillance shall be conducted on only one EDG at a time. This SR shall be preceded by and immediately follow without shutdown a successful performance of SR 3.8.1.2 or SR 3.8.1.7. <p>-----</p> <p>Verify each EDG is synchronized and loaded and operates for ≥ 60 minutes at a load ≥ 8550 kW and ≤ 9500 kW.</p> | 31 days |

SURVEILLANCE REQUIREMENTS (continued)

| SURVEILLANCE | | FREQUENCY |
|--------------|--|-----------|
| SR 3.8.1.4 | Verify each day tank contains ≥ 700 gal of fuel oil. | 31 days |
| SR 3.8.1.5 | Check for and remove accumulated water from each day tank. | 31 days |
| SR 3.8.1.6 | Verify each fuel oil transfer system operates to automatically transfer fuel oil from storage tank to the day tank. | 31 days |
| SR 3.8.1.7 | <p>-----NOTE-----</p> <p>All EDG starts may be preceded by an engine prelube period.</p> <p>-----</p> <p>Verify each EDG starts from standby condition and achieves:</p> <p>a. In ≤ 15 seconds, voltage ≥ 6555 V and frequency ≥ 58.8 Hz; and</p> <p>b. Steady state voltage ≥ 6555 V and ≤ 7260 V, and frequency ≥ 58.8 Hz and ≤ 61.2 Hz.</p> | 184 days |
| SR 3.8.1.8 | <p>-----NOTE-----</p> <p>[This Surveillance shall not normally be performed in MODE 1 or 2. However, this Surveillance may be performed to reestablish OPERABILITY provided an assessment determines the safety of the plant is maintained or enhanced. Credit may be taken for unplanned events that satisfy this SR.]</p> <p>-----</p> <p>Verify automatic and manual transfer of AC power sources from the normal offsite circuit to the alternate offsite circuit.</p> | 24 months |

SURVEILLANCE REQUIREMENTS (continued)

| SURVEILLANCE | FREQUENCY |
|---|------------------|
| <p>SR 3.8.1.9</p> <p>-----NOTES-----</p> <p>[1. This Surveillance shall not normally be performed in MODE 1 or 2. However, this Surveillance may be performed to reestablish OPERABILITY provided an assessment determines the safety of the plant is maintained or enhanced. Credit may be taken for unplanned events that satisfy this SR.</p> <p>2.] If performed with the EDG synchronized with offsite power, it shall be performed at a power factor ≤ 0.9. However, if grid conditions do not permit, the power factor limit is not required to be met. Under this condition the power factor shall be maintained as close to the limit as practicable.</p> <p>-----</p> <p>Verify each EDG rejects a load greater than or equal to its associated single largest post-accident load, and:</p> <p>a. Following load rejection, the frequency is ≤ 63 Hz;</p> <p>b. Within 3 seconds following load rejection, the voltage is ≥ 6555 V and ≤ 7260 V; and</p> <p>c. Within 3 seconds following load rejection, the frequency is ≥ 58.8 Hz and ≤ 61.2 Hz.</p> | <p>24 months</p> |

SURVEILLANCE REQUIREMENTS (continued)

| SURVEILLANCE | FREQUENCY |
|--|------------------|
| <p>SR 3.8.1.10</p> <p>-----NOTES-----</p> <p>[1. This Surveillance shall not normally be performed in MODE 1 or 2. However, this Surveillance may be performed to reestablish OPERABILITY provided an assessment determines the safety of the plant is maintained or enhanced. Credit may be taken for unplanned events that satisfy this SR.</p> <p>2.] If performed with EDG synchronized with offsite power, it shall be performed at a power factor ≤ 0.9. However, if grid conditions do not permit, the power factor limit is not required to be met. Under this condition the power factor shall be maintained as close to the limit as practicable.</p> <p>-----</p> <p>Verify each EDG does not trip and voltage is maintained ≤ 8280 V during and following a load rejection of ≥ 8550 kW and ≤ 9500 kW.</p> | <p>24 months</p> |

SURVEILLANCE REQUIREMENTS (continued)

| SURVEILLANCE | FREQUENCY |
|---|------------------|
| <p>SR 3.8.1.11</p> <p>-----NOTES-----</p> <ol style="list-style-type: none"> 1. All EDG starts may be preceded by an engine prelube period. 2. This Surveillance shall not normally be performed in MODE 1, 2, 3, or 4. However, portions of the Surveillance may be performed to reestablish OPERABILITY provided an assessment determines the safety of the plant is maintained or enhanced. Credit may be taken for unplanned events that satisfy this SR. <p>-----</p> <p>Verify on an actual or simulated loss of offsite power signal:</p> <ol style="list-style-type: none"> a. De-energization of emergency buses; b. Load shedding from emergency buses; c. Each EDG auto-starts from standby condition, and: <ol style="list-style-type: none"> 1. Energizes permanently connected loads in ≤ 15 seconds; 2. Energizes auto-connected shutdown loads through the Protection System; 3. Maintains steady state voltage ≥ 6555 V and ≤ 7260 V; 4. Maintains steady state frequency ≥ 58.8 Hz and ≤ 61.2 Hz; and 5. Supplies permanently connected and auto-connected shutdown loads for ≥ 5 minutes. | <p>24 months</p> |

SURVEILLANCE REQUIREMENTS (continued)

| SURVEILLANCE | FREQUENCY |
|--|------------------|
| <p>SR 3.8.1.12</p> <p>-----NOTES----- [1.] All EDG starts may be preceded by prelube period. [2. This Surveillance shall not normally be performed in MODE 1 or 2. However, portions of the Surveillance may be performed to reestablish OPERABILITY provided an assessment determines the safety of the plant is maintained or enhanced. Credit may be taken for unplanned events that satisfy this SR.] -----</p> <p>Verify on an actual or simulated Safety Injection System actuation signal each EDG auto-starts from standby condition and:</p> <ul style="list-style-type: none"> a. In ≤ 15 seconds after auto-start and during tests, achieves voltage ≥ 6555 V and frequency ≥ 58.8 Hz; b. Achieves steady state voltage ≥ 6555 V and ≤ 7260 V and frequency ≥ 58.8 Hz and ≤ 61.2 Hz; c. Operates for ≥ 5 minutes; d. Permanently connected loads remain energized from the offsite power system; and e. Emergency loads are energized or autoconnected through the Protection System from the offsite power system. | <p>24 months</p> |

SURVEILLANCE REQUIREMENTS (continued)

| SURVEILLANCE | FREQUENCY |
|--|------------------|
| <p>SR 3.8.1.13</p> <p>-----NOTE----- [This Surveillance shall not normally be performed in MODE 1 or 2. However, this Surveillance may be performed to reestablish OPERABILITY provided an assessment determines the safety of the plant is maintained or enhanced. Credit may be taken for unplanned events that satisfy this SR.] -----</p> <p>Verify each EDG's noncritical automatic trips are bypassed on an actual or simulated Loss of Offsite Power signal on the emergency bus concurrent with an actual or simulated Safety Injection System actuation signal.</p> | <p>24 months</p> |

SURVEILLANCE REQUIREMENTS (continued)

| SURVEILLANCE | FREQUENCY |
|---|------------------|
| <p>SR 3.8.1.14 -----NOTES-----</p> <ol style="list-style-type: none"> 1. Momentary transients outside the load and power factor ranges do not invalidate this test. 2. If performed with EDG synchronized with offsite power, it shall be performed at a power factor ≤ 0.9. However, if grid conditions do not permit, the power factor limit is not required to be met. Under this condition the power factor shall be maintained as close to the limit as practicable. <p>-----</p> <p>Verify each EDG operates for ≥ 24 hours:</p> <ol style="list-style-type: none"> a. For ≥ 2 hours loaded ≥ 9975 kW and $\leq 10,450$ kW; and b. For the remaining hours of the test loaded ≥ 8550 kW and ≤ 9500 kW. | <p>24 months</p> |
| <p>SR 3.8.1.15 -----NOTES-----</p> <ol style="list-style-type: none"> 1. This Surveillance shall be performed within 5 minutes of shutting down the EDG after the EDG has operated ≥ 2 hours loaded ≥ 8550 kW and ≤ 9500 kW. <p>Momentary transients outside of load range do not invalidate this test.</p> <ol style="list-style-type: none"> 2. All EDG starts may be preceded by an engine prelube period. <p>-----</p> <p>Verify each EDG starts and achieves:</p> <ol style="list-style-type: none"> a. In ≤ 15 seconds, voltage ≥ 6555 V and frequency ≥ 58.8 Hz; and b. Steady state voltage ≥ 6555 V, and ≤ 7260 V and frequency ≥ 58.8 Hz and ≤ 61.2 Hz. | <p>24 months</p> |

SURVEILLANCE REQUIREMENTS (continued)

| SURVEILLANCE | FREQUENCY |
|--|------------------|
| <p>SR 3.8.1.16</p> <p>-----NOTE----- This Surveillance shall not normally be performed in MODE 1, 2, 3, or 4. However, this Surveillance may be performed to reestablish OPERABILITY provided an assessment determines the safety of the plant is maintained or enhanced. Credit may be taken for unplanned events that satisfy this SR. -----</p> <p>Verify each EDG:</p> <ul style="list-style-type: none"> a. Synchronizes with offsite power source while loaded with emergency loads upon a simulated restoration of offsite power; b. Transfers loads to offsite power source; and c. Returns to ready-to-load operation. | <p>24 months</p> |
| <p>SR 3.8.1.17</p> <p>-----NOTE----- This Surveillance shall not normally be performed in MODE 1, 2, 3, or 4. However, portions of the Surveillance may be performed to reestablish OPERABILITY provided an assessment determines the safety of the plant is maintained or enhanced. Credit may be taken for unplanned events that satisfy this SR. -----</p> <p>Verify, with a EDG operating in test mode and connected to its bus, an actual or simulated Safety Injection System actuation signal overrides the test mode by:</p> <ul style="list-style-type: none"> a. Returning EDG to ready-to-load operation; and b. Automatically energizing the emergency loads from offsite power. | <p>24 months</p> |

SURVEILLANCE REQUIREMENTS (continued)

| SURVEILLANCE | FREQUENCY |
|---|------------------|
| <p>SR 3.8.1.18</p> <p>-----NOTES-----</p> <ol style="list-style-type: none"> 1. All EDG starts may be preceded by an engine prelube period. 2. This Surveillance shall not normally be performed in MODE 1, 2, 3, or 4. However, portions of the Surveillance may be performed to reestablish OPERABILITY provided an assessment determines the safety of the plant is maintained or enhanced. Credit may be taken for unplanned events that satisfy this SR. <p>-----</p> <p>Verify on an actual or simulated loss of offsite power signal in conjunction with an actual or simulated Safety Injection System actuation signal:</p> <ol style="list-style-type: none"> a. De-energization of emergency buses; b. Load shedding from emergency buses; and c. Each EDG auto-starts from standby condition; and: <ol style="list-style-type: none"> 1. Energizes permanently connected loads in ≤ 15 seconds; 2. Energizes auto-connected emergency loads through the Protection System; 3. Achieves steady state voltage ≥ 6555 V and ≤ 7260 V; 4. Achieves steady state frequency ≥ 58.8 Hz and ≤ 61.2 Hz; and 5. Supplies permanently connected and auto-connected emergency loads for ≥ 5 minutes. | <p>24 months</p> |

SURVEILLANCE REQUIREMENTS (continued)

| SURVEILLANCE | FREQUENCY |
|---|-----------------|
| <p>SR 3.8.1.19</p> <p>-----NOTE----- All EDG starts may be preceded by an engine prelube period. -----</p> <p>Verify, when started simultaneously from standby condition, each EDG achieves:</p> <ul style="list-style-type: none"> a. In ≤ 15 seconds, voltage ≥ 6555 V and frequency ≥ 58.8 Hz; and b. Steady state voltage ≥ 6555 V and ≤ 7260 V, and frequency ≥ 58.8 Hz and ≤ 61.2 Hz. | <p>10 years</p> |

3.8 ELECTRICAL POWER SYSTEMS

3.8.2 AC Sources - Shutdown

LCO 3.8.2 The following AC electrical power sources shall be OPERABLE:

- a. One qualified circuit between the offsite transmission network and the onsite Class 1E AC electrical power distribution subsystem(s) required by LCO 3.8.10, "Distribution Systems - Shutdown"; and
- b. Two emergency diesel generators (EDGs) in one divisional pair capable of supplying the onsite Class 1E power distribution subsystem(s) required by LCO 3.8.10.

APPLICABILITY: MODES 5 and 6,
During movement of irradiated fuel assemblies.

ACTIONS

-----NOTE-----
LCO 3.0.3 is not applicable.

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|---|---|-----------------|
| A. One required offsite circuit inoperable. | <p>-----NOTE----- Enter applicable Conditions and Required Actions of LCO 3.8.10, with one required division de-energized as a result of Condition A.</p> <hr/> <p>A.1 Declare affected feature(s) with no offsite power available inoperable.</p> <p><u>OR</u></p> | Immediately |

ACTIONS (continued)

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|--|---|--|
| | <p>A.2.1 Suspend movement of irradiated fuel assemblies.</p> <p><u>AND</u></p> <p>A.2.2 Suspend operations involving positive reactivity additions that could result in loss of required SDM or boron concentration.</p> <p><u>AND</u></p> <p>A.2.3 Initiate action to restore required offsite power circuit to OPERABLE status.</p> | <p>Immediately</p> <p>Immediately</p> <p>Immediately</p> |
| <p>B. One or two required EDGs inoperable.</p> | <p>B.1 Suspend movement of irradiated fuel assemblies.</p> <p><u>AND</u></p> <p>B.2 Suspend operations involving positive reactivity additions that could result in loss of required SDM or boron concentration.</p> <p><u>AND</u></p> <p>B.3 Initiate action to restore required EDGs to OPERABLE status.</p> | <p>Immediately</p> <p>Immediately</p> <p>Immediately</p> |

SURVEILLANCE REQUIREMENTS

| SURVEILLANCE | FREQUENCY |
|--|--|
| <p>SR 3.8.2.1</p> <p>-----NOTE-----</p> <p>The following SRs are not required to be performed: SR 3.8.1.3, SR 3.8.1.9 through SR 3.8.1.11, SR 3.8.1.13 through SR 3.8.1.16.</p> <p>-----</p> <p>For AC sources required to be OPERABLE, the SRs of Specification 3.8.1, "AC Sources - Operating," except SR 3.8.1.8, SR 3.8.1.12, SR 3.8.1.17, SR 3.8.1.18, and SR 3.8.1.19, are applicable.</p> | <p>In accordance with applicable SRs</p> |

3.8 ELECTRICAL POWER SYSTEMS

3.8.3 Diesel Fuel Oil, Lubricating Oil, and Starting Air

LCO 3.8.3 The diesel fuel oil, lubricating oil, and starting air systems shall be within limits for each emergency diesel generator (EDG).

APPLICABILITY: When associated EDG is required to be OPERABLE.

ACTIONS

-----NOTE-----
Separate Condition entry is allowed for each EDG.

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|--|--|-----------------|
| A. One or more EDGs with fuel level < 95,000 gal and > 80,000 gal in storage tank. | A.1 Restore fuel oil level to within limits. | 48 hours |
| B. One or more EDGs with lubricating oil inventory < 750 gal and > 635 gal. | B.1 Restore lubricating oil inventory to within limits. | 48 hours |
| C. One or more EDGs with diesel fuel oil total particulates not within limit. | C.1 Restore diesel fuel oil total particulates to within limits. | 7 days |
| D. New diesel fuel oil properties not within limits. | D.1 Restore new diesel fuel oil properties to within limits. | 30 days |

ACTIONS (continued)

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|---|---|-----------------|
| E. One or more EDGs with starting air receiver pressure < 435 psig and ≥ 220 psig. | E.1 Restore starting air receiver pressure to ≥ 435 psig. | 48 hours |
| F. Required Action and associated Completion Time of Condition A, B, C, D, or E not met. <u>OR</u> One or more EDGs with diesel fuel oil, lubricating oil, or starting air subsystem not within limits for reasons other than Condition A, B, C, D, or E. | F.1 Declare associated EDG inoperable. | Immediately |

SURVEILLANCE REQUIREMENTS

| SURVEILLANCE | FREQUENCY |
|---|--|
| SR 3.8.3.1 Verify each diesel fuel oil storage tank contains ≥ 95,000 gal of fuel. | 31 days |
| SR 3.8.3.2 Verify each EDG lubricating oil inventory is ≥ 750 gal. | 31 days |
| SR 3.8.3.3 Verify diesel fuel oil properties of new and stored diesel fuel oil are tested in accordance with, and maintained within the limits of, the Diesel Fuel Oil Testing Program. | In accordance with the Diesel Fuel Oil Testing Program |

SURVEILLANCE REQUIREMENTS (continued)

| SURVEILLANCE | | FREQUENCY |
|--------------|--|-----------|
| SR 3.8.3.4 | Verify each EDG starting air receiver pressure is ≥ 435 psig. | 31 days |
| SR 3.8.3.5 | Check for and remove accumulated water from each diesel fuel oil storage tank. | 92 days |

3.8 ELECTRICAL POWER SYSTEMS

3.8.4 DC Sources - Operating

LCO 3.8.4 Four DC electrical power divisions shall be OPERABLE.

APPLICABILITY: MODES 1, 2, 3, and 4.

ACTIONS

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|--|---|-------------------|
| A. One required battery charger inoperable. | A.1 Restore battery terminal voltage to greater than or equal to the minimum established float voltage. | 2 hours |
| | <u>AND</u> | |
| | A.2 Verify battery float current ≤ 2 amps. | Once per 12 hours |
| | <u>AND</u> | |
| | A.3 Restore required battery charger to OPERABLE status. | 72 hours |
| B. One battery inoperable. | B.1 Restore battery to OPERABLE status. | 2 hours |
| C. One DC electrical power subsystem inoperable for reasons other than Condition A or B. | C.1 Restore DC electrical power subsystem to OPERABLE status. | 2 hours |

ACTIONS (continued)

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|--|---------------------------------|-----------------|
| D. Required Action and Associated Completion Time not met. | D.1 Be in MODE 3. | 6 hours |
| | <u>AND</u> D.2 Be in MODE 5. | 36 hours |

SURVEILLANCE REQUIREMENTS

| SURVEILLANCE | | FREQUENCY |
|--------------|--|-----------|
| SR 3.8.4.1 | Verify battery terminal voltage is greater than or equal to the minimum established float voltage. | 7 days |
| SR 3.8.4.2 | <p>Verify each required battery charger supplies ≥ 400 amps at greater than or equal to the minimum established float voltage for ≥ 8 hours.</p> <p><u>OR</u></p> <p>Verify each required battery charger can recharge the battery to the fully charged state within 24 hours while supplying the largest combined demands of the various continuous steady state loads, after a battery discharge to the bounding design basis event discharge state.</p> | 24 months |

SURVEILLANCE REQUIREMENTS (continued)

| SURVEILLANCE | FREQUENCY |
|---|------------------|
| <p>SR 3.8.4.3</p> <p>-----NOTES-----</p> <ol style="list-style-type: none"> 1. The modified performance discharge test in SR 3.8.6.6 may be performed in lieu of SR 3.8.4.3. 2. This Surveillance shall not normally be performed in MODE 1, 2, 3, or 4. However, portions of the Surveillance may be performed to reestablish OPERABILITY provided an assessment determines the safety of the plant is maintained or enhanced. Credit may be taken for unplanned events that satisfy this SR. <p>-----</p> <p>Verify battery capacity is adequate to supply, and maintain in OPERABLE status, the required emergency loads for the design duty cycle when subjected to a battery service test.</p> | <p>24 months</p> |

3.8 ELECTRICAL POWER SYSTEMS

3.8.5 DC Sources - Shutdown

LCO 3.8.5 Class 1E DC subsystem(s) shall be OPERABLE to support the DC electrical power distribution subsystem(s) required by LCO 3.8.10, "Distribution Systems - Shutdown."

APPLICABILITY: MODES 5 and 6,
During movement of irradiated fuel assemblies.

ACTIONS

-----NOTE-----
LCO 3.0.3 is not applicable.

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|--|---|-------------------|
| A. One required battery charger inoperable. | A.1 Restore battery terminal voltage to greater than or equal to the minimum established float voltage. | 2 hours |
| | <u>AND</u> | |
| | A.2 Verify battery float current ≤ 2 amps. | Once per 12 hours |
| | <u>AND</u> | |
| | A.3 Restore required battery charger to OPERABLE status. | 72 hours |
| B. One or more required DC electrical power subsystems inoperable for reasons other than Condition A. <u>OR</u> | B.1 Declare affected required feature(s) inoperable. <u>OR</u> | Immediately |

ACTIONS (continued)

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|--|---|--------------------|
| <p>Required Actions and associated Completion Time of Condition A not met.</p> | <p>B.2.1 Suspend movement of irradiated fuel assemblies.</p> <p><u>AND</u></p> | <p>Immediately</p> |
| | <p>B.2.2 Suspend operations involving positive reactivity additions that could result in loss of required SDM or boron concentration.</p> <p><u>AND</u></p> | <p>Immediately</p> |
| | <p>B.2.3 Initiate action to restore required DC subsystem(s) to OPERABLE status.</p> | <p>Immediately</p> |

SURVEILLANCE REQUIREMENTS

| SURVEILLANCE | FREQUENCY |
|--|--|
| <p>SR 3.8.5.1 -----NOTE----- The following SRs are not required to be performed: SR 3.8.4.2 and SR 3.8.4.3. -----</p> <p>For DC subsystems required to be OPERABLE, the following SRs are applicable:</p> <p>SR 3.8.4.1 SR 3.8.4.2 SR 3.8.4.3</p> | <p>In accordance with applicable SRs</p> |

3.8 ELECTRICAL POWER SYSTEMS

3.8.6 Battery Parameters

LCO 3.8.6 Battery parameters for Divisions 1, 2, 3, and 4 batteries shall be within limits.

APPLICABILITY: When associated Class 1E DC subsystems are required to be OPERABLE.

ACTIONS

-----NOTE-----
Separate Condition entry is allowed for each battery.

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|---|---|-----------------|
| A. One battery with one or more battery cells float voltage < 2.07 V. | A.1 Perform SR 3.8.4.1. | 2 hours |
| | <u>AND</u> | |
| | A.2 Perform SR 3.8.6.1. | 2 hours |
| | <u>AND</u> | |
| | A.3 Restore affected cell voltage ≥ 2.07 V. | 24 hours |
| B. One battery with float current > 2 amps. | B.1 Perform SR 3.8.4.1. | 2 hours |
| | <u>AND</u> | |
| | B.2 Restore battery float current to ≤ 2 amps. | 12 hours |

ACTIONS (continued)

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|--|---|---|
| <p>-----NOTE----- Required Action C.2 shall be completed if electrolyte level was below the top of plates. -----</p> <p>C. One battery with one or more cells electrolyte level less than minimum established design limits.</p> | <p>-----NOTE----- Required Actions C.1 and C.2 are only applicable if electrolyte level was below the top of plates. -----</p> <p>C.1 Restore electrolyte level to above top of plates. <u>AND</u> C.2 Verify no evidence of leakage. <u>AND</u> C.3 Restore electrolyte level to greater than or equal to minimum established design limits.</p> | <p>8 hours</p> <p>12 hours</p> <p>31 days</p> |
| <p>D. One battery with pilot cell electrolyte temperature less than minimum established design limits.</p> | <p>D.1 Restore battery pilot cell temperature to greater than or equal to minimum established design limits.</p> | <p>12 hours</p> |
| <p>E. One battery in two or more divisions with battery parameters not within limits.</p> | <p>E.1 Restore battery parameters for batteries in all but one division to within limits.</p> | <p>2 hours</p> |

ACTIONS (continued)

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|---|---|--------------------|
| <p>F. Required Action and associated Completion Time of Condition A, B, C, D, or E not met.</p> <p><u>OR</u></p> <p>One battery with one or more battery cells float voltage < 2.07 V and float current > 2 amps.</p> | <p>F.1 Declare associated battery inoperable.</p> | <p>Immediately</p> |

SURVEILLANCE REQUIREMENTS

| SURVEILLANCE | FREQUENCY |
|--|----------------|
| <p>SR 3.8.6.1 -----NOTE----- Not required to be met when battery terminal voltage is less than the minimum established float voltage of SR 3.8.4.1. ----- Verify each battery float current is \leq 2 amps.</p> | <p>7 days</p> |
| <p>SR 3.8.6.2 Verify each battery pilot cell float voltage is \geq 2.07 V.</p> | <p>31 days</p> |
| <p>SR 3.8.6.3 Verify each battery connected cell electrolyte level is greater than or equal to minimum established design limits.</p> | <p>31 days</p> |
| <p>SR 3.8.6.4 Verify each battery pilot cell temperature is greater than or equal to minimum established design limits.</p> | <p>31 days</p> |

SURVEILLANCE REQUIREMENTS (continued)

| SURVEILLANCE | FREQUENCY |
|--|---|
| SR 3.8.6.5 Verify each battery connected cell float voltage is ≥ 2.07 V. | 92 days |
| SR 3.8.6.6 -----NOTE----- This Surveillance shall not be performed in MODE 1, 2, 3, or 4. However, portions of the Surveillance may be performed to reestablish OPERABILITY provided an assessment determines the safety of the plant is maintained or enhanced. Credit may be taken for unplanned events that satisfy this SR. ----- Verify battery capacity is $\geq 80\%$ of the manufacturer's rating when subjected to a performance discharge test or a modified performance discharge test. | 60 months <u>AND</u> 12 months when battery shows degradation, or has reached 85% of the expected life with capacity < 100% of manufacturer's rating <u>AND</u> 24 months when battery has reached 85% of the expected life with capacity $\geq 100\%$ of manufacturer's rating |

3.8 ELECTRICAL POWER SYSTEMS

3.8.7 Inverters - Operating

LCO 3.8.7 Divisions 1, 2, 3, and 4 inverters shall be OPERABLE.

APPLICABILITY: MODES 1, 2, 3, and 4.

ACTIONS

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|--|--|-----------------|
| A. One inverter inoperable. | <p>A.1 -----NOTE----- Enter applicable Conditions and Required Actions of LCO 3.8.9, "Distribution Systems - Operating," with any AC vital bus de-energized. -----</p> <p>Restore inverter to OPERABLE status.</p> | 24 hours |
| B. Required Action and associated Completion Time not met. | B.1 Be in MODE 3. | 6 hours |
| | <u>AND</u> B.2 Be in MODE 5. | 36 hours |

SURVEILLANCE REQUIREMENTS

| SURVEILLANCE | FREQUENCY |
|--|-----------|
| SR 3.8.7.1 Verify correct inverter voltage, frequency, and alignment to required AC vital buses. | 7 days |

3.8 ELECTRICAL POWER SYSTEMS

3.8.8 Inverters - Shutdown

LCO 3.8.8 Inverters shall be OPERABLE to support the onsite Class 1E AC vital bus electrical power distribution subsystem(s) required by LCO 3.8.10, "Distribution Systems - Shutdown."

APPLICABILITY: MODES 5 and 6,
During movement of irradiated fuel assemblies.

ACTIONS

-----NOTE-----
LCO 3.0.3 is not applicable.

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|--------------------------------------|--|-----------------|
| A. One or more inverters inoperable. | A.1 Declare affected required feature(s) inoperable. | Immediately |
| | <u>OR</u> | |
| | A.2.1 Suspend movement of irradiated fuel assemblies. | Immediately |
| | <u>AND</u> | |
| | A.2.2 Suspend operations involving positive reactivity additions that could result in loss of required SDM or boron concentration. | Immediately |
| | <u>AND</u> | |
| | A.2.3 Initiate action to restore inverter(s) to OPERABLE status. | Immediately |

SURVEILLANCE REQUIREMENTS

| SURVEILLANCE | | FREQUENCY |
|--------------|--|-----------|
| SR 3.8.8.1 | Verify correct inverter voltage, frequency, and alignments to required AC vital buses. | 7 days |

3.8 ELECTRICAL POWER SYSTEMS

3.8.9 Distribution Systems - Operating

LCO 3.8.9 Divisions 1, 2, 3, and 4 AC, DC, and AC Vital electrical power distribution subsystems shall be OPERABLE.

APPLICABILITY: MODES 1, 2, 3, and 4.

ACTIONS

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|---|--|-----------------|
| <p>A. One or more AC electrical power distribution subsystems inoperable.</p> | <p>-----NOTE----- Enter applicable Conditions and Required Actions of LCO 3.8.4, "DC Sources - Operating," for DC trains made inoperable by inoperable power distribution subsystems. -----</p> <p>A.1 Restore AC electrical power distribution subsystem(s) to OPERABLE status.</p> | <p>8 hours</p> |
| <p>B. One or more AC vital electrical power distribution subsystems inoperable.</p> | <p>B.1 Restore AC vital electrical power distribution subsystem(s) to OPERABLE status.</p> | <p>2 hours</p> |
| <p>C. One or more DC electrical power distribution subsystems inoperable.</p> | <p>C.1 Restore DC electrical power distribution subsystem(s) to OPERABLE status.</p> | <p>2 hours</p> |

ACTIONS (continued)

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|---|--|-------------------------|
| D. Required Action and associated Completion Time of Condition A, B, or C not met. | D.1 Be in MODE 3. <u>AND</u> D.2 Be in MODE 5. | 6 hours 36 hours |
| E. Two or more electrical power distribution subsystems inoperable that results in a loss of safety function. | E.1 Enter LCO 3.0.3. | Immediately |

SURVEILLANCE REQUIREMENTS

| SURVEILLANCE | FREQUENCY |
|---|-----------|
| SR 3.8.9.1 Verify correct breaker alignments and voltage to required AC, DC, and AC vital electrical power distribution subsystems. | 7 days |

3.8 ELECTRICAL POWER SYSTEMS

3.8.10 Distribution Systems - Shutdown

LCO 3.8.10 The necessary portions of the AC, DC, and AC vital electrical power distribution subsystems shall be OPERABLE to support equipment required to be OPERABLE.

APPLICABILITY: MODES 5 and 6,
During movement of irradiated fuel assemblies.

ACTIONS

-----NOTE-----
LCO 3.0.3 is not applicable.

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|--|--|-----------------|
| A. One or more required AC, DC, or AC vital electrical power distribution subsystems inoperable. | A.1 Declare associated supported required feature(s) inoperable. <u>OR</u> | Immediately |
| | A.2.1 Suspend movement of irradiated fuel assemblies. <u>AND</u> | Immediately |
| | A.2.2 Suspend operations involving positive reactivity additions that could result in loss of required SDM or boron concentration. <u>AND</u> | Immediately |

ACTIONS (continued)

| CONDITION | REQUIRED ACTION | COMPLETION TIME |
|-----------|---|--|
| | <p>A.2.3 Initiate actions to restore required AC, DC, and AC vital electrical power distribution subsystem(s) to OPERABLE status.</p> <p><u>AND</u></p> <p>A.2.4 Declare associated required residual heat removal loop(s) inoperable and not in operation.</p> | <p>Immediately</p> <p>Immediately</p> |

SURVEILLANCE REQUIREMENTS

| SURVEILLANCE | FREQUENCY |
|---|---------------|
| <p>SR 3.8.10.1 Verify correct breaker alignments and voltage to required AC, DC, and AC vital electrical power distribution subsystems.</p> | <p>7 days</p> |