

3.8 ELECTRICAL POWER SYSTEMS

3.8.5 DC Sources - Shutdown

LCO 3.8.5 The following DC electrical power subsystems shall be OPERABLE:

- a. One Division 1 or Division 2 DC electrical power subsystem; and
- b. The Division 3 DC electrical power subsystem, when the Division 3 onsite Class 1E DC electrical power distribution subsystem is required by LCO 3.8.9, "Distribution System – Shutdown."

APPLICABILITY: MODES 4 and 5,
During movement of irradiated fuel assemblies in the secondary containment,

ACTIONS

-----NOTE-----

LCO 3.0.3 is not applicable.

CONDITION	REQUIRED ACTION	COMPLETION TIME
A. One or more required DC electrical power subsystems inoperable.	A.1 Declare affected required feature(s) inoperable.	Immediately
	<p style="text-align: center;"><u>OR</u></p> A.2.1 Suspend CORE ALTERATIONS.	Immediately
	<p style="text-align: center;"><u>AND</u></p> A.2.2 Suspend movement of irradiated fuel assemblies in the secondary containment.	Immediately
<u>AND</u>		(continued)