



REFERENCE DRAWINGS & CALCULATIONS:
 FLOW DIAGRAM LEGEND & SYMBOLS HBR2-7863LR
 SERVICE WATER SYSTEM SCREENING CALC. RNP-L/LR-8137

CALC. RNP-L/LR-8121
 ATTACHMENT 5
 REV. 1
 PAGE 4 OF 10

INITIAL ISSUE AS REVISION 58.	CARDINAL POWER & LIGHT CO 1100 S. BRIDGES BLVD. CHICAGO, ILL. 60606 (773) 399-1000 FAX (773) 399-1001 WWW.CPL.COM
SERVICE & COOLING WATER SYSTEM FLOW DIAGRAM	
PROJECT NO. G-198199LR SHEET NO. 4 OF 13	

D-10