INITIAL SUBMISSION OF THE SCENARIOS

FOR THE PALISADES EXAMINATION - DECEMBER 2001

(I)

Appendix D			Simulator Scenario Outline FORM ES-D-1 (R8, S1)					
Facility:	Facility: PALISADES Scenario No.: Spare Op-Test No.:							
Examiners	Operators							
Initial Cond	ditions:	IC-19; Appro P-55A with C Option 1 ope	eximately 100% power EOL; Equipment OOS is Charging Pump aution Tag hung on handswitch; Charging System is aligned for ration with P-55B in MANUAL and P-55C in AUTO.					
Turnover:	 Turnover: Power is 100% at EOL. Charging Pump P-55A is out of service for repairs with the Charging System aligned for Option 1 operations and CV-2004 closed. PCS Boron concentration is 50 ppm; ASI is +0.02; S/G B/D @ 20K ea.; Off-gas is ~2 scfm; equilibrium Xenon. Shift orders are to lower power to 60% load at 20% per hour to allow taking Main Feedwater Pump P-1B out-of-service due to elevated seal leakage conditions. 							
Event No.	Malf. No.	Event Type*	Event Description					
1	RX07B	RO (I)	Pressurizer Level Control Channel B Upscale Demand					
2	RX12C	SRO (İ)	Pressurizer Heater Groups Fail OFF (Backup Gp. 1&2) (IPE)					
3	N/A	RO (R) TURB (N) SRO (N)	Downpower Ramp					
4	RX14A	TURB (I) SRO (I)	Feedwater Flow Transmitter FT-0701 Fail HIGH					
5	TC04C	TURB (C) SRO (C)	Turbine Governor Valve GV 3 Fails Shut					
6	RP19	RO (C) SRO (C)	Failure of the Reactor to Automatically Trip					
7	MS03A	RO (M) TURB (M) SRO (M)	Main Steamline Rupture Inside of the Containment					
8	CH05A/B	RO (C) TURB (C) SRO (C)	Initiation Failure of Containment Isolation, Safety Injection, and Containment Spray					

* (N)ormal, (R)eactivity, (I)nstrument, (C)omponent, (M)ajor

palisades nuclear plant

ø

o

Simulator Operator Instructions for Scenario: SPARE

Event Number	Simulator Operator Actions			
	IC-19; Approximately 100% power EOL			
CONDITIONS	Equipment OOS is Charging Pump P-55A with Caution Tag hung on hand switch; Charging System is aligned for Option 1 operation with P-55B in MANUAL and P-55C n AUTO. P-55B Control Select to Manual P-55C Control Select to Auto Start P-55B with Control Switch Stop P-55A with Control Switch Place CV-2004 in Close Remote CV32, P-55A, Rackout Malfunction for Event 6 ACTIVE AT SETUP MALF RP19 OVRD DI REACTOR_TRIP to OFF Malfunction for Event 8 ACTIVE AT SETUP.			
1**	MALF RX07B Activate Event #1 and Event #2 simultaneously			
2**	MALF RX12C Activate Event #1 and Event #2 simultaneously			
	OVERRIDE GREEN lights OFF for Heater Groups #1 and #2			
3	NONE			
4	MALF RX14A, Severity = 100%			
5	MALF TC04C			
6	Malfunction for Event 6 ACTIVE AT SETUP • MALF RP19 • OVRD DI REACTOR_TRIP to OFF			
7	MALF MS03A, Severity = 15%, Ramp = 10 minutes			
8	Malfunction for Event 8 ACTIVE AT SETUP. • MALF CHO5A and CHO5B			

** Events #1 and #2 should be activated at the same time.

SHIFT TURNOVER - SCENARIO: SPARE

Power is 100% at EOL.

.

Charging Pump P-55A is out of service for repairs with the Charging System aligned for Option 1 operations and CV-2004 closed.

PCS Boron concentration is 50 ppm; ASI is +0.02; S/G B/D @ 20K ea.; Off-gas is ~2 scfm; equilibrium Xenon.

Shift orders are to lower power to 60% load at 20% per hour to allow taking Main Feedwater Pump P-1B out-of-service due to elevated seal leakage conditions

.

Appendix D **Operator Actions** FORM ES-D-2 (R8, S1) Op-Test No.: Scenario No.: SPARE Event No.: 1 Page of Event Description: Pressurizer Level Control Channel B Upscale Demand Time Position Applicant's Actions or Behavior Diagnose low failure of Pressurizer Level Transmitter LT-0101B · Pressurizer Level Control 'B' output demand high Pressurizer Level Indication LI-0101B failed low • EK-07-61, PRESSURIZER LEVEL HI-LO, alarm RO • EK-07-63, PRESSURIZER LEVEL CH "A" LO-LO, alarm • Various other alarms · Letdown Orifice Stop Valves closed · Pressurizer Heaters off Actual Pressurizer level rising SRO Enters and directs the actions of ARP-4 (EK-07) Takes manual control of Pressurizer Level controller OR selects Channel 'A' as controlling channel RO CRITICAL TASK to obtain control of pressurizer level prior to vct low-low level causing a charging pump suction swapover to the SIRW tank. Restores Pressurizer level to program value and regains heater control by RO selecting 'Channel A' on LIC-0101, Heater Control Select SRO Contact maintenance to initiate troubleshooting and repairs.

Appendi	k D	Operator Actions FORM ES-D-2 (R8, S1					
	+ No :						
op-res	LINU	Scenario No.: SPARE Event No.: 2 Page of					
Event D	escription:	Pressurizer Backup Heater Groups #1 and #2 Fail OFF (IPE)					
Time	Position	Applicant's Actions or Behavior					
		<i>NOTE: This malfunction should be activated at the same time that EVENT 1 is activated.</i>					
		Diagnoses tripped supply breaker for Backup heater Group #1 and #2					
	 RO Indication on Group #1 and #2 heaters Lower than normal current on heater current indication Slower pressure recovery following depressurization on previous even 						
	SRO Consults Tech Spec 3.4.9 to determine required current = 91 amps determines a 72 hour completion time.						
	SRO	Initiates troubleshooting and repair.					

Appendix D		Operator Actions FORM ES-D-2 (R8, S	1)
			=
Op-Tes	t No.:	Scenario No.: SPARE Event No.: 3 Page of	
Event D	escription:	Downpower Ramp	
	1		
Time	Position	Applicant's Actions or Behavior	
	SRO	Enters and directs the actions of GOP-8.	
	SRO	Reviews Precautions and Limitations with crew.	
	SRO	Notifies Area Power Control and Chemistry of impending shutdown.	
	SRO	Evaluate PCS leak rate surveillance interval.	
			-
		Establish "Power Operation Degas Lineup" (SOP-2A, Section 7.13, "Degas Of PCS")	
	SRO	NOTE: Not required since plant is not being taken off line.	

Appendix	(D	Operator Actions FORM ES-D-2 (R8, S1					
Op-Test No.:		Scenario No.: SPARE Event No.: 3 Page of					
Event D	escription:	Downpower Ramp					
Time	Position	Applicant's Actions or Behavior					
	SRO	 Evaluate ASI guidelines (EM-04-17, "Axial Shape Index (ASI) Control") For an unplanned rapid power reduction, the operator need not worry about maintaining ASI within Target ASI ± 0.05 during the power reduction Initiate trending of ASI Power reduction should be initiated by boration 					
	RO Commence boration of PCS (SOP-2A, Section 7.5.1, "Boration" • Determine required amount of boron • Establish boration flow • Maintain boron concentration to ensure regulating rods above						
	If Reactor power changes by 15% or more in one hour or less, the SRO Chemistry to perform an isotopic analysis for iodine						
	BOP Adjust Valve Position Limiter to maintain Limiter just above v signal						
	NOTE: Next event should be entered once power has been lowered approximately 3-5%.						

Appendix D		Operator Actions FORM ES-D-2 (R8, S1				
Op-Test No.: Event Description:		Scenario No.: SPARE Event No.: 4 Page of Feedwater Flow Transmitter FT-0701 Failure High				
Time	Position	Applicant's Actions or Behavior				
	ВОР	 Diagnose high failure of Feedwater Flow Transmitter FT-0701 LIC-0701 demand goes low Recorder FI-0701 feed flow goes high SG 'A' level lowers EK-09-62, STEAM GEN E-50A LO LEVEL, alarm 				
	SRO	Enters and directs the actions of ARP-5 (EK-00) and ONP-3.0.				
	Takes manual control of FRV-0701 using LIC-0701BOPCRITICAL TASK to take manual control of FRV and gain control before low SG level reactor trip.					
	BOP Slowly raise S/G level using manual control of FRV-0701 to restore le					
	SRO	Contact maintenance to initiate troubleshooting and repairs.				

Appendi	< D	Operator Actions FORM ES-D-2 (R8, S1)
Op-Test No.: Event Description:		Scenario No.: SPARE Event No.: 5 Page of Turbine Governor Valve GV 3 Fails Shut
Time	Position	Applicant's Actions or Behavior
	TURB	Diagnoses turbine control valve GV-3 failing shut • EK-0318, TURBINE PANEL TROUBLE, alarms • Indication on DEH panel • Load lowering • Steam pressure rising • PCS temperature rising • Reactor power lowering
	SRO	If time permits, enter and direct the actions of ONP-1, Loss of Load.
	RO	Insert control rods to match Tave to Tref as time permits (Immediate Action of ONP-1).
	TURB	Ensures Turbine Controls in MANUAL
	TURB	Ensures at least one EHC pump running.
	SRO	Orders reactor trip due to being above 15% power CRITICAL TASK to order reactor tripped per procedure and to prevent PCS overpressure.

Appendix D		Operator Actions FORM ES-D-2 (R8, S1)			
Op-Test No.: Event Description:		Scenario No.: SPARE Event No.: 5 Page of Turbine Governor Valve GV 3 Fails Shut			
Time Position Applicant's Actions or Behavior					
	RO	Trips the reactor as directed.			
	SRO	Enters and directs the actions of EOP-1.0.			
	RO	Determines that Reactivity Control acceptance criteria are met.			
BOP Control the Feedwater System • Places ALL operating MFPs to manual and ramp one to minimum spectron of the Feedwater System • As Tave lowers toward 525°F ramps second MFP to minimum spectron • Closes ALL MFRVs and Bypass FRVs CRITICAL TASK to prevent PCS overcooling.					
	BOP	Determines that Vital Auxiliaries - Electric acceptance criteria are met.			
	RO	Determines that PCS Inventory Control acceptance criteria are met.			
	RO	Determines that PCS Pressure Control acceptance criteria are met.			

¢

٠

e:

Appendix D		Operator Actions			FORM ES-D-2 (R8, S1		
Op-Test No.: Event Description:		Scenario No.: Spare Even	nt No.:	5	Page	of	
Time	Position	Behavior					
	RO	Determines that Core Heat Removal acceptance	e criteria ar	re met.			
	ВОР	Determines that PCS Heat Removal acceptance	criteria ar	e met.			
	RO Determines that Containment Isolation acceptance criteria are n						
	RO	Determines that Containment Atmosphere acceptance criteria are met.					
	RO Determines that Vital Auxiliaries - Water acceptance criteria are met.						
	RO	Determines that Vital Auxiliaries - Air acceptance	e criteria ar	e met.			

o

Appendix	(D	Оре	erator Actions		FORM	ES-D-2 (F	<u>8, S1</u>
Op-Tes	t No.:	Scenario No.:	Spare	Event No.:	5	Page	of
Event D	escription:	Turbine Governor Va	lve GV 3 Fai	ls Shut			
Time	Position		Applicant's A	ctions or Behavior			
	BOP	Verify at least one Conder operating.	ısat Pump ar	nd at least one Coo	ling Tower	Pump	
	BOP	Commence Emergency SI	hutdown Che	ecklist (GOP-10)			
	SRO	Refers to Attachment 1, "E	Event Diagnos	stic Flow Chart" and	d diagnose	es the eve	ent.
	SRO	Transition to EOP-2.0, "Reactor Trip Recovery" due to all safety function acceptance criteria met, and Control Room is habitable.					
	SRO	Directs the actions of EOP	-2.0				
	SRO	Verify acceptance criteria r	net at interva	lls of approximately	vevery 15	minutes.	
	RO	Verify all PCPs operating					
	RO	 Verify Pressurizer level with Level between 20% and a Level trending to between 	nin limits: 85% n 42% and 57	7%			

Appendix D		Operator Actions			FORM ES-D-2 (R8, S1		
Op-Tes	t No.:	Scenario No.:	Spare	Event No.:	5	Page of	
Event D	escription:	Turbine Governor Val	lve GV 3 Fail	s Shut			
Time	Position	,	Applicant's Ac	tions or Behavior			
	RO	Verify Pressurizer pressur	e within limits	:			
		 Pressure between 1650 Pressure trending to bet 	and 2185 psi ween 2010 ai	a nd 2100 psia			
			<u></u>	·····	<u>.</u>		
		SIMULATOR OPERATOR	R:	·····			
		Initiate next event once I given by SRO to the RO.	Pressurizer le	evel and pressure	bands h	ave been	
.:							
					<u> </u>		
			A				

Appendi	x D	Operator Actions				FORM ES-D-2 (R8, S1		
Op-Tes	st No.:	Scenario No.:	Spare	Event No.:	6	Page of		
Event [Description:	Failure of the Reactor to Automatically Trip, including from C-02						
Time	Time Position Applicant's Actions or Behavior							
		NOTE: This malfunction the reactor prior to cond	n may not ap litions warra	ply if the crew ele nting an automat	ects to maic trip.	anually trip		
	RO	Determines that the React Trip pushbutton depressed	tor has failed d on panel C-	to trip automaticall 02.	y and whe	en Reactor		
		NOTE: This is actually p	erformed as	part of Event 5.				
	RO BOP	Trip Reactor from panel C	-06.					
		CRITICAL TASK to caus	e reactor trip	o following ATWS	conditio	n.		
	RO	Informs SRO of failure of r	eactor to trip	from panel C-02.				
				· .				

Appendix D **Operator Actions** FORM ES-D-2 (R8, S1) Op-Test No.: Scenario No.: Spare Event No 1 7 Page of Event Description: Main Steam Line Rupture Inside of the Containment Time Position Applicant's Actions or Behavior SRO Diagnose Main Steam line rupture inside containment: RO BOP · Excessive steam flow from 'A' S/G · S/G isolation actuation · S/G pressures and PCS temperatures and pressures lowering · Containment humidity, temperature, and pressure rising · PCS subcooling rising Numerous Control Room alarms (CAC DRY PAN Hi-LEVEL SRO Enters and directs the actions of EOP-6.0. NOTE: May return to EOP-1.0, but acceptable to enter EOP-6.0 directly. If EOP-1.0 is re-entered, it will be to perform re-diagnosis or to re-assess Safety Functions. RO Determine that Containment Isolation acceptance criteria NOT met. BOP RO Determine Containment Isolation did NOT occur: BOP • EK-1126, "CIS INITIATED", NOT in alarm. · Containment isolation valves NOT properly aligned

Appendix D

Operator Actions

FORM ES-D-2 (R8, S1)

Op-Tes	t No.:	Scenario No.: Spare Event No.: 7 Page of
Event D	escription:	Main Steam Line Rupture Inside of the Containment
Time	Position	Applicant's Actions or Behavior
	RO BOP	Initiates CHR signal to isolate containment Depresses CHRL-CS, HIGH RADIATION INITIATE, and/or Depresses CHRR-CS, HIGH RADIATION INITIATE
	<u> </u>	CRITICAL TASK to ensure containment is isolated when required.
	SRO RO BOP	<i>Note:</i> Crew may opt to secure PCPs at this time due to no CCW to containment. Depending on timing of crew, conditions will probably NOT be met to restore CCW to containment.
	BOP	Perform EOP Supplement 6, "Checklist for Containment Isolation"
	RO BOP	Close both MSIVs and CCW Containment Isolation Valves CRITICAL TASK to close MSIVs since they are required to be closed on CHP
	Manually initiates SIAS. CRITICAL TASK to initiate Safety Injection on Containment High Pressure.	
	SRO	Verify Attachment 1, "Safety Function Status Check Sheet", acceptance criteria are satisfied at intervals of approximately every fifteen minutes.

palisades nuclear plant

Appendix D		Operator Actions FORM ES-D-2 (R8, S ²					
Op-Tes Event D	t No.: escription:	Scenario No.: Spare Event No.: 7 Page of Main Steam Line Rupture Inside of the Containment					
Time	Position	Applicant's Actions or Behavior					
	RO	Verifies EK-1342, "SAFETY INJ INITIATED" is alarmed due to PZR pressure less than or equal to 1605 psia OR containment pressure greater than or equal to 4.0 psig.					
	вор	Ensure MISVs and MSIV Bypass Valves are closed					
	RO	Stop one PCP in each loop in pressure drops below 1300 psia NOTE: May have already stopped PCPs due to lack of CCW flow to containment. CRITICAL TASK to secure PCPs when determined that CCW flow cannot be restored to containment.					
	RO	Commence emergency boration to establish PCS boron concentration greater than or equal to boron needed for Tave >525°F as verfied by sample or hand calculation per EOP Supplement 35.					
	RO	Verify PCP operating limits are satisfied per EOP Supplement 1. Note: May have already stopped PCPs due to lack of CCW flow to containment.					

Appendix D		Operator Actions FORM ES-D-2 (R8, S1
Op-Test No.: Event Description:		Scenario No.: Spare Event No.: 7 Page of Main Steam Line Rupture Inside of the Containment
Time	Position	Applicoption of Debastics
	BOP	Place LTOP in service.
	SRO BOP	Ensure at least one train of CR HVAC in Emergency Mode within 20 minutes of the time of the Reactor trip per SOP-24.
	SRO RO BOP	Determine the most affected S/G by considering ALL of the following: High steam flow from S/G Lowering S/G pressure Lowering S/G level Lowering Loop Tc temperature
	BOP	Isolate 'A' S/G per EOP Supplement 17
	RO BOP	Stabilize PCS temperature by maintaining 'B' S/G level between 60% and 70%.
	RO	Verify SI pump throttling criteria are satisifed.
		Terminate scenario when 'A' S/G has been isolated, PCS temperature has been stabilized, and SI Pump throttling criteria are satisfied.

٠

•

Appendix D		Operator Actions				FORM ES-D-2 (R8, S		
Op-Tes	t No.:	Scenario No.:	Spare	Event No.:	8	Page of		
Event D	Description:	Initiation Failure of C Containment Spray	ontainment l	solation, Safety I	njection,	, and		
Time	Position		Applicant's Ac	tions or Behavior				
	RO BOP	<u> </u>						
		Valve NOT properly alig <i>Note: This is actually pe</i>	ned e rformed as j	part of EVENT 7.				
	RO BOPInitiates CHR signal to isolate containment and d• Depresses CHRL-CS, HIGH RADIATION INITI• Depresses CHRR-CS, HIGH RADIATION INIT				s CIS doi d/or	es NOT occur		
	BOP	Manually aligns for Contai	nment Isolatic re containme	on per EOP Supple ant isolated when	ement 6 require	d.		
	RO BOP	Manually closes both MSIV • CV-0510 ('A' S/G) • CV-0501 ('B' S/G) CRITICAL TASK to close	/s • MSIVs since	e they are require	d to be c	losed on CHP		

0 0

Appendi	(D	Оре	rator Actions		FORM	ES-D-2 (F	8, S1)		
Op-Tes	t No.:	Scenario No.:	Spare	Event No.:	8	Page	of		
Event D	escription:	Initiation Failure of Co Containment Spray	ontainment l	solation, Safety I	njection,	and			
Time	Position	Applicant's Actions or Behavior							
	RO BOP	Manually closes CCW Cor • CV-0910, (KEY # 337) • CV-0911, (KEY # 338) • CV-0940, (KEY # 336)	ntainment Iso	lation Valves					
		Note: SRO may direct le PCPs (as long as Contai	aving CCW Inment press	valves open to m sure remains less	aintain c than 35	ooling to psia).			
	RO BOP	Initiates SIAS Depresses PB-1, INJEC Depresses PB-2, INJEC CRITICAL TASK to initia	TION INITIA TION INITIA te Safety Inje	TE TE ection when requ	uired.				
	RO	Manually aligns for Contain • Opens both Containmen • Starts ALL Containment CRITICAL TASK to ensu	nment Spray It Spray Valve Spray Pumps re Containm	es (CV-3001, CV-3 s (P-54A, B, C) ent Spray actuat	3002) ed when	required.			

Facility:							
	PALISADE	ES	Scenario No.: 2	Op-Test No.:			
Examiners:			Operators:				
Initial Conditions:		IC-19. A with Cau	Approx. 100% power EOL. Equipment C Ition Tag on handswitch.	OS is Charging Pump P-55C			
Turnover:		Power is and will ppm. As Blowdow	er is at 100%. Charging Pump P-55C is ouot of service for maintenance will not be available for approximately 12 hours. Boron concentration is 50 ASI is +0.02. Equilibrium Xenon. Off-gas flow is 2 scfm. S/G downs are at 20K each.				
		Shift ord	ers are to reduce power at 12% per hou	r for the Refueling Outage.			
Event No.	Malf No.	Event Type*	Event Description				
1	NA	SRO (N) RO (R) BOP (N)	Power Reduction	¢			
2	TC20	SRO (C) BOP (C)	Loss of Panel L21				
3	CV05	SRO (I) RO (I)	Loss of Letdown Pressure Control Hig	h			
4	RX11A	SRO (I) BOP (I)	Erratic Feedwater Regulating Valve O	peration			
5	RD12-15	SRO (C) RO (C)	Dropped Rod #15	······································			
6	SG01A	SRO (M) RO (M) BOP (M)	'A' Steam Generator Tube Rupture at	700 gpm			
7	RP19 RP20	SRO (C) RO (C)	Failure of Automatic AND Manual Rea	ctor Trip			

SIMULATOR OPERATOR INSTRUCTIONS

Event No.	Simulator Operator Instructions
	Reset to IC-19. Approx. 100% power EOL. Equipment OOS is Charging Pump P-55C with Caution Tag on handswitch.
1	Power Reduction - no setup required
2	 TC20 - Insert malfunction a couple of minutes after crew starts power reduction. When dispatched as an AO to investigate the problem, report: "There appears to be a problem internal to the UPS. I recommend that the UPS be placed on BYPASS."
3	CV05
4	RX11A - FRV should cycle <u>+</u> 10% of current position
5	RD12-15
6	SG01A - Ramp time = 3 minutes; Severity = 700 gpm
7	RP19, RP20 - Insert MALFs at beginning of scenario.

SHIFT TURNOVER - SCENARIO: SPARE

Power is at 100%. Charging Pump P-55C is ouot of service for maintenance and will not be available for approximately 12 hours. Boron concentration is 50 ppm. ASI is +0.02. Equilibrium Xenon. Off-gas flow is 2 scfm. S/G Blowdowns are at 20K each.

Shift orders are to reduce power at 12% per hour for the Refueling Outage.

palisades nuclear plant

,

Θ

.

Appendix D		Operator Actions	FORM ES-D-2 (R8, S1		
<u> </u>	<u></u>				
Op-Tes	it No.:	Scenario No.: 2 Event No.:	1	Page of	
Event E	escription:	Power Reduction			
Time	Position	Applicant's Actions or Behavior			
	SRO	Reviews Precautions and Limitations of GOP-8.			
	RO	Reviews Precautions and Limitations of applicable SOPs			
	ВОР	Selects DEH de-escalation rates for Main Turbine.			
	RO	Borates to commence downpower			
	BOP	Initiates turbine de-rate.			

Appendix D		Operator Actio	FORM ES-D-2 (R8, S						
Op-Tes	t No.:	Scenario No.: 2	Event No.:	2	Page	of			
Event [Description:	Loss of Panel L-21							
Time	Position	Applicant's	Actions or Behavior						
	вор	Diagnose loss of panel L-21							
		EK-0318, TURBINE PANEL TROU DEH Screen Alarm, UPS ON BAT	JBLE						
		Note: BOP may go to HOLD on M	ain Turbine, but NO	Г require	d.				
	SRO BOP	Refer to EK-0318 and EK-03, Attach	ment 1						
		Note: Can also be monitored on SYS STATUS SCREEN							
	SRO BOP	Directs AO to determine if DPU 52 a	ower avail	able					
		Note: AO reports there appears to be an internal problem. Recomn bypassing.							
	SRO	Within 20 minutes of loss of Panel L- or restores UPS to NORMAL or BYP	21, directs AO to rest	ore Prima	ary AC Pov	wer			
			······						
	SRO	Notifies I&C to troubleshoot.		<u></u>	<u>, </u>				
				 -					
				<u> </u>					
					····				

Appendix D		Operator Actions				FORM ES-D-2 (R8,			
Op-Tes	t No.:	Scenario No.:	2	Event No.:	3	Page	of		
Event D	Description:	Loss of Letdown Pres	ssure Co	ntrol High					
Time	Position		Applicant	's Actions or Behavior					
RO Diagnoses failure of the intermediate letdown pressure controller * Selected intermediate letdown pressure control valve opens. * Flashing in the Letdown Heat Exchanger, resulting in pressure and flow oscillations on the letdown line. * EK-0704, LETDOWN HT EX TUBE INLET HI-LO PRESS, alarms.						nd flow s.			
	SRO	Enters and directs the acti	Enters and directs the actions of EK-0704.						
	RO	Determines charging and	letdown fi	ows NOT matched.					
	RO	Determines Letdown Press approximately 460 psig.	sure Con	troller PIC-0202 NOT	controlling	g at			
	RO	Selects manual on the pre	ssure cor	ntroller.					
	RO	Manually respositions sele psig.	cted valv	e to control pressure a	at approxi	mately 460			
	SRO	Initiates troubleshooting ar	nd repairs						

¢

Appendix [D	Оре	erator Act	ions	FORM E	S-D-2 (R8, S1
Op-Test I Event De	No.: escription:	Scenario No.: Dropped Control Roo	2 #15	Event No.:	4	Page of
Time	Position		Applicant	's Actions or Behavior		
	SRO RO BOP	Diagnose Dropped Rod. • EK-0911, ROD POSITI • EK-0912, ROD POSITI • EK-0948, DROPPED R Note the following plant re • Tave lowers • PZR pressure lowers • PZR level lowers	ON 4 INC ON 8 INC OD sponses:	CHES DEVIATION CHES DEVIATION		
	SRO	Enters and directs the acti	ons of O	NP-5.1.		
F	RO	Identifies affected rod as F	Rod 15.			
E	BOP	Adjusts Main Turbine load	to mainta	ain Tave within 3°F of T	ref.	
	SRO	Tech Spec involvement ma • 3.1.5.a • 3.1.4.c • 3.1.4.e • 3.4.2 • 3.2.3 • 3.2.2	ay include	e any of the following se	ctions:	
s	SRO	Notify Reactor Engineering	j.			

.

К

Appendi	×D	Оре	erator Actio	ns	FORM	ES-D-2 (R8, S
Op-Test No.: Event Description:		Scenario No.: Erratic Feedwater Reg	2 gulating V	Event No.:	5	Page of
Time	Position		Applicant's	Actions or Behavior		
	SRO BOP	 Diagnoses erratic operatio Feed flow to 'A' S/G risir 'A' S/G level rising and fa Note: May get Main Turk 	n of FRV (ng and fallin alling bine Hi Vit	CV-0701 ng pration alarm (EK-01	05)	
	SRO	Enters and directs the activ	ons of ONI	P-10, Excessive Feed	lwater Inc	crease
	BOP	Takes manual control of Fl CRITICAL TASK to take r	RV CV-07(D1 to restore S/G feen	d flow and vel prior	t actual level. <i>to trip.</i>
	SRO	Initiates troubleshooting/re	pair.			

¢

Appendix D

Operator Actions

FORM ES-D-2 (R8, S1)

Op-Tes	t No.:	Scenario No.: 2 Event No.: 6 Page of
Event D	escription:	'A' Steam Generator Tube Rupture at 700 gpm
Time	Position	Applicant's Actions or Behavior
	SRO RO BOP	 Diagnoses Steam Generator Tube Leak/Rupture on 'A' S/G Rising radiation levels on secondary plant Lowering PZR level Lowering PCS pressure Rising level in 'A' S/G Lowering feed flow for 'A' S/G EK-1364, GASEOUS WASTE MONITORING HI RADIATION alarms
	SRO	Directs a Reactor trip and enters and enters EOP-1.0. Based on rising S/G leakage confirmed AND CVCS charging rate rising to maintain PZR level. Note: Tube rupture ramps in over 3 minutes to 700 gpm. (May first enter ONP-23.2 for SG tube leakage, but not likely due to severity of tube rupture.)
	RO	Trips the Reactor Note: See Event 7 for details on how reactor is tripped. CRITICAL TASK to trip reactor when required.
	BOP	Manually trips Main Turbine when the majority of Rod Matrix lights have turned from RED to GREEN. <i>Note: This potential delay may cause SIAS actuation.</i> <i>CRITICAL TASK to trip turbine when reactor has tripped.</i>

o

Appendix D **Operator Actions** FORM ES-D-2 (R8. S1) Op-Test No.: Scenario No.: 2 Event No.: 6 Page of Event Description: 'A' Steam Generator Tube Rupture at 700 gpm Time Position Applicants's Actions or Behaviors RO Determines that Reactivity Control acceptance criteria is met. BOP Control the Feedwater System • Places ALL operating MFPs to manual and ramp one to minimum speed · As Tave lowers toward 525°F ramps second MFP to minimum speed Closes ALL MFRVs and Bypass FRVs CRITICAL TASK to prevent PCS overcooling. BOP Determines that Vital Auxiliaries - Electric acceptance criteria are met. RO Determines that PCS Inventory Control acceptance criteria are NOT met due to lowering PZR level. RO Determines that PCS Pressure Control acceptance criteria are NOT met due to lowering PZR pressure. RO Verify EK-1342, SAFETY INJ INITIATED, alarms if PZR pressure is less than 1605 psia RO Stop PCPs, as required: • If pressure less than 1300 psia, stop two PCPs (one in each loop) · If PCP operating limits not met, stop ALL PCPs. CRITICAL TASK to minimize inventory loss and to protect PCPs.

Op-Test No.: Scenario No.: 2 Event No.: 6 Page of Event Description: 'A' Steam Generator Tube Rupture at 700 gpm Time Position Applicants's Actions or Behaviors RO Determines that Core Heat Removal acceptance criteria are NOT met. · Possibly NO PCPs operating · Possible loss of subcooling BOP Determines that PCS Heat Removal acceptance criteria are met. BOP Determines that Containment Isolation acceptance criteria are NOT met, due to Condenser Off-Gas Monitor RIA-0631 alarm NOT clear. RO Determines that Containment Atmosphere acceptance criteria are met. RO Determines that Vital Auxiliaries - Water acceptance criteria are met. RO Determines that Vital Auxiliaries - Air acceptance criteria are met. BOP Verify at least one Condensate Pump and Cooling Tower Pump operating SRO Assigns performance of SIAS Checklist, EOP Supplement 5

Operator Actions

palisades nuclear plant

Appendix D

0

FORM ES-D-2 (R8, S1)

k D	Operator Actions			FORM ES-D-2 (R8, S		
t No.:	Scenario No.: 2	Event No.:	6	Page of		
Description:	'A' Steam Generator Tube Rup	ture at 700 gpm				
Position	S	······································				
BOP	Commence Emergency Shutdown C	Checklist (GOP-10)				
SRO	Refers to EOP-1.0, Attachment 1, "Event Diagnostic Flow Chart" and diagnoses the event.					
SRO	Transitions to and directs the actions Rupture" NOTE: Even though all PCPs may should NOT be made to EOP-9.0 to on Event Diagnostic Flow Chart.	s of EOP-5.0, "Steam be off concurrent based on no PCPs w	Generati with the s	or Tube SGTR, entry TR. See note		
	x D t No.: Description: Position BOP SRO SRO SRO	x D Operator Action est No.: Scenario No.: 2 Description: 'A' Steam Generator Tube Rup Position Applicants's BOP Commence Emergency Shutdown C SRO Refers to EOP-1.0, Attachment 1, "E SRO Transitions to and directs the actions Rupture" NOTE: Even though all PCPs may should NOT be made to EOP-9.0 to on Event Diagnostic Flow Chart.	x D Operator Actions at No.: Scenario No.: 2 Event No.: Description: 'A' Steam Generator Tube Rupture at 700 gpm Position Applicants's Actions or Behaviors BOP Commence Emergency Shutdown Checklist (GOP-10) SRO Refers to EOP-1.0, Attachment 1, "Event Diagnostic Flow the event. SRO Transitions to and directs the actions of EOP-5.0, "Steam Rupture" NOTE: Even though all PCPs may be off concurrent to should NOT be made to EOP-9.0 based on no PCPs woon Event Diagnostic Flow Chart.	x D Operator Actions FORM it No.: Scenario No.: 2 Event No.: 6 Description: 'A' Steam Generator Tube Rupture at 700 gpm Position Applicants's Actions or Behaviors BOP Commence Emergency Shutdown Checklist (GOP-10) SRO Refers to EOP-1.0, Attachment 1, "Event Diagnostic Flow Chart" a the event. SRO Transitions to and directs the actions of EOP-5.0, "Steam Generate Rupture" NOTE: Even though all PCPs may be off concurrent with the should NOT be made to EOP-9.0 based on no PCPs with a SG on Event Diagnostic Flow Chart.		

Appendix D		Operator Actions			FORM	FORM ES-D-2 (R8, S1		
Op-Test No.:		Scenario No.:	2 Zubo Rup	Event No.:	6	Page of		
				ure at 700 gpm				
Time	Position		Applicant's	Actions or Behavior				
	SRO	Verifies acceptance criteria	a met at in	tervals of approxima	tely every	15 minutes.		
		Note: SRO can assign tl	he STA/SI	E surrogate to perfo	rm this fu	inction.		
	SRO	Notify Health Physics to pe Supplement 14	Notify Health Physics to perform preliminary radiation surveys per EOP Supplement 14					
	BOP/RO	Verify at least minimum SI	flow per E	OP Supplement 4				
RO Commence emergency boration to establish PCS bor than or equal to boron needed for Tave > 525°F					concentrat	ion greater		
	BOP	Ensure at least one train or <i>Note: Must be performed</i>	f CR HVA	C in Emergency Mod	e, per SO r trip.	P-24.		
	BOP	Ensure S/G blowdown con	trol valves	are closed				
	RO BOP	Cooldown the PCS to high 500°F to 515°F) using the	est narrow Turbine B	range Thot less thar ypass Valve	ז 524°F (p	preferably		
	RO	Records each occurrence o temp minus spray temp) gr	of PZR Sp eater than	ray operation with a 2 200°F in the Reacto	∆T (PZR v pr Logbool	apor phase		

Appendix D **Operator** Actions FORM ES-D-2 (R8, S1) Op-Test No.: Scenario No.: 2 Event No 1 6 Page of Event Description: 'A' Steam Generator Tube Rupture at 700 gpm Time Position Applicant's Actions or Behavior RO If less than BOTH Cooling Tower Pumps AND less than BOTH Condensate BOP Pumps NOT operating, close BOTH MSIVs and Bypasses. Note: One or more Condensate Pumps may have been manually tripped due to a loss of cooling water upon SIAS actuation. SRO Verify SI Pump throttling criteria are satisfied: RO ROP ٠ Based on the Average of Qualified CETs, PCS subcooling at least 25°F subcooled Corrected PZR level is greater than 20% and controlled, per EOP Supplements 9 and 10. At least one S/G available for PCS heat removal with corrected level being maintained or being restored to between 60% and 70% per EOP Supplement 11. Operable RVLMS channel indicates greater than 102 inches above the bottom of fuel alignment plate. RO Depressurize the PCS BOP Maintain PZR pressure within ALL of the following criteria: Less than 940 psia Within the limits of EOP Supplement 1 Preferably within 50 psid of the isolated S/G pressure Operate Main or Auxiliary Spray valves If SI pump throttling criteria are met, throttle HPSI flow or control charging and letdown flow TERMINATE SCENARIO WHEN THE CREW HAS DEPRESSURIZED THE PCS BELOW 940 PSIA AND WITHIN 50 PSID OF 'A' S/G

Appendix D		Operator Actions				FORM ES-D-2 (R8, S1		
Op-Tes	it No.:	Scenario No.:	2	Event No.:	7	Page of		
Event D	Description:	Failure of Automatic	and Manu	al Reactor Trip				
Time	Position		Applicant's	Actions or Behavior				
	RO	Determines that the React and C-06.	tor has fail	ed to trip from pushbo	uttons on	panels C-02		
	RO	Opens CRD Clutch Power	r Feeder B	reakers 42-1RPS and	1 42-2RP	s		
				OR				
		Places ALL CRD clutch po	ower toggle	e switches to CLUTC	HOFF.			
		NOTE: Either of the abo acceptable.	ve metho	ds will result in a rea	actor trip	and is		
		This is actually perform	ed as part	of Event 6.				
				<u> </u>				
				· · · · · · · · · · · · · · · · · · ·				

•

Appendix	D		Simulator Scenario Outline FORM ES-D-1 (R8, S
Facility:	PALISAD	ES	Scenario No.: 1 Op-Test No.:
Examine	rs:		Operators:
Initial Cor	nditions:	Approx. Tag hur	60% power MOL; equipment OOS is AFW Pump P-8C with Caution ig on handswitch; two MFW pumps in operation.
Turnover	60% power MOL; AFW Pp. P-8C is out of service. Main Feedwater is in operation with both MFW Pps in service. Boron concentration is n. ASI is -0.01. Shift orders are to continue a power escalation at 4% to full power. All GOP-5 steps up to and including GOP-5, Section been completed.		
Event No.	Malf No.	Event Type*	Event Description
1	NA	SRO (N) RO (R) BOP (N)	Power Escalation
2	EG04	SRO (I) BOP (I)	Main Generator Automatic Voltage Regulator Failure
3	CC02A	SRO (C) RO (C)	CCW Pp. Trip (Standby Fails to Start)
4	CV04	SRO (C) RO (C)	Charging Pump P-55A Fluid Drive Failure High (IPE)
5	RX15B	SRO (I) BOP (I)	Main Steam Flow Transmitter FT-0704 Failure on "B" S/G (lower than current - use value = 26. No trip)
6	RC03	SRO (C) RO (C) BOP (C)	Primary Coolant System Leak into Containment at approx. 5 gpm. (IPE) (Use value = 5.0)
7	RC04	SRO (M) RO (M) BOP (M)	Primary Coolant System Leak into Containment at 200 gpm (Use value = 20.0)
8	RD10	SRO (C) RO (C)	Three Stuck Control Rods (Rods, 12, 17, and 18)
(N)ormal	(R)eac		nstrument (C)omponent (M)pior

,

SIMULATOR OPERATOR INSTRUCTIONS

Event No.	Simulator Operator Instructions
	Reset to IC-15 Approx. 60% power MOL; equipment OOS is AFW Pump P-8C with Caution Tag hung on handswitch; two MFW pumps in operation. Ensure CCW Pumps P-52B AND P-52C are running.
1	Power Escalation - No setup required.
2	EG04 - After insertion, change grid voltage/frequency once or twice to require manual operation of Voltage Regulator to maintain generator terminal voltage.
3	CC02A
4	CV04
5	RX15B - Severity = lower than current (use value of 26)
6	RC03 - Severity = use value of 5.0 (5 gpm)
7	RC04 - Severity = use value of 20.0 (200 gpm)
8	RD10-12, RD10-17, RD10-18 INSERT at beginning of scenario.

Special Notes:

- 1. Ensure EOOS indicates that P-8C is OOS.
- 2. P-8C-4 OFF, Insert RED, GREEN light OFF.
- 3. Insert RD10-12, RD10-17, RD10-18 malfunctions for three stuck control rods.
- 4. CC13C must be inserted at begin of scenario (prevents standby CCW pump from starting)
- 5. OVERRIDE Amber Standby light for P-52A ON. Cycle handswitch to OFF and then neutral to make it appear that P-52A is in Standby.
- 6. If sent as the AO to check CCW Hx dp PRIOR to manually starting the second CCW Pp, report as 10.1, 10.2.
- 5. If sent as the AO to check CCW Hx dp AFTER manually starting the second CCW Pp, report as 13.1, 13.2

SHIFT TURNOVER - SCENARIO: ONE

Approx. 60% power MOL; AFW Pp. P-8C is out of service. Main Feedwater System is in operation with both MFW Pps in service. Boron concentration is 842 ppm. ASI is -0.01. Shift orders are to continue a power escalation at 4% per hour to full power. All GOP-5 steps up to and including GOP-5, Section 3.5 have been completed.

Appendix D		Operator Actions			FORM ES-D-2 (R8, S1		
Op-Test No.: Event Description:		Scenario No.: 1 Power Escalation	Event No.:	1	Page 1 of 1		
Time	Position	Applicant's A	Actions or Behavior				
	SRO	Enters and directs the actions of GOP	9-5.				
	SRO	Reviews GOP-5 Precaution and Limita	ations with crew.				
	SRO	May discuss ASI control strategy.					
	TURB RO	Continue power escalation as directed	l by CRS.				
· · · ·							

Appendix D		Operator Actions			FORM ES-D-2 (R8, S		
Op-Tes	st No.:	Scenario No.:	1	Event No.:	2	Page 1 of 1	
Event [Description:	Voltage Regulator Fa	ilure				
Time	Position	,	Applicant's	Actions or Behavior			
	SRO BOP	Diagnoses Main Generato • EK-0310, GENERATOR • Voltage regulator auto tr	or Automat ≀ VOLTAG ransfers to	tic Voltage Regulator fi E REG TRIP alarms Manual	ailure		
	BOP	May go to Hold on Main Tu	urbine (no	t required)			
	вор	Any adjustments to voltage	Any adjustments to voltage must be done with the Direct Contro				
	SRO	Initiates troubleshooting ar	nd repair.				

Appendix D		Operator Actions	FORM ES-D-2 (R8, S1							
Op-Test No.:		Scenario No.: 1 Event No	0.:	3	Page 1	of 1				
Event L	escription:	CCW Pump Trip (Standby Fail to Start)								
Time	Position	Applicant's Actions or Beha	Applicant's Actions or Behavior							
	SRO RO	 Diagnose trip of CCW Pump P-52A P-52A breaker indicates OPEN EK-1167, COMPONENT CLG PUMPS P-52A/B/C EK-1168, COMPONENT CLG PUMPS STANDBY does NOT alarm. Standby CCW Pump FAILS to start 	TRIP PUMF	alarms ^D RUNI	VING					
	SRO	Enters and directs the actions of ARP-7 and ONP-6.2 of entering ONP-6.2.	announce	ment						
	RO	Starts available CCW Pump P-52C.								
	RO	Monitors CRDM and PCP parameters, as appropriate	ə.							
	SRO	Refers to Tech Spec 3.7.7. A.1 is required action. D inoperable and must restore within 72 hours.	eterm	ines on	e train					
	SRO	Initiates troubleshooting and repair. May also write a	Cond	ition Re	eport.					
			<u>.</u>							

palisades nuclear plant

dec 2001

Appendix D **Operator Actions** FORM ES-D-2 (R8, S1) Op-Test No.: Scenario No.: 1 Event No.: 4 Page 1 of 2 Event Description: Charging Pump P-55A Fluid Drive Failure High Time Position Applicant's Actions or Behavior SRO Diagnoses high failure of Charging Pump P-55A speed Charging/letdown mismatch RO Pressurizer level rising VCT level lowering May also get EK-0704, Letdown Ht Ex Tube Inlet Hi-Lo Pressure alarm SRO Enters and directs the actions of EK-0704, as appropriate. NOTE: Actions directed by EK-0704 do NOT address this condition. SRO Directs RO to take manual control of P-55A speed or place Charging Pump P-55B or P-55C in service and secure Charging Pump P-55A per SOP-2A RO Takes manual control of P-55A speed to restore charging flow to normal (33-44 gpm) NOTE: Remainder of this event applies ONLY if crew takes actions to place P-55B or P-55C in manual and secures P-55A. It is acceptable for either set of actions to be taken. RO If directed, place in MANUAL either P-55B (preferred) or P-55C Charging Pumps Control Select Switch

Appendix D		Ope	FOR	FORM ES-D-2 (R8, S1		
Op-Test No.: Event Descri	ption:	Scenario No.: Charging Pump P-55,	1 A Fluid D	Event No rive Failure High	.: 4	Page 2 of 2
Time Po:	sition		Applicant'	s Actions or Beha	vior	
RO		May direct AO to ensure t	hrottled O	PEN P-55B Seal (Coolant Flov	w Control Vlv.
RO		Ensure in AUTO charging capacity charging pump	pump coi	ntrol select switch	for the seco	and fixed
RO		Start pump selected for m	anual ope	eration.		
SRC RO)	Refer to Attachment 2 and check that the charging pump selected for AUTO (P-55C preferred), and possibly additional Letdown Orifice Stop Valves cycle according to controller output to maintain PZR level setpoint				
RO		IF desired to minimize Leto CV-2004, Orifice Stop Valv	down Orifi ve	ce Valve cycling, ⁻	THEN CLOS	SE
RO		When charging flow increa	ises, stop	P-55A.		
SRO)	Initiate troubleshooting and	repair of	P-55A drive		
		٥٥				

Appendix D

Operator Actions

FORM ES-D-2 (R8, S1)

Op-Test No.:		Scenario No.: 1 Event No.: 5 Page 1 of 1						
Event D	escription:	Main Steam Flow Transmitter (FT-0704) Fail to Lower than Normal						
Time	Position	Applicant's Actions or Behavior						
	TURB	Diagnoses failure of steam flow transmitter FT-0704 on 'B' S/G						
		 Steam flow lower than feed flow CV-0703 closing to lower feed flow Feed pump speed lowering SG 'B' level lowering SG 'A' level lowering, then restoring to normal as CV-0701 opens 						
	SRO	Enters and directs the actions of ONP-3. Loss of Feedwater						
	TURB	Takes manual control of CV-0703 and feed pumps, if needed, to maintain SG levels at program						
		CRITICAL TASK to prevent reactor trip on low SG level (immediate action).						
	SRO	Initiates troubleshooting and repairs						

Appendix D Operator Actions FORM ES-D-2 (R8, S1) Op-Test No.: Scenario No.: 1 Event No.: 6 Page 1 of 2 Event Description: PCS Leak Inside Containment (5 gpm) Time Position Applicant's Actions or Behavior RO Diagnoses leakage from PCS into containment BOP SRO · Containment humidity rising Pressurizer level lowering until recovered by PLCS · Pressurizer pressure lowering until recovered by PPCS · Charging requirements rising Charging/letdown mismatch greater than normal • VCT level lowering Containment sump level rising • EK-1364, GASEOUS WASTE, alarms due to Containment Air alarm SRO Refers to and directs the actions of ONP-23.1 RO Ensures additional Charging Pumps start (if needed) RO Ensure that the increase in average makeup rate has not been caused by a large generator load change or by a change in Tave RO At SRO discretion, close CV-2001 and CV-2009 to isolate letdown SRO NOTE: May elect to NOT isolate letdown. This is acceptable.

Appendix D		Operator Actions			FOR	FORM ES-D-2 (R8, S1		
Op-Test No.: Event Description:		Scenario No.: 1 PCS Leak Inside Contain	ment (5 g	Event No.:	6	Page 2 of 2		
Time	Position	Аррі	licant's Actio	ons or Behavior				
	RO BOP SRO	Determine PCS leakrate NOTE: Full leak rate calculati determination may be somewi PCS temperature changing sli	on is not ex hat masked ightly	pected to be per by previous eve	formed nts whit	. Leak rate ch may still have		
	RO BOP	Attempt to locate the leak Containment Sump level rec Containment humidity indica Area radiation monitors 	corders ators					
	SRO	Refers to and enters Tech Spe	ec 3.4.13 fo	r PCS Leakage I	mits			
	SRO	Enters GOP-8 to perform an o NOTE: Crew may elect to tri	orderly shutc	own. tor. This is acc	eptabl	9.		
		NOTE: Initiate next event w Tech Specs	hen SRO h	as addressed p	ant co	nditions and		
			7 - 14 .4 14.1.					

palisades nuclear plant

۲

6

¢

Appendix D Operator Actions FORM ES-D-2 (R8, S1) Op-Test No.: Scenario No.: 1 Event No.: 7 Page 1 of 5 Event Description: PCS Leak Inside Containment Raises to 200 gpm Time Position Applicant's Actions or Behavior RO Diagnoses large break LOCA BOP SRO · SIAS actuated PCS pressure lowering rapidly Containment pressure rising rapidly Containment humidity and temperature rising · EK-1363, CONT HI RAD and numerous alarms annunciating SRO Orders reactor trip and enters and directs actions of EOP-1.0 RO Determines Reactivity Control NOT met due to three stuck rods and commences **Emergency Boration** CRITICAL TASK for reactivity control. BOP Control the Feedwater System • Places ALL operating MFPs to manual and ramp one to minimum speed • As Tave lowers toward 525°F ramps second MFP to minimum speed Closes ALL MFRVs and Bypass FRVs CRITICAL TASK to prevent PCS overcooling. BOP Determines Vital Auxiliaries - Electric acceptance criteria met

Appendix D		Operator Actions			FORM	FORM ES-D-2 (R8, S	
Op-Test No.: Event Description:		Scenario No.: PCS Leak Inside Con	1 tainment Rais	Event No.: ses to 200 gpm	7	Page 2 of 5	
Time	Position	7	Applicant's Act	ions or Behavior			
	RO	Determine that PCS Inven low Pressurizer level	ntory Control ac	cceptance criteria	are NO	T met due to	
	RO	Determines PCS Pressure actuated)	e Control accep	otance criteria NC)T met (SIAS has	
	RO	Determines Core Heat Rei	moval accpeta	nce criteria are m	et		
	RO BOP	Determines that PCS Heat • Ensure Turbine Bypass \ • Ensure Atmospheric Ste • Ensure both MSIVs close • Ensure Main Feed Reg \	t Removal acce Valve closed am Dump Valv ed Valves and Byp	eptance criteria a ves closed bass Feed Reg Va	re met alves clc	osed	
	RO BOP	Determine that Containme	nt Isolation acc	ceptance criteria a	are met		
	RO BOP	Determine that Containmer	nt Atmosphere	acceptance crite	ria are N	IOT met	
	RO	Ensure all CAC high capac	ity outlet valve	s are open, as SV	VS conc	litions permit	
			n				

Appendi	x D	Оре	erator Acti	ons	FORM	1 ES-D-2 (R8, S1	
Op-Test No.: Event Description:		Scenario No.: PCS Leak Inside Con	1 tainment	Event No.: Raises to 200 gpm	7	Page 3 of 5	
	Position	Applicant's Actions or Behavior					
	RO	Determine Vital Auxiliaries - Water acceptance criteria are met					
	RO	Determine Vital Auxiliaries - Air acceptance criteria are met					
	BOP	Perform EOP Supplement SIAS"	: 5, "Checl	klist for Safeguards Ec	uipment	Following	
	BOP	Perform EOP Supplement 6, "Checklist for Containment Isolation"					
	вор	Commence Emergency St	nutdown C	hecklist (GOP-10)			
	SRO	Refers to Attachment 1, "E	event Diag	nostic Flow Chart" and	diagno	ses the event.	
	SRO	Transitions to EOP-9.0 due THAN one full length contr	e to indica ol rod stud	tions of a PCS LOCA, ck out.	concurr	ent with MORE	
		CRITICAL TASK to ensu	re entry ir	nto Functional Recov	very Pro	cedure.	
					·		
	····						

Appendix D

Operator Actions

FORM ES-D-2 (R8, S1)

Op-Test No.:		Scenario No.: 1		Event No.:	7	Page 4 of 5		
Event Description:		PCS Leak Inside Containment Raises to 200 gpm						
Time	Position	Applicant's Actions or Behavior						
	RO	Stop PCPs, as required.						
		 If pressure less than 1300 psia, stop one PCP in each loop If subcooling less than 25°F, stop remaining 2 PCPs. 						
		CRITICAL TASK to minimize inventory loss and to protect PCPs.						
					<u> </u>			
	SRO	Direct that all PCPs be stopped NOT satisfied.	Direct that all PCPs be stopped if PCP operating limits of EOP Supplement 1 are NOT satisfied.					
	SRO	Ensure emergency boration in progress. (already in progress due to three stuck control rods)						
	SRO	Direct BOP to place one train of CR HVAC in Emergency Mode within 20 minute of reactor trip.						
	SRO	Direct BOP to place a Hydroger	n Monitor in s	ervice.				
				<u></u>				
			<u> </u>		-			
					-, <u></u>			
					<u> </u>			

.

Appendi	x D	Оре	erator Acti	ons	FOR	M ES-D-2 (R8, S1	
Op-Tes	it No.:	Scenario No.:	1	Event No.:	7	Page 5 of 5	
Event D	Description:	PCS Leak Inside Con	tainment	Raises to 200 gpm			
Time	Position		Applicant's	s Actions or Behavior			
	SRO Select appropriate success paths per Resource Assessment Trees A thru						
		 RC - 2/3 MVAE DC - 1 MVAE AC - 1 IC - 2 PC - 1 HR - 2 CI - 1 CA - 2 MVAW - 1 MVAA - 1 					
	SRO	Direct SE to perform Safet		- Status Chaoka ovor	15 min		
		Direct SE to perform Salety Function Status Checks every 15 minutes.					
	RO	Verify "SAFETY INJ INITIA	\TED" (EK	(-1342) is alarmed.			
	SRO/RO	When proper boron is veri cooldown.	fied for co	oldown, commence a	control	led PCS	
		Terminate scenario wher	ı PCS coc	oldown commenced.			