ELECTRICAL POWER SYSTEMS

SURVEILLANCE REQUIREMENTS (Continued)

connected loads within 15 seconds, energizes the auto-connected shutdown loads through the load sequencer and operates for greater than or equal to 5 minutes while its generator is loaded with the auto-connected shutdown loads. After automatic load sequencing, the steady-state voltage and frequency of the emergency busses shall be maintained at 4160 \pm 420 volts and 60 \pm 1.2 Hz during this test.

- 5) Verifying that on an ESF Actuation test signal, without loss-of-offsite power, the diesel generator starts on the auto-start signal and operates on standby for greater than or equal to 5 minutes. The generator voltage and frequency shall be 4160 \pm 420 volts and 60 \pm 1.2 Hz within 15 seconds after the auto-start signal; the steady-state generator voltage and frequency shall be maintained within these limits during this test;
- 6) Simulating a loss-of-offsite power in conjunction with an ESF Actuation test signal, and:
 - a) Verifying deenergization of the emergency busses and load shedding from the emergency busses;
 - b) Verifying the diesel starts on the auto-start signal, energizes the emergency busses with any permanently connected loads within 15 seconds, energizes the auto-connected emergency (accident) loads through the load sequencer and operates for greater than or equal to 5 minutes while its generator is loaded with the emergency loads. After automatic load sequencing, the steady-state voltage and frequency of the emergency busses shall be maintained at 4160 ± 420 volts and 60 ± 1.2 Hz during this test; and
 - c) Verifying that diesel generator trips that are made operable during the test mode of diesel operation are inoperable.
- 7)* # Verifying the diesel generator operates for at least 24 hours. During the first 2 hours of this test, the diesel generator shall be loaded to 2550-2750 kW (Unit 3), 2950-3150 kW (Unit 4)** and during the remaining 22 hours of this test, the diesel generator shall be loaded to 2300-2500 kW (Unit 3), 2650-2850 kW (Unit 4)**. The generator voltage and frequency shall be 4160 ± 420 volts and 60 ± 1.2 Hz within 15 seconds after the start signal; the steady-state generator voltage and frequency

^{*}For the purpose of this test, warmup procedures, such as idling, gradual acceleration, and gradual loading as recommended by the manufacturer may be used.

^{**}Momentary transients outside these load bands do not invalidate this test.

[#] This test may be performed during POWER OPERATION