

NOV 18 1982

DISTRIBUTION:  
Document Control (50-416)  
NRC PDR  
L PDR  
NSIC  
PRC  
LB#2 Reading  
EHylton  
DHouston  
MWagner, OELD  
ACRS (16)  
ELJordan, DEQA:IE  
JMTaylor, DRP:IE  
Region II

Docket No.: 50-416

Mr. J. P. McGaughy, Jr.  
Assistant Vice President -  
Nuclear Production  
Mississippi Power & Light Company  
P. O. Box 1640  
Jackson, Mississippi 39205

Dear Mr. McGaughy:

Subject: Corrections to the Technical Specifications for Facility Operating License No. NPF-13 - Grand Gulf Nuclear Station, Unit 1

By letter dated June 16, 1982, the Commission issued Facility Operating License No. NPF-13 for Grand Gulf Nuclear Station, Unit 1. Technical Specifications for Grand Gulf 1 were contained in Appendix A to the license. Two inadvertent errors have been identified in the Technical Specifications as issued. On page 3/4 3-29 in Table 3.3.3-2, the time delay trip setpoint (9.0 seconds) and allowable value (9.0 + 0.5 seconds) for degraded voltage (Section D.1.C) were left out. Also, the time delay allowable value of 9.0 + 0.5 seconds for loss of voltage (Section D.2.a) was obviously in error. This allowable value should have been 0.5 + 0.5, - 0.1 seconds. On page 3/4 8-19 in Section 4.8.4.1.a.1.b, reference is made to Table 3.8.3.2-1 which is non-existent. This reference should have been to Table 3.8.4.1-1.

By letter dated October 14, 1982, the Commission issued Amendment No. 4 to Facility Operating License No. NPF-13. As part of this amendment, changes were granted for Technical Specification 3/4 6.5, Drywell Post-LOCA Vacuum Breakers. On page 3/4 6-45a in Section 3.6.5.c of Note 1, the clarifying clause involving the isolation valve was omitted in the statement relating to operability of the position indicator of a drywell post-LOCA vacuum breaker. This statement should have referred to the operability of the position indicator of a drywell post-LOCA isolation valve for a vacuum breaker.

Enclosed are the corrected pages 3/4 3-29, 3/4 6-45a and 3/4 8-19 to be inserted into the Technical Specifications for Grand Gulf Unit 1.

Sincerely,

Original signed by:  
NOV 16 1982

A. Schwencer, Chief  
Licensing Branch No. 2  
Division of Licensing

8211240178 821118  
PDR ADDCK 05000416  
P PDR

OFFICE	Enclosures	DL:LB#2/PM	DL:LB#2/BC			
SURNAME	As stated	DHouston:kw	ASchwencer			
DATE	cc: See next page	11/18/82	11/16/82			

TABLE 3.3.3-2 (Continued)

EMERGENCY CORE COOLING SYSTEM ACTUATION INSTRUMENTATION SETPOINTS

<u>TRIP FUNCTION</u>	<u>TRIP SETPOINT</u>	<u>ALLOWABLE VALUE</u>
D. <u>LOSS OF POWER</u>		
1. <u>Division 1 and 2</u>		
a. 4.16 kV Bus Undervoltage (Loss of Voltage)	1. 4.16 kV Basis 2912 volts	2912 +0, -291 volts
	2. 120 volt Basis 83.2 volts	83.2 +0, -8.3 volts
	3. Time Delay 0.5 seconds	0.5 +0.5, -0.1 seconds
b. 4.16 kV Bus Undervoltage (BOP Load Shed)	1. 4.16 kV Basis 3328 volts	3328 +0, -167 volts
	2. 120 volt Basis 95.1 volts	95.1 +0, -4.8 volts
	3. Time delay 0.5 seconds	0.5 +0.5, -0.1 seconds
c. 4.16 kV Bus Undervoltage (Degraded Voltage)	1. 4.16 kV Basis 3744 volts	3744 +93.6, -0 volts
	2. 120 volt Basis 107 volts	107 +2.7, -0 volts
	3. Time Delay 9.0 seconds	9.0 ± 0.5 seconds
2. <u>Division 3</u>		
a. 4.16 kV Bus Undervoltage (Loss of Voltage)	1. 4.16 kV Basis 3045 volts	3045 ± 61 volts
	2. 120 volt Basis 87 volts	87 ± 1.7 volts
	3. Time Delay 0.5 seconds	0.5 + 0.5, -0.1 seconds

\*See Bases Figure B 3/4 3-1.

#These are inverse time delay voltage relays or instantaneous voltage relays with a time delay. The voltages shown are the maximum that will not result in a trip. Lower voltage conditions will result in decreased trip times.

8211240183 821118  
PDR ADDCK 05000416  
PDR

GRAND GULF-UNIT 1

3/4 3-29

November 18, 1982

## CONTAINMENT SYSTEMS

### SURVEILLANCE REQUIREMENTS (Continued)

---

---

3. By verifying the OPERABILITY of the vacuum breaker isolation valve differential pressure actuation instrumentation with the opening setpoint 1.0 psid by performance of a:
    - a) CHANNEL CHECK at least once per 24 hours,
    - b) CHANNEL FUNCTIONAL TEST at least once per 31 days, and
    - c) CHANNEL CALIBRATION at least once per 18 months.
- 
- 

Note 1: Until restart after the first refueling outage, the following requirements shall apply:

#### 3.6.5

- c. With the position indicator of an OPERABLE drywell post-LOCA isolation valve for a vacuum breaker inoperable, verify the isolation valve to be closed at least once per 24 hours by local indication. Otherwise declare the isolation valve inoperable.

#### 4.6.5.b.1

- b. Verifying the position indicator for the vacuum breaker isolation valve OPERABLE by observing expected valve movement during the cycling test.

#### 4.6.5.b.2

At least once per 18 months by:

- a) Verifying the pressure differential required to open the vacuum breaker, from the closed position, to be less than or equal to 1.0 psid by use of an equivalent test weight and lever arm on the vacuum breaker, and
- b) Verifying the position indicator for the vacuum breaker isolation valve OPERABLE by performance of a CHANNEL CALIBRATION.

## ELECTRICAL POWER SYSTEMS

### 3/4.8.4 ELECTRICAL EQUIPMENT PROTECTIVE DEVICES

#### PRIMARY CONTAINMENT PENETRATION CONDUCTOR OVERCURRENT PROTECTIVE DEVICES

##### LIMITING CONDITION FOR OPERATION

3.8.4.1 All primary containment penetration conductor overcurrent protective devices shown in Table 3.8.4.1-1 shall be OPERABLE.

APPLICABILITY: OPERATIONAL CONDITIONS 1, 2 and 3.

##### ACTION:

- a. With one or more of the primary containment penetration conductor overcurrent protective devices shown in Table 3.8.4.1-1 inoperable, declare the affected system or component inoperable and apply the appropriate ACTION statement for the affected system, and:
  1. For 6.9 kV circuit breakers, de-energize the 6.9 kV circuit(s) by tripping the associated redundant circuit breaker(s) within 72 hours and verify the redundant circuit breaker to be tripped at least once per 7 days thereafter.
  2. For 480 volt circuit breakers, remove the inoperable circuit breaker(s) from service by racking out the breaker within 72 hours and verify the inoperable breaker(s) to be racked out at least once per 7 days thereafter.

Otherwise, be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.-

- b. The provisions of Specification 3.0.4 are not applicable to overcurrent devices in 6.9 kV circuits which have their redundant circuit breakers tripped or to 480 volt circuits which have the inoperable circuit breaker racked out.

##### SURVEILLANCE REQUIREMENTS

4.8.4.1 Each of the primary containment penetration conductor overcurrent protective devices shown in Table 3.8.4.1-1 shall be demonstrated OPERABLE:

- a. At least once per 18 months:
  1. By verifying that the medium voltage 6.9 kV circuit breakers are OPERABLE by selecting, on a rotating basis, at least 10% of the circuit breakers and performing:
    - a) A CHANNEL CALIBRATION of the associated protective relays, and
    - b) An integrated system functional test which includes simulated automatic actuation of the system and verifying that each relay and associated circuit breakers and overcurrent control circuits function as designed and as specified in Table 3.8.4.1-1.
    - c) For each circuit breaker found inoperable during these functional tests, an additional representative sample of at least 10% of all the circuit breakers of the inoperable type shall also be functionally tested until no more failures are found or all circuit breakers of that type have been functionally tested.

Grand Gulf

Mr. J. P. McGaughy  
Assistant Vice President  
Nuclear Production  
Mississippi Power & Light Company -  
P. O. Box 1640  
Jackson, Mississippi 39205

cc: Robert B. McGehee, Esquire  
Wise, Carter, Child, Steen and Caraway  
P. O. Box 651  
Jackson, Mississippi 39205

Troy B. Conner, Jr., Esquire  
Conner and Wetterhahn  
1747 Pennsylvania Avenue, N. W.  
Washington, D. C. 20006

Dr. D. C. Gibbs, Vice President  
Middle South Energy, Inc.  
225 Baronne Street  
P. O. Box 6100  
New Orleans, Louisiana 70161

Mr. John Richardson  
Mississippi Power & Light Company  
P. O. Box 1640  
Jackson, Mississippi 39205

Mr. R. Trickovic, Project Engineer  
Grand Gulf Nuclear Station.  
Bechtel Power Corporation  
Gaithersburg, Maryland 20760

Mr. Alan G. Wagner  
Resident Inspector  
Route 2, Box 150  
Port Gibson, Mississippi 39150

Office of the Attorney General  
Attn: William J. Guste, Jr.  
Department of Justice, Suite C  
7434 Parkins Road  
Baton Rouge, Louisiana 70808

Grand Gulf

cc: (continued)

President  
Claiborne County Board of Supervisors  
Port Gibson, Mississippi 39150

Office of the Governor  
State of Mississippi  
Jackson, Mississippi 39201

U. S. Environmental Protection Agency  
Attn: EIS Coordinator  
Region IV Office  
345 Courtland Street, N. E.  
Atlanta, Georgia 30309