

SURVEILLANCE REQUIREMENTS (continued)

SURVEILLANCE	FREQUENCY
<p>SR 3.8.1.8 -----NOTE----- This Surveillance shall not be performed in MODE 1 and 2. However, credit may be taken for unplanned events that satisfy this SR. ----- Verify manual transfer of unit power supply from the normal offsite circuit to required alternate offsite circuit.</p>	<p>18 months</p>
<p>SR 3.8.1.9 -----NOTES----- 1. Credit may be taken for unplanned events that satisfy this SR. 2. If performed with DG synchronized with offsite power, it shall be performed at a power factor ≤ 0.9. ----- Verify each DG rejects a load greater than or equal to its associated single largest post accident load and engine speed is maintained less than nominal plus 75% of the difference between nominal speed and the overspeed setpoint or 15% above nominal, whichever is lower.</p>	<p>18 months</p>

(continued)

SURVEILLANCE REQUIREMENTS (continued)

SURVEILLANCE	FREQUENCY
<p>SR 3.8.1.10 -----NOTE----- Credit may be taken for unplanned events that satisfy this SR. -----</p> <p>Verify each DG operating at a power factor ≤ 0.9 does not trip and voltage is maintained ≤ 5000 V during and following a load rejection of a load ≥ 5450 kW and ≤ 5740 kW for DG 11 and DG 12 and ≥ 3300 kW for DG 13.</p>	<p>18 months</p>

(continued)

SURVEILLANCE REQUIREMENTS (continued)

SURVEILLANCE	FREQUENCY
<p>SR 3.8.1.13 -----NOTE----- Credit may be taken for unplanned events that satisfy this SR. -----</p> <p>Verify each DG's automatic trips are bypassed on an actual or simulated ECCS initiation signal except:</p> <ul style="list-style-type: none"> a. Engine overspeed; b. Generator differential current; and c. Low lube oil pressure for DG 11 and DG 12. 	<p>18 months</p>

(continued)

SURVEILLANCE REQUIREMENTS (continued)

SURVEILLANCE	FREQUENCY
<p>SR 3.8.1.17 -----NOTE----- Credit may be taken for unplanned events that satisfy this SR. -----</p> <p>Verify, with a DG operating in test mode and connected to its bus, an actual or simulated ECCS initiation signal overrides the test mode by:</p> <ul style="list-style-type: none"> a. Returning DG to ready-to-load operation; and b. Automatically energizing the emergency loads from offsite power. 	<p>18 months</p>
<p>SR 3.8.1.18 -----NOTE----- This Surveillance shall not be performed in MODE 1, 2, or 3. However, credit may be taken for unplanned events that satisfy this SR. -----</p> <p>Verify interval between each sequenced load block is within $\pm 10\%$ of design interval for each automatic load sequencer.</p>	<p>18 months</p>

(continued)