

**Project:**

**TRICON v10 NUCLEAR QUALIFICATION PROJECT**




Non -Proprietary copy per 10CFR2.390  
 - Areas of proprietary information have been redacted.  
 - Designation letter corresponds to Triconex proprietary policy categories (Ref. transmittal number NRC-V10-09-001, Affidavit, Section 4.)

## EMI/RFI TEST REPORT

**Document No: 9600164-527**

**Revision 2**

**April 30, 2008**

	Name	Signature	Title
Author:	Steve Landas	See attached	R&D Engineer
Reviewers:	Ravindar Baskaran	See attached	Independent Review Engineer
	Frank Kloer		Project Engineer
	George Hughes		Project QA Engineer
Approval:	Naresh Desai		Project Manager

Project:	TRICON v10 NUCLEAR QUALIFICATION PROJECT
<p><b>EMI/RFI          TEST REPORT</b></p> <p>Document No: 9600164-527</p> <p>Revision 2</p> <p>April 30, 2008</p>	

	Name	Signature	Title
Author:	Steve Landas		R&D Engineer
Reviewers:	Ravindar Baskaran		Independent Review Engineer
	Frank Kloer		Project Engineer
	George Hughes		Project QA Engineer
Approval:	Naresh Desai		Project Manager

<b>Project:</b>	<b>TRICON v10 NUCLEAR QUALIFICATION PROJECT</b>
-----------------	---

## EMI/RFI TEST REPORT

**Document No: 9600164-527**

**Revision 2**

**April 30, 2008**

	Name	Signature	Title
<b>Author:</b>	Steve Landas		R&D Engineer
<b>Reviewers:</b>	Ravindar Baskaran		Independent Review Engineer
	Frank Kloer		Project Engineer
	George Hughes		Project QA Engineer
<b>Approval:</b>	Naresh Desai		Project Manager

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	2 of 49	<b>Date:</b>	04/30/08

<b>Document Change History</b>			
<b>Revision</b>	<b>Date</b>	<b>Change</b>	<b>Preparer</b>
0	07/20/07	Initial Issue	M. Albers
1	07/26/07	Incorporated results of Triconex Qualification Project Anomaly Report (QPAR) No. 055	M. Albers
2	04/30/08	Added Supplement 1. Revised Reference 9.29 in response to NUPIC audit corrective action (Reference CAR 2528-1).	S. Landas

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	3 of 49	<b>Date:</b>	04/30/08

## TABLE OF CONTENTS

<u>Section</u>	<u>Page</u>
<b>1.0 EXECUTIVE SUMMARY</b>	<b>4</b>
<b>2.0 PURPOSE</b>	<b>8</b>
<b>3.0 TEST OBJECTIVE</b>	<b>8</b>
<b>4.0 DESCRIPTION OF TEST SPECIMEN</b>	<b>8</b>
<b>5.0 TEST SETUP AND INSTRUMENTATION</b>	<b>9</b>
<b>6.0 TEST PROCEDURES</b>	<b>12</b>
<b>7.0 TEST RESULTS</b>	<b>17</b>
<b>8.0 CONCLUSIONS</b>	<b>39</b>
<b>9.0 REFERENCES</b>	<b>46</b>
<b>10.0 ATTACHMENTS</b>	
<b>Attachment 1:</b> Example Plots of TUT Normal Operating Data	
<b>11.0 SUPPLEMENTS</b>	
<b>Supplement 1:</b> Supplemental Testing to IEC 61000-4-16, Short Duration Disturbance at 0 Hz (DC)	

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	4 of 49	<b>Date:</b>	04/30/08

## 1.0 EXECUTIVE SUMMARY

The TRICON v10 Nuclear Qualification Project Electromagnetic Interference / Radiofrequency Interference (EMI/RFI) Test was performed on February 16 to April 17, 2007 at National Technical Systems (NTS) Laboratories in Boxborough, Massachusetts. As required by Triconex Document No. 9600164-500, “Master Test Plan,” (Reference 9.1), the EMI/RFI Test was executed to demonstrate acceptable performance of the TRICON v10 Programmable Logic Controller (PLC) in accordance with the EMI/RFI criteria specified in U.S. Nuclear Regulatory Commission (NRC) Regulatory Guide (RG) 1.180, Revision 1, “Guidelines for Evaluating Electromagnetic and Radio-Frequency Interference in Safety-Related Instrumentation and Control Systems,” (Reference 9.2).

MPR Procedure No. 9600164-510, “EMI/RFI Test Procedure,” (Reference 9.3) was developed in accordance with the requirements of NRC RG 1.180 (Reference 9.2), EPRI TR-107330, “Generic Requirements Specification for Qualifying a Commercially Available PLC for Safety-Related Applications in Nuclear Power Plants,” (Reference 9.4), Triconex Document No. 9600164-500 (Reference 9.1), and Triconex Document No. 9600164-002, “Nuclear Qualification Quality Plan,” (Reference 9.5). The procedure included steps to direct: 1) proper setup of the TRICON-Under-Test (TUT) and test system prior to testing, 2) measurement of EMI/RFI emissions from the TUT components, 3) application of EMI/RFI disturbance signals to the TUT components, 4) acquisition of TUT operational parameters during testing, and 5) evaluation of acceptable TUT performance during testing. The TUT executed a verified and validated Test Specimen Application Program (TSAP) throughout EMI/RFI Testing. The TSAP revision used was “V10\_TSAP\_REV\_0”. EMI/RFI Testing was performed by MPR certified Project Test Engineers and witnessed by Triconex Project Quality Assurance.

Triconex Drawing No. 9600164-100, “TRICON v10 Nuclear Qualification Project TRICON-Under-Test, General Arrangement,” (Reference 9.6), shows the basic configuration of the TUT components for EMI/RFI Testing.

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	5 of 49	<b>Date:</b>	04/30/08

a

The following EMI/RFI emissions tests were performed in accordance with Department of Defense Interface Standard MIL-STD-461E, “Requirements for the Control of Electromagnetic Interference Characteristics of Subsystems and Equipment,” (Reference 9.7):

- MIL-STD-461E, Test Method CE101, Conducted Emissions, 30 Hz to 10 kHz
- MIL-STD-461E, Test Method CE102, Conducted Emissions, 10 kHz to 2 MHz
- MIL-STD-461E, Test Method RE101, Radiated Emissions, 30 Hz to 100 kHz
- MIL-STD-461E, Test Method RE102, Radiated Emissions, 2 MHz to 1 GHz

The following EMI/RFI susceptibility tests were performed in accordance with the referenced International Electrotechnical Commission (IEC) Standards:

- IEC Standard 61000-4-3, “Electromagnetic Compatibility (EMC), Part 4-3: Testing and Measurement Techniques, Radiated, Radio-Frequency, Electromagnetic Field Immunity Test,” (Reference 9.8), 26 MHz to 1 GHz
- IEC Standard 61000-4-6, “Electromagnetic Compatibility (EMC), Part 4-6: Testing and Measurement Techniques, Immunity to Conducted Disturbances, Induced by Radio-Frequency Fields,” (Reference 9.9), 150 kHz to 80 MHz
- IEC Standard 61000-4-8, “Electromagnetic Compatibility (EMC), Part 4-8: Testing and Measurement Techniques, Power Frequency Magnetic Field Immunity Test,” (Reference 9.10)
- IEC Standard 61000-4-9, “Electromagnetic Compatibility (EMC), Part 4-9: Testing and Measurement Techniques, Pulse Magnetic Field Immunity Test,” (Reference 9.11)
- IEC Standard 61000-4-10, “Electromagnetic Compatibility (EMC), Part 4-10: Testing and Measurement Techniques, Damped Oscillatory Magnetic Field Immunity Test,” (Reference 9.12)
- IEC Standard 61000-4-13, “Electromagnetic Compatibility (EMC), Part 4-13: Testing and Measurement Techniques, Harmonics and Interharmonics Including Mains Signaling at A.C. Power Port, Low Frequency Immunity Tests,” (Reference 9.13)
- IEC Standard 61000-4-16, “Electromagnetic Compatibility (EMC), Part 4-16: Testing and Measurement Techniques, Test for Immunity to Conducted, Common Mode Disturbances in the Frequency Range 0 Hz to 150 kHz,” (Reference 9.14)

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	6 of 49	<b>Date:</b>	04/30/08

The EMI/RFI emissions test results demonstrate that the Triconex TRICON v10 PLC does not fully comply with the allowable emissions levels of NRC RG 1.180 (Reference 9.2) for MIL-STD-461E, CE101 and CE102 testing. The Triconex TRICON v10 PLC does fully comply with the allowable emissions levels of NRC RG 1.180 for MIL-STD-461E, RE101 and RE102 testing.

The EMI/RFI susceptibility test results show that the TRICON v10 PLC system complies with the minimum susceptibility levels required by NRC RG 1.180 (Reference 9.2). The main processors continued to function correctly throughout testing. The transfer of input and output data was not interrupted. There were no interruptions or inconsistencies in the operation of the system or the software.

The EMI/RFI susceptibility test results show that the following TRICON v10 PLC input/output hardware does not fully comply with the minimum susceptibility thresholds required by NRC RG 1.180 (Reference 9.2) for the listed susceptibility tests:

IEC Standard 61000-4-3 Testing

- RTD Signal Conditioning Module 1600083-600 (threshold levels determined)
- RTD Signal Conditioning Module 1600083-200 (threshold levels determined)
- RTD Signal Conditioning Module 1600024-030 (threshold levels determined)
- RTD Signal Conditioning Module 1600024-020 (threshold levels determined)

IEC Standard 61000-4-6 Testing

- RTD Signal Conditioning Module 1600081-001 (no threshold levels determined)
- Digital Output Module 3601T (115 VAC) w/ ETP 9663-610N (threshold levels determined)

IEC Standard 61000-4-16 Testing

- Digital Input Module 3503E (24V AC/DC) w/ ETP 9563-810N (threshold levels determined)
- Digital Output Module 3625 (24V DC) w/ ETP 9662-810N (threshold levels determined)
- Digital Output Module 3625 (24V DC) w/ ETP 9662-610N (threshold levels determined)

**NOTE: The susceptibility test results given above are contingent on a TRICON v10 PLC installation design that separates and isolates the 24 VDC field power supplies to the discrete and analog input and output module circuits.**

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	7 of 49	<b>Date:</b>	04/30/08

The specific TRICON v10 PLC hardware which was tested (chassis, power supplies, modules, external termination assemblies and interconnecting cabling) is identified in Triconex Document No. 9600164-540, “Master Configuration List,” (Reference 9.15).

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	8 of 49	<b>Date:</b>	04/30/08

## 2.0 PURPOSE

The purpose of this test report is to summarize the results of EMI/RFI Testing of the TRICON v10 Nuclear Qualification Project TRICON-Under-Test (TUT) to meet the requirements of NRC RG 1.180 (Reference 9.2). The format of this test report conforms to Section 8.3.(4) of IEEE Standard 323-1974, “Standard for Qualifying Class 1E Equipment for Nuclear Power Generating Stations,” (Reference 9.16).

Details regarding the performance and results of the EMI/RFI Testing are recorded in the completed MPR Procedure No. 9600164-510, “EMI/RFI Test Procedure,” (Reference 9.17). Conclusions from the EMI/RFI Testing are provided in Section 8.0 of this test report.

## 3.0 TEST OBJECTIVE

NRC RG 1.180 (Reference 9.2) states that EMI/RFI Testing is required to demonstrate compliance with NRC regulations on testing to address the effects of EMI/RFI and power surges on safety-related instrumentation and control systems. Appendix 8 of Triconex Document No. 9600164-500 (Reference 9.1) states that EMI/RFI Testing shall demonstrate acceptable performance of the TRICON v10 Programmable Logic Controller (PLC) in accordance with the EMI/RFI criteria specified in NRC RG 1.180. MPR Procedure No. 9600164-510 (Reference 9.3) states that EMI/RFI Testing shall demonstrate the suitability of the TRICON v10 PLC for qualification as a safety-related device with respect to EMI/RFI emissions and susceptibility levels.

## 4.0 DESCRIPTION OF TEST SPECIMEN

The equipment tested consists of four TRICON v10 PLC chassis populated with selected main processor, input, output, communication, chassis interface and chassis power supply modules. The tested equipment also includes external termination panels (ETPs) provided for connection of field wiring to the TRICON v10 input and output modules, and interfacing cable assemblies for connection of the ETPs to the TRICON v10 chassis and for interconnection of the TRICON v10 chassis.

Triconex Drawing No. 9600164-100 (Reference 9.6), shows the basic configuration of the TUT components for EMI/RFI Testing. Triconex Drawing No. 9600164-103, “TRICON v10 Nuclear Qualification Project System Block Diagram,” (Reference 9.18), shows the general arrangement and interconnection of the TUT chassis. Triconex Document No. 9600164-541, “TRICON v10 Nuclear Qualification Project, System Description,” (Reference 9.19), provides an overview and description of the TUT and test system. A detailed identification of the tested equipment is provided in Triconex Document No. 9600164-540 (Reference 9.15).

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	9 of 49	<b>Date:</b>	04/30/08

During testing, the TUT was executing a Test Specimen Application Program (the TSAP) developed specifically for the qualification project and designed to support the test procedures, which demonstrate the functionality of the TUT during all phases of qualification testing. Requirements for operation of the TSAP are defined in Triconex Document No. 9600164-517, “Test Specimen Application Program (TSAP) Software Requirements Specification (SRS),” (Reference 9.20). The completed MPR Procedure No. 9600164-510 (Reference 9.17) identifies the TSAP revision used during this testing as “V10\_TSAP\_REV\_0”. Triconex Document No. 9600164-540 (Reference 9.15) identifies the revision level of all TUT firmware.

## 5.0 TEST SETUP AND INSTRUMENTATION

The following sections describe the setup of the TUT during EMI/RFI Testing, the instrumentation used to generate and measure the applied EMI/RFI test conditions, and the instrumentation used to measure TUT performance during and after testing. The TUT setup is documented in the completed MPR Procedure No. 9600164-510 (Reference 9.17). Specifications for test instrumentation supplied by NTS Laboratories are included in NTS Test Procedure No. TP62987-07N-EMI, “Test Procedure for EMI/RFI Testing of the TRICON v10 Nuclear Qualification Project TRICON-Under-Test,” (Reference 9.21).

### 5.1 TRICON-Under-Test Mounting

a
---

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	10 of 49	<b>Date:</b>	04/30/08

## 5.2 TRICON-Under-Test Chassis and Module Configuration

Section 4.0 above describes the general arrangement of the TUT which was maintained throughout all of the qualification testing. Chassis configurations for EMI/RFI Testing are documented in Triconex Document No. 9600164-540 (Reference 9.15).

## 5.3 TRICON-Under-Test Power Supply and Wiring Configuration

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	11 of 49	<b>Date:</b>	04/30/08

a

**5.4 NTS Instrumentation**


NTS provided the test instrumentation for generating, applying, and monitoring the EMI/RFI Test signals. NTS also provided instrumentation for measuring temperature and relative humidity inside the anechoic test chamber during EMI/RFI Testing. These instruments are identified in NTS Test Report No. TR62987-07N-EMI (Reference 9.29).

**5.5 Triconex and MPR Instrumentation**

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	12 of 49	<b>Date:</b>	04/30/08

Details on the identification, configuration and calibration of the test instrumentation described above are included in the completed MPR Procedure No. 9600164-510 (Reference 9.17), and the completed Pre-EMI/RFI Testing Run No. 3.6 of Triconex Procedure No. 9600164-502, “System Setup and Checkout Procedure,” (Reference 9.31). The completed MPR Procedure



**5.6 Instrument Calibration**

All tests were performed using calibrated test instruments. Calibration certifications are held by NTS, MPR and Triconex. NTS Test Report No. TR62987-07N-EMI (Reference 9.29) documents the calibration status of the test instrumentation used by NTS. The completed MPR Procedure No. 9600164-510 (Reference 9.17) documents the calibration status of the test instrumentation used by MPR. The completed Triconex Procedure No. 9600164-502 (Reference 9.31) documents the calibration status of the test instrumentation used by Triconex.

**6.0 TEST PROCEDURES**

EMI/RFI Testing of the TUT was performed to the requirements of Sections 3 and 4 of NRC RG 1.180 (Reference 9.2). Section 3 of NRC RG 1.180 addresses EMI/RFI emissions testing. Section 4 of NRC RG 1.180 addresses EMI/RFI susceptibility testing. Each section endorses both Military Standard MIL-STD-461E series and IEC 61000 series EMI/RFI test methods. The qualifier has the option to use either series of test methods, although NRC RG 1.180 stipulates that for emissions or susceptibility testing, the chosen series of test methods must be applied in its entirety (i.e., there should be no selective application or mixing of the MIL-STD and IEC test methods).

EMI/RFI emissions testing of the TUT included both radiated and conducted emissions testing done to the MIL-STD-461E series test methods (Reference 9.7) specified in Section 3 of NRC RG 1.180 (Reference 9.2). EMI/RFI susceptibility testing of the TUT included both radiated and conducted susceptibility testing done to the IEC 61000 series test methods (References 9.8 through 9.14) specified in Section 4 of NRC RG 1.180, Rev. 1 (Reference 9.2).

The following sections describe the approach to satisfying the requirements of the referenced documents for EMI/RFI Testing of the TUT. The test procedure used by NTS to perform EMI/RFI Testing of the TUT is NTS Test Procedure No. TP62987-07N-EMI (Reference 9.21). The test procedure used by MPR to perform EMI/RFI Testing of the TUT is MPR Procedure No. 9600164-510 (Reference 9.3).

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	13 of 49	<b>Date:</b>	04/30/08

## 6.1 Test Sequence

Figure 2 of Triconex Document No. 9600164-500 (Reference 9.1) shows the sequence of qualification testing performed on the TUT. In accordance with the test sequence shown in Figure 2, EMI/RFI Testing was performed after Radiation Exposure, Environmental, and Seismic Testing, and prior to Electrical Fast Transient Testing, Surge Withstand, Electrostatic Discharge and Class 1E to Non-1E Isolation Testing.

## 6.2 Test Method

Section 3 of NRC RG 1.180 (Reference 9.2) includes the requirements for EMI/RFI emissions testing of safety-related instrumentation and control (I&C) systems. EMI/RFI emissions testing of the TUT included both radiated and conducted emissions testing done to the following MIL-STD-461E series test methods (Reference 9.7):

- MIL-STD-461E, Test Method CE101, Conducted Emissions, Low Frequency (30 Hz to 10 kHz), AC and DC Power Leads
- MIL-STD-461E, Test Method CE102, Conducted Emissions, High Frequency (10 kHz to 2 MHz), AC and DC Power Leads
- MIL-STD-461E, Test Method RE101, Radiated Emissions, Magnetic Field (30 Hz to 100 kHz), TUT Surfaces and Leads
- MIL-STD-461E, Test Method RE102, Radiated Emissions, Electric Field (2 MHz to 1 GHz), Antenna Measurement

Section 4 of NRC RG 1.180 (Reference 9.2) includes the requirements for EMI/RFI susceptibility testing of safety-related instrumentation and control (I&C) systems. EMI/RFI susceptibility testing of the TUT included both radiated and conducted testing done to the following IEC series test methods:

- IEC Standard 61000-4-3, Radiated Susceptibility, High Frequency (26 MHz to 1 GHz), Antenna Exposure (Reference 9.8)
- IEC Standard 61000-4-6, Conducted Susceptibility, Radio Frequency (150 kHz to 80 MHz), Power and Signal Leads (Reference 9.9)
- IEC Standard 61000-4-8, Radiated Susceptibility, Power Line Frequency (60 Hz) Magnetic Field, Helmholtz Coil Exposure (Reference 9.10)
- IEC Standard 61000-4-9, Radiated Susceptibility, Pulsed Magnetic Field, Helmholtz Coil Exposure (Reference 9.11)

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	14 of 49	<b>Date:</b>	04/30/08

- IEC Standard 61000-4-10, Radiated Susceptibility, Damped Oscillatory Magnetic Field (100 kHz and 1 MHz), Helmholtz Coil Exposure (Reference 9.12)
- IEC Standard 61000-4-13, Conducted Susceptibility, Harmonics and Interharmonics (16 Hz to 2.4 kHz), Power Leads (Reference 9.13)
- IEC Standard 61000-4-16, Conducted Susceptibility, Common-Mode Disturbances (15 Hz to 150 kHz), Power and Signal Leads (Reference 9.14)

### 6.3 Test Levels

The following lists the EMI/RFI Testing emissions acceptance levels and applied susceptibility test levels from the applicable figures and tables of NRC RG 1.180 (Reference 9.2).

<u>EMI/RFI Emissions Test Method</u>	<u>NRC RG 1.180, Rev. 1 Acceptance Level</u>
MIL-STD-461E, CE101	Figure 3.1
MIL-STD-461E, CE102	Figure 3.2
MIL-STD-461E, RE101	Figure 3.3
MIL-STD-461E, RE102	Figure 3.4

<u>EMI/RFI Susceptibility Test Method</u>	<u>NRC RG 1.180, Rev. 1 Test Level</u>
IEC Standard 61000-4-3	Sect. 4.3.3: 10 V/m
IEC Standard 61000-4-6	Sect. 4.1.2: Power Leads, 140 dB $\mu$ V
IEC Standard 61000-4-6	Table 15: Signal Leads, 130 dB $\mu$ V
IEC Standard 61000-4-8	Table 19: Continuous, 30 A/m
IEC Standard 61000-4-8	Table 19: Short Duration, 300 A/m
IEC Standard 61000-4-9	Table 19: 300 A/m
IEC Standard 61000-4-10	Table 19: 30 A/m
IEC Standard 61000-4-13	Table 10: See Table 10
IEC Standard 61000-4-16	Table 11: Power Leads, See Table 11
IEC Standard 61000-4-16	Table 11: Signal Leads: 3/10 of Power Leads

### 6.4 TRICON-Under-Test Operation

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	15 of 49	<b>Date:</b>	04/30/08

a

## 6.5 TRICON-Under-Test Performance Monitoring

Appendix 7 of Triconex Document No. 9600164-500 (Reference 9.1) and Section 6.6 of this test report list the EMI/RFI Test acceptance criteria. Appendix 7 states that monitoring of normal TUT operation during EMI/RFI Testing will demonstrate satisfaction of the acceptance criteria. In order to clarify the definition of normal operation, Appendix 7 provides the following additional EMI/RFI Testing acceptance criteria adapted from Section 4.3.7 of EPRI TR-107330 (Reference 9.4):

- i.) The main processors shall continue to function.
- ii.) The transfer of I/O data shall not be permanently interrupted.
- iii.) The applied EMI/RFI disturbances shall not cause the discrete I/O to change state.
- iv.) Analog I/O levels shall not vary more than 3% (of full scale).

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	16 of 49	<b>Date:</b>	04/30/08

a

## 6.6 Test Acceptance Criteria

The following EMI/RFI Test acceptance criteria are as given in Appendix 7 of Triconex Document No. 9600164-500 (Reference 9.1), and Section 4.3.7 of EPRI TR-107330 (Reference 9.4).

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	17 of 49	<b>Date:</b>	04/30/08

- a) The TUT shall meet allowable equipment emission limits as specified in Section 3 of NRC RG 1.180 (Reference 9.2) for the following MIL-STD-461E Emissions Test Methods:

- CE101 – Conducted Emissions, 30 Hz to 10 kHz (NRC RG 1.180, Figure 3.1)
- CE102 – Conducted Emissions, 10 kHz to 2 MHz (NRC RG 1.180, Figure 3.2)
- RE101 – Radiated Emissions, 30 Hz to 100 kHz (NRC RG 1.180, Figure 3.3)
- RE102 – Radiated Emissions, 2 MHz to 1 GHz (NRC RG 1.180, Figure 3.4)

- b) The TUT shall operate as intended during and after application of the EMI/RFI test levels specified in Section 4 of NRC RG 1.180 (Reference 9.2) for the following IEC Standard Susceptibility Test Methods:

- IEC 61000-4-3 – Radiated Susceptibility, High Frequency, 26 MHz to 1 GHz
- IEC 61000-4-6 – Conducted Susceptibility, Radio Frequency, 150 kHz to 80 MHz
- IEC 61000-4-8 – Radiated Susceptibility, Magnetic Field, 60 Hz
- IEC 61000-4-9 – Radiated Susceptibility, Pulsed Magnetic Field
- IEC 61000-4-10 – Radiated Susceptibility, Damped Magnetic Field, 100 kHz and 1 MHz
- IEC 61000-4-13 – Conducted Susceptibility, Harmonics/Interharmonics, 16 Hz to 2.4 kHz
- IEC 61000-4-16 – Conducted Susceptibility, Common Mode Disturb., 15 Hz to 150 kHz

Evaluation of normal operating performance data (inputs, outputs and diagnostic indicators) shall demonstrate operation as intended, including the following specific operational performance from Section 4.3.7 of EPRI TR-107330 (Reference 9.4):

- i.) The main processors shall continue to function.
- ii.) The transfer of I/O data shall not be interrupted.
- iii.) The emissions shall not cause the discrete I/O to change state.
- iv.) Analog I/O levels shall not vary more than 3%.

## 7.0 TEST RESULTS

This section summarizes the results of EMI/RFI Testing of the TUT. This section also discusses performance or data anomalies which were observed or recorded during the testing.

### 7.1 EMI/RFI Test Setup and Checkout Testing

Triconex Procedure No. 9600164-502, “System Setup and Checkout Procedure,” (Reference 9.32) directs setup of the TUT for the different qualification tests to be performed, and verifies proper operation of the TUT and test system prior to start of testing. EMI/RFI Testing of the TUT was performed following Seismic Testing and upon completion of the Pre-EMI/RFI Testing Run No. 3.6 of Triconex Procedure No. 9600164-502 (Reference 9.31).

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	18 of 49	<b>Date:</b>	04/30/08

Results of Reference 9.31 show that the system was operating correctly prior to start of EMI/RFI Testing.

## 7.2 EMI/RFI Testing

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	19 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	20 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	21 of 49	<b>Date:</b>	04/30/08

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	22 of 49	<b>Date:</b>	04/30/08

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	23 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	24 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	25 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	26 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	27 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	28 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	29 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	30 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	31 of 49	<b>Date:</b>	04/30/08

**Table 7.1: Summary of IEC Standard 61000-4-16 Final Test Results**

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	32 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	33 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	34 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	35 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	36 of 49	<b>Date:</b>	04/30/08

•

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	37 of 49	<b>Date:</b>	04/30/08

### 7.3 Post-EMI/RFI Operability and Prudency Tests

Section 5.5 of EPRI TR-107330 (Reference 9.4) requires Operability and Prudency testing to be performed during EMI/RFI Testing.

a

As reported by Triconex, the completed Performance Proof Test Run No. 3.7 of Triconex Procedure No. 9600164-503, “Operability Test Procedure,” (Reference 9.38) and the completed Performance Proof Test Run No. 3.4 of Triconex Procedure No. 9600164-504, “Prudency Test Procedure,” (Reference 9.39) performed at the completion of all qualification testing demonstrate acceptable system performance following EMI/RFI Testing.

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	38 of 49	<b>Date:</b>	04/30/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	39 of 49	<b>Date:</b>	04/30/08

a

## 8.0 CONCLUSIONS

### 8.1 Test Methodology

EMI/RFI Testing of the TUT was performed in accordance with the applicable requirements of NRC RG 1.180 (Reference 9.2). The following EMI/RFI Tests were performed on the TUT:

- Radiated Magnetic Field Emissions from 30 Hz to 100 kHz (MIL-STD-461E, RE101)
- Radiated Electric Field Emissions from 2 MHz to 1 GHz (MIL-STD-461E, RE102)
- Low Frequency Conducted Emissions from 30 Hz to 10 kHz (MIL-STD-461E, CE101)
- High Frequency Cond. Emissions from 10 kHz to 2 MHz (MIL-STD-461E, CE102)
- High Frequency Radiated Susceptibility from 26 MHz to 1 GHz (IEC 61000-4-3)
- Radio Frequency Conducted Susceptibility from 150 kHz to 80 MHz (IEC 61000-4-6)
- Magnetic Field Radiated Susceptibility at 60 Hz (IEC 61000-4-8)
- Pulsed Magnetic Field Radiated Susceptibility (IEC 61000-4-9)

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	40 of 49	<b>Date:</b>	04/30/08

- Damped Magnetic Field Radiated Suscept. at 100 kHz and 1 MHz (IEC 61000-4-10)
- Harmonics and Interharmonics Conducted Susceptibility (IEC 61000-4-13)
- Common Mode Disturb. Conducted Suscept., 15 Hz to 150 kHz (IEC 61000-4-16)

The specific TRICON v10 PLC hardware which was tested (chassis, power supplies, modules, external termination assemblies and interconnecting cabling) is identified in Triconex Document No. 9600164-540 (Reference 9.15).

Section 5.5 of EPRI TR-107330 (Reference 9.4) requires Operability and Prudence testing to be performed during EMI/RFI Testing. The test system as configured for EMI/RFI Testing did not support Operability or Prudence Testing (see Section 6.5 of this test report). The normal operating performance data recorded during EMI/RFI Testing demonstrates system performance during EMI/RFI exposure.

## 8.2 Emissions Testing

- The TUT fully complies with the allowable equipment emissions levels defined in NRC RG 1.180 (Reference 9.2) for MIL-STD-461E, RE101 and RE102 testing.
- The TUT does not fully comply with the allowable equipment emissions levels defined in NRC RG 1.180 (Reference 9.2) for MIL-STD-461E, CE101 and CE102 testing. Sections 7.2.1 and 7.2.2 of this test report provide a detailed description of the non-compliances in emissions which were measured during CE101 and CE102 testing.

An understanding of the electromagnetic emissions from a device is necessary to minimize the potential for the device to adversely affect the operation of other equipment that is physically located near the device, shares common electrical connections with it, or has wires or cables routed in close proximity to it. Therefore, prior to installing the TRICON v10 PLC in a nuclear safety-related or non-safety related application, an evaluation of the device emission levels should be made to determine whether the emission levels are acceptable for the planned application, or if mitigating actions would be required. The TRICON v10 PLC EMI/RFI emissions testing documented in this report provides the data required to perform such an evaluation. The TRICON v10 PLC was tested without the benefit of a secondary enclosure, additional cable and wire shielding, or installed power line filtering. Mitigating actions to address the non-compliances in measured emission levels would likely incorporate these common in-plant installation features.

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	41 of 49	<b>Date:</b>	04/30/08

### 8.3 Susceptibility Testing

**NOTE: The following susceptibility test results are contingent on a TRICON v10 PLC installation design that separates and isolates the 24 VDC field power supplies to the discrete and analog input and output module circuits.**

- a. The TUT successfully passed all of the EMI/RFI susceptibility tests listed in Section 8.1. The main processors continued to function correctly throughout testing. The transfer of input and output data was not interrupted. There were no interruptions or inconsistencies in the operation of the system or the software.
- b. The TUT main processor, chassis power supply, remote extender, and communication modules fully comply with the minimum susceptibility thresholds required by NRC RG 1.180 (Reference 9.2) for all of the EMI/RFI susceptibility tests listed in Section 8.1.
- c. The EMI/RFI susceptibility test results show that the following TUT discrete and analog input/output hardware does not fully comply with the minimum susceptibility thresholds required by NRC RG 1.180 (Reference 9.2) for the EMI/RFI susceptibility tests listed in Section 8.1:

IEC Standard 61000-4-3 Testing

- RTD Signal Conditioning Module 1600083-600
- RTD Signal Conditioning Module 1600083-200
- RTD Signal Conditioning Module 1600024-030
- RTD Signal Conditioning Module 1600024-020

IEC Standard 61000-4-6 Testing

- RTD Signal Conditioning Module 1600081-001
- Digital Output Module 3601T (115 VAC) w/ ETP 9663-610N

IEC Standard 61000-4-16 Testing

- Digital Input Module 3503E (24V AC/DC) w/ ETP 9563-810N
- Digital Output Module 3625 (24V DC) w/ ETP 9662-810N
- Digital Output Module 3625 (24V DC) w/ ETP 9662-610N

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	42 of 49	<b>Date:</b>	04/30/08

Sections 7.2.5, 7.2.7 and 7.2.11 of this test report provide a detailed description of the module susceptibilities which were measured during each of the tests listed above, and the results of threshold testing which was performed. Module susceptibilities included spurious changes in the state of the discrete inputs and outputs, and variations in RTD input levels of greater than  $\pm 3\%$  of the expected levels.

- d. An understanding of the electromagnetic susceptibility of a device is necessary to ensure that its operation will not be adversely affected by EMI/RFI levels already present or permitted in the area where the device will be located. Therefore, prior to installing the TRICON v10 PLC in a nuclear safety-related application, an evaluation of the input, output and communication module susceptibilities should be performed. An evaluation of the module susceptibilities should also be performed for non-safety related applications if there is a potential for the PLC to impact plant reliability and availability. The TRICON v10 PLC EMI/RFI susceptibility testing documented in this test report provides the data required to perform such an evaluation.

To address the impact of the TRICON v10 PLC input and output module EMI/RFI susceptibilities for a specific plant application, one or more of the following approaches may be pursued:

- i. Demonstrate that the EMI/RFI levels at which the PLC modules are susceptible are not credible threats at the point of installation.
  - ii. Demonstrate that the type of susceptibility failures that occurred during the EMI/RFI Testing will not adversely affect the safety function of the PLC or plant operation. For example, variations in analog input and output levels in excess of  $\pm 3\%$  may not impact the safety-related function of the PLC or adversely affect plant operation.
  - iii. Implement actions to mitigate unacceptable EMI/RFI sources. The TRICON v10 PLC was tested without the benefit of a secondary enclosure, additional cable and wire shielding, or installed power line filtering. Mitigating actions to address module susceptibility levels would likely incorporate these common in-plant installation features. Mitigating actions might also include administrative controls on the EMI/RFI sources.
- e. Tables 8-1 and 8-2 included at the end of this section provide a summary of the EMI/RFI conducted and radiated susceptibility test results for each module installed in the TUT. The purpose of the tables is to identify a set of modules which demonstrated acceptable susceptibility performance at the required test levels specified in NRC RG 1.180 (Reference 9.2).

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	43 of 49	<b>Date:</b>	04/30/08

### 8.4 Post-EMI/RFI Operability and Prudency Testing

As reported by Triconex, the completed Performance Proof Test Run No. 3.7 of Triconex Procedure No. 9600164-503, “Operability Test Procedure,” (Reference 9.38) and the completed Performance Proof Test Run No. 3.4 of Triconex Procedure No. 9600164-504, “Prudency Test Procedure,” (Reference 9.39) demonstrate acceptable system performance following EMI/RFI Testing.

### 8.5 Test Anomalies

Several test anomalies were encountered during EMI/RFI Testing as described in Section 7.5 of this test report. Each of the test anomalies was dispositioned for its impact on the validity of the test results. Test system revisions were made and/or repeat testing was performed as necessary to correct any negative impact the test anomalies may have had on the validity of the test results.

**TABLE 8-1: SUMMARY OF EMI/RFI CONDUCTED SUSCEPTIBILITY TEST RESULTS**

Module Model No.	ETP Model No.	Module Type	IEC 61000-4-6	IEC 61000-4-13	IEC 61000-4-16
			Radio Frequency 150 kHz - 80 MHz	Harmonics and Interharmonics	Common-Mode Disturbances
3008	---	Main Processor	Pass	Pass	Pass
8310	---	Power Supply, 115 VAC	Pass	Pass	Pass
8311	---	Power Supply, 230 VAC	Pass	Pass	Pass
8312	---	Power Supply, 24 VDC	Pass	Pass	Pass
4200	---	Remote Extender	Pass	Pass	Pass
4201	---	Remote Extender	Pass	Pass	Pass
4352A	---	Communication	Pass	Pass	Pass
3511	9794-110N	Pulse Input	Pass	Pass	Pass
3708E	9782-110N	Thermocouple Input	Pass	Pass	Pass
3501T	9561-810N	Digital Input, 115 VAC	Pass	Pass	Pass
	9561-110N	Digital Input, 115 VAC	Pass	Pass	Pass
3623T	9664-810N	Digital Output, 120 VDC	Pass	Pass	Pass
3603T	9664-810N	Digital Output, 120 VDC	Pass	Pass	Pass
3601T	9663-610N	Digital Output, 115 VAC	<b>Susceptible</b>	Pass	Pass
3503E	9563-810N	Digital Input, 24 VDC	Pass	Pass	<b>Susceptible</b>

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	44 of 49	<b>Date:</b>	04/30/08

**TABLE 8-1: SUMMARY OF EMI/RFI CONDUCTED SUSCEPTIBILITY TEST RESULTS**

Module Model No.	ETP Model No.	Module Type	IEC 61000-4-6	IEC 61000-4-13	IEC 61000-4-16
			Radio Frequency 150 kHz - 80 MHz	Harmonics and Interharmonics	Common-Mode Disturbances
3625	9662-810N	Digital Output, 24 VDC	Pass	Pass	<b>Susceptible</b>
	9662-610N	Digital Output, 24 VDC	Pass	Pass	<b>Susceptible</b>
3636T	9668-110N	Relay Output	Pass	Pass	Pass
3607E	9667-810N	Digital Output, 48 VDC	Pass	Pass	Pass
3502E	9562-810N	Digital Input, 48 VDC	Pass	Pass	Pass
3701	9795-610N	Analog Input, 0-10 VDC	Pass	Pass	Pass
	9783-110N	Analog Input, 0-10 VDC	Pass	Pass	Pass
3703E	9790-610N	Analog Input, 0-10 VDC	Pass	Pass	Pass
	9783-110N	Analog Input, 0-10 VDC	Pass	Pass	Pass
3805E	9860-610N	Analog Output, 4-20 mA	Pass	Pass	Pass
3721	9764-310N	RTD, No. 1600083-600	Pass	Pass	Pass
		RTD, No. 1600083-200	Pass	Pass	Pass
		RTD, No. 1600024-040	Pass	Pass	Pass
		RTD, No. 1600024-030	Pass	Pass	Pass
		RTD, No. 1600024-020	Pass	Pass	Pass
		RTD, No. 1600024-010	Pass	Pass	Pass
		mV, No. 1600082-001	Pass	Pass	Pass
RTD, No. 1600081-001	<b>Susceptible</b>	Pass	Pass		
3721	9783-110N	Analog Input, 0-5 VDC	Pass	Pass	Pass
	9790-610N	Analog Input, 0-5 VDC	Pass	Pass	Pass
	9783-110N	Analog Input, 0-5 VDC	Pass	Pass	Pass

**TABLE 8-2: SUMMARY OF EMI/RFI RADIATED SUSCEPTIBILITY TEST RESULTS**

Module Model No.	ETP Model No.	Module Type	IEC 61000-4-3	IEC 61000-4-8	IEC 61000-4-9	IEC 61000-4-10
			High Frequency 26 MHz - 1 GHz	60 Hz Magnetic Field	Pulsed Magnetic Field	Oscillatory Magnetic Field
3008	---	Main Processor	Pass	Pass	Pass	Pass
8310	---	Power Supply, 115 VAC	Pass	Pass	Pass	Pass
8311	---	Power Supply, 230 VAC	Pass	Pass	Pass	Pass
8312	---	Power Supply, 24 VDC	Pass	Pass	Pass	Pass

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	45 of 49	<b>Date:</b>	04/30/08

**TABLE 8-2: SUMMARY OF EMI/RFI RADIATED SUSCEPTIBILITY TEST RESULTS**

Module Model No.	ETP Model No.	Module Type	IEC 61000-4-3	IEC 61000-4-8	IEC 61000-4-9	IEC 61000-4-10
			High Frequency 26 MHz - 1 GHz	60 Hz Magnetic Field	Pulsed Magnetic Field	Oscillatory Magnetic Field
4200	---	Remote Extender	Pass	Pass	Pass	Pass
4201	---	Remote Extender	Pass	Pass	Pass	Pass
4352A	---	Communication	Pass	Pass	Pass	Pass
3511	9794-110N	Pulse Input	Pass	Pass	Pass	Pass
3708E	9782-110N	Thermocouple Input	Pass	Pass	Pass	Pass
3501T	9561-810N	Digital Input, 115 VAC	Pass	Pass	Pass	Pass
	9561-110N	Digital Input, 115 VAC	Pass	Pass	Pass	Pass
3623T	9664-810N	Digital Output, 120 VDC	Pass	Pass	Pass	Pass
3603T	9664-810N	Digital Output, 120 VDC	Pass	Pass	Pass	Pass
3601T	9663-610N	Digital Output, 115 VAC	Pass	Pass	Pass	Pass
3503E	9563-810N	Digital Input, 24 VDC	Pass	Pass	Pass	Pass
3625	9662-810N	Digital Output, 24 VDC	Pass	Pass	Pass	Pass
3636T	9668-110N	Relay Output	Pass	Pass	Pass	Pass
3607E	9667-810N	Digital Output, 48 VDC	Pass	Pass	Pass	Pass
3502E	9562-810N	Digital Input, 48 VDC	Pass	Pass	Pass	Pass
3701	9795-610N	Analog Input, 0-10 VDC	Pass	Pass	Pass	Pass
	9783-110N	Analog Input, 0-10 VDC	Pass	Pass	Pass	Pass
3703E	9790-610N	Analog Input, 0-10 VDC	Pass	Pass	Pass	Pass
	9783-110N	Analog Input, 0-10 VDC	Pass	Pass	Pass	Pass
3805E	9860-610N	Analog Output, 4-20 mA	Pass	Pass	Pass	Pass
3721	9764-310N	RTD, No. 1600083-600	<b>Susceptible</b>	Pass	Pass	Pass
		RTD, No. 1600083-200	<b>Susceptible</b>	Pass	Pass	Pass
		RTD, No. 1600024-040	Pass	Pass	Pass	Pass
		RTD, No. 1600024-030	<b>Susceptible</b>	Pass	Pass	Pass
		RTD, No. 1600024-020	<b>Susceptible</b>	Pass	Pass	Pass
		RTD, No. 1600024-010	Pass	Pass	Pass	Pass
		mV, No. 1600082-001	Pass	Pass	Pass	Pass
RTD, No. 1600081-001	Pass	Pass	Pass	Pass		
3721	9783-110N	Analog Input, 0-5 VDC	Pass	Pass	Pass	Pass
	9790-610N	Analog Input, 0-5 VDC	Pass	Pass	Pass	Pass
	9783-110N	Analog Input, 0-5 VDC	Pass	Pass	Pass	Pass

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	46 of 49	<b>Date:</b>	04/30/08

## 9.0 REFERENCES

*Note: Triconex qualification project documentation and hardware are configuration controlled under the Triconex Quality Assurance Program. Triconex Document No. 9600164-540, “Master Configuration List,” (Reference 9.15) provides a record of the currently applicable revision level of all Triconex documents, procedures and drawings throughout performance of the qualification program. As recorded in the completed MPR Procedure No. 9600164-510 (Reference 9.17), Triconex Document No. 9600164-540, Rev. 10 was in effect at the start of EMI/RFI Testing.*

- 9.1 Triconex Document No. 9600164-500, “Master Test Plan,” Rev. 4
- 9.2 U.S. Nuclear Regulatory Commission Regulatory Guide 1.180, Revision 1, “Guidelines for Evaluating Electromagnetic and Radio-Frequency Interference in Safety-Related Instrumentation and Control Systems,” October 2003
- 9.3 MPR Procedure No. 9600164-510, “EMI/RFI Test Procedure,” Rev. 0
- 9.4 EPRI TR-107330, “Generic Requirements Specification for Qualifying a Commercially Available PLC for Safety-Related Applications in Nuclear Power Plants,” Final Report dated December, 1996
- 9.5 Triconex Document No. 9600164-002, “Nuclear Qualification Quality Plan,” Rev. 3
- 9.6 Triconex Drawing No. 9600164-100, “TRICON v10 Nuclear Qualification Project TRICON Under Test - General Arrangement,” Rev. 1
- 9.7 Department of Defense Interface Standard MIL-STD-461E, “Requirements for the Control of Electromagnetic Interference Characteristics of Subsystems and Equipment,” August 20, 1999
- 9.8 IEC Standard 61000-4-3, “Electromagnetic Compatibility (EMC), Part 4-3: Testing and Measurement Techniques, Radiated, Radio-Frequency, Electromagnetic Field Immunity Test,” September 2002
- 9.9 IEC Standard 61000-4-6, “Electromagnetic Compatibility (EMC), Part 4-6: Testing and Measurement Techniques, Immunity to Conducted Disturbances, Induced by Radio-Frequency Fields,” November 2004

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	47 of 49	<b>Date:</b>	04/30/08

- 9.10** IEC Standard 61000-4-8, “Electromagnetic Compatibility (EMC), Part 4-8: Testing and Measurement Techniques, Power Frequency Magnetic Field Immunity Test,” March 2001
- 9.11** IEC Standard 61000-4-9, “Electromagnetic Compatibility (EMC), Part 4-9: Testing and Measurement Techniques, Pulse Magnetic Field Immunity Test,” March 2001
- 9.12** IEC Standard 61000-4-10, “Electromagnetic Compatibility (EMC), Part 4-10: Testing and Measurement Techniques, Damped Oscillatory Magnetic Field Immunity Test,” March 2001
- 9.13** IEC Standard 61000-4-13, “Electromagnetic Compatibility (EMC), Part 4-13: Testing and Measurement Techniques, Harmonics and Interharmonics Including Mains Signaling at A.C. Power Port, Low Frequency Immunity Tests,” March 2002
- 9.14** IEC Standard 61000-4-16, “Electromagnetic Compatibility (EMC), Part 4-16: Testing and Measurement Techniques, Test for Immunity to Conducted, Common Mode Disturbances in the Frequency Range 0 Hz to 150 kHz,” July 2002
- 9.15** Triconex Document No. 9600164-540, “Master Configuration List,” Rev. 18
- 9.16** IEEE Standard 323-1974, “Standard for Qualifying Class 1E Equipment for Nuclear Power Generating Stations”
- 9.17** Completed MPR Procedure No. 9600164-510, “EMI/RFI Test Procedure,” Rev. 0, MPR Review and Approval Dated July 16, 2007
- 9.18** Triconex Drawing No. 9600164-103, “TRICON v10 Nuclear Qualification Project System Block Diagram,” Rev. 2
- 9.19** Triconex Document No. 9600164-541, “TRICON v10 Nuclear Qualification Project, System Description,” Rev. 0
- 9.20** Triconex Document No. 9600164-517, “Test Specimen Application Program (TSAP) Software Requirements Specification (SRS),” Rev. 3
- 9.21** National Technical Systems Test Procedure No. TP62987-07N-EMI, “Test Procedure for Electromagnetic Compatibility Qualification of the TRICON v10 Nuclear Qualification Project TRICON-Under-Test,” Rev. 0
- 9.22** Triconex Drawing No. 9600164-201, Sheets 1 and 2, “TRICON v10 Nuclear Qualification Project - Power Distribution Wiring Diagram,” Rev. 1

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	48 of 49	<b>Date:</b>	04/30/08

- 9.23** Triconex Drawing No. 9600164-202, Sheet 1, “TRICON v10 Nuclear Qualification Project - Test Chassis #1 Power Distribution Wiring Diagram,” Rev. 0
- 9.24** Triconex Drawing No. 9600164-203, Sheets 1 and 2, “TRICON v10 Nuclear Qualification Project - Test Chassis #2 Power Distribution Wiring Diagram,” Rev. 0
- 9.25** Triconex Drawing No. 9600164-204, Sheets 1 and 2, “TRICON v10 Nuclear Qualification Project - Test Chassis #3 Power Distribution Wiring Diagram,” Rev. 0
- 9.26** Triconex Drawing No. 9600164-205, Sheets 1 and 2, “TRICON v10 Nuclear Qualification Project - Test Chassis #4 Power Distribution Wiring Diagram,” Rev. 2
- 9.27** Triconex Drawing No. 9600164-206, Sheet 1, “TRICON v10 Nuclear Qualification Project - Simulator Chassis #5 Power Distribution Wiring Diagram,” Rev. 0
- 9.28** Triconex Drawing No. 9600164-207, Sheet 1, “TRICON v10 Nuclear Qualification Project - Simulator Chassis #6 Power Distribution Wiring Diagram,” Rev. 0
- 9.29** National Technical Systems Test Report No. TR62987-07N-EMI, “Test Report for Electromagnetic Compatibility Qualification of the TRICON v10 Nuclear Qualification Project TRICON-Under-Test,” Rev. 1
- 9.30** Triconex Document No. 9600164-700, “TRICON v10 Nuclear Qualification Project Wiring Schedule,” Rev. 3
- 9.31** Completed Pre-EMI/RFI Testing Run No. 3.6 of Triconex Procedure No. 9600164-502, “System Setup and Checkout Procedure,” Rev. 4
- 9.32** Triconex Procedure No. 9600164-502, “System Setup and Checkout Procedure,” Rev. 4
- 9.33** Triconex Qualification Project Anomaly Report (QPAR) No. 045, “Isolation Ground Resistance (Chassis 3 and Chassis 4)”
- 9.34** MPR Nonconformance Report NCR-2007-04 dated March 9, 2007, “Incorrect Configuration of TRICON-Under-Test Analog I/O Circuits”
- 9.35** MPR Document No. 0449-0602-RWP-001 dated March 9, 2007, “Rework Procedure for the TRICON v10 Nuclear Qualification Project TRICON-Under-Test (TUT),” Rev. 0

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT</b>		
<b>Revision:</b>	2	<b>Page:</b>	49 of 49	<b>Date:</b>	04/30/08

- 9.36** Triconex Qualification Project Anomaly Report (QPAR) No. 044, “Load Fuse Errors on Module 3623T”
- 9.37** Triconex Letter 9600164-025T dated February 6, 2007 to MPR Associates, “Internally Generated Frequencies - TRICON v10 EMI/RFI Testing”
- 9.38** Completed Performance Proof Run No. 3.7 of Triconex Procedure No. 9600164-503, “Operability Test Procedure,” Rev. 3
- 9.39** Completed Performance Proof Run No. 3.4 of Triconex Procedure No. 9600164-504, “Prudency Test Procedure,” Rev. 1
- 9.40** Triconex Qualification Project Anomaly Report (QPAR) No. 055, “3636T Relay Output Module IEC 61000-4-16 Analysis”

## 10.0 ATTACHMENTS

**Attachment 1:** Example Plots of TUT Normal Operating Data

## 11.0 SUPPLEMENTS

**Supplement 1: Supplemental Testing to IEC 61000-4-16, Short Duration Disturbance at 0 Hz (DC)**

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT: ATTACHMENT 1</b>		
<b>Revision:</b>	2	<b>Page:</b>	1 of 14	<b>Date:</b>	05/10/08

**ATTACHMENT 1**

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT: ATTACHMENT 1</b>		
<b>Revision:</b>	2	<b>Page:</b>	2 of 14	<b>Date:</b>	05/10/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT: ATTACHMENT 1</b>		
<b>Revision:</b>	2	<b>Page:</b>	3 of 14	<b>Date:</b>	05/10/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT: ATTACHMENT 1</b>		
<b>Revision:</b>	2	<b>Page:</b>	4 of 14	<b>Date:</b>	05/10/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT: ATTACHMENT 1</b>		
<b>Revision:</b>	2	<b>Page:</b>	5 of 14	<b>Date:</b>	05/10/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT: ATTACHMENT 1</b>		
<b>Revision:</b>	2	<b>Page:</b>	6 of 14	<b>Date:</b>	05/10/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT: ATTACHMENT 1</b>		
<b>Revision:</b>	2	<b>Page:</b>	7 of 14	<b>Date:</b>	05/10/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT: ATTACHMENT 1</b>		
<b>Revision:</b>	2	<b>Page:</b>	8 of 14	<b>Date:</b>	05/10/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT: ATTACHMENT 1</b>		
<b>Revision:</b>	2	<b>Page:</b>	9 of 14	<b>Date:</b>	05/10/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT: ATTACHMENT 1</b>		
<b>Revision:</b>	2	<b>Page:</b>	10 of 14	<b>Date:</b>	05/10/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT: ATTACHMENT 1</b>		
<b>Revision:</b>	2	<b>Page:</b>	11 of 14	<b>Date:</b>	05/10/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT: ATTACHMENT 1</b>		
<b>Revision:</b>	2	<b>Page:</b>	12 of 14	<b>Date:</b>	05/10/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT: ATTACHMENT 1</b>		
<b>Revision:</b>	2	<b>Page:</b>	13 of 14	<b>Date:</b>	05/10/08

a

<b>Document:</b>	9600164-527	<b>Title:</b>	<b>EMI/RFI TEST REPORT: ATTACHMENT 1</b>		
<b>Revision:</b>	2	<b>Page:</b>	14 of 14	<b>Date:</b>	05/10/08

a