

3/4.8 ELECTRICAL POWER SYSTEMS

3/4.8.1 A.C. SOURCES

A.C. SOURCES - OPERATING

LIMITING CONDITION FOR OPERATION

3.8.1.1 As a minimum, the following A.C. electrical power sources shall be OPERABLE:

- a. Two physically independent circuits between the offsite transmission network and the onsite Class 1E distribution system, and
- b. Four separate and independent diesel generators*, each with:
 - 1. Separate engine mounted day fuel tanks containing a minimum of 325 gallons of fuel,
 - 2. A separate fuel storage system containing a minimum of 47,570 gallons of fuel, and
 - 3. A separate fuel transfer pump.

APPLICABILITY: OPERATIONAL CONDITIONS 1, 2, and 3.

ACTION: X

SEE
INSERT A

- ~~a. With either one offsite circuit or one diesel generator of the above required A.C. electrical power sources inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirements 4.8.1.1.1.a within 1 hour and 4.8.1.1.2.a.4, for one diesel generator at a time, within 4 hours and at least once per 8 hours thereafter; restore at least two offsite circuits and four diesel generators to OPERABLE status within 72 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.~~
- ~~b. With one offsite circuit and one diesel generator of the above required A.C. electrical power sources inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirements 4.8.1.1.1.a within 1 hour and 4.8.1.1.2.a.4, for one diesel generator at a time, within 3 hours and at least once per 8 hours thereafter; restore at least one of the inoperable A.C. sources to OPERABLE status within 12 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours. Restore at least two offsite circuits and four diesel generators to OPERABLE status within 72 hours from time of initial loss or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.~~

*Shared with Unit 2.

8607230179 860717
PDR ADCK 05000387
P PDR

* Prior to but within 24 hours of removing any diesel generator from service in order to do work associated with tying in the additional diesel generator, Surveillance Requirement 4.8.1.1.2.a.4 shall be performed on the diesel generators which are to remain in service.

When any diesel generator is removed from service in order to do work associated with tying in the additional diesel generator, the ACTIONS shall read as follows:

- a. With one diesel generator of the above required A.C. electrical power sources inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirements 4.8.1.1.1.a within one hour and 4.8.1.1.2.a.4, within 72 hours and at least once per 72 hours thereafter; restore at least four diesel generators to OPERABLE status within 60 days of accumulated tie-in outage time for all four diesels or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours. The provisions of Specification 3.0.4 are not applicable.
- b. With one offsite circuit and one diesel generator of the above required A.C. electrical power sources inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirements 4.8.1.1.1.a within one hour and 4.8.1.1.2.a.4, within 24 hours and at least once per 72 hours thereafter; restore at least two offsite circuits to OPERABLE status within 12 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours. With the two offsite circuits restored to OPERABLE status, follow ACTION a.
- c. With one diesel generator of the above required A.C. electrical power sources inoperable, in addition to ACTION a or b, above, verify within 2 hours that all required systems, subsystems, trains, components and devices that depend on the remaining diesel generators as a source of emergency power are also OPERABLE except as noted in Specification 3.7.1.2; otherwise, be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.
- d. With two of the above required offsite circuits inoperable, demonstrate the OPERABILITY of four diesel generators by performing Surveillance Requirement 4.8.1.1.2.a.4, for one diesel generator at a time, within four hours and at least once per 8 hours thereafter, unless the diesel generators are already operating; restore at least one of the inoperable offsite circuits to OPERABLE status within 24 hours or be in at least HOT SHUTDOWN within the next 12 hours. With only one offsite circuit restored to OPERABLE status, restore at least two offsite circuits to OPERABLE status within 72 hours from time of initial loss or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.
- e. With two or more of the above required diesel generators inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirement 4.8.1.1.1.a within one hour and 4.8.1.1.2.a.4, for one diesel generator at a time, within 2 hours; restore at least three of the diesel generators to OPERABLE status within 2 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours. With three diesel generators restored to OPERABLE status, follow ACTION a.

INSERT A

- a. With one off-site circuit of the above 3.8.1.1.a required A.C. electrical power sources inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirement 4.8.1.1.1.a within one hour and at least once per 8 hours thereafter and Surveillance Requirement 4.8.1.1.2.a.4 within 24 hours sequentially on four diesel generators unless previously and successfully tested within the last 24 hours; restore at least two off-site circuits to OPERABLE status within 72 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.
- b. With one diesel generator of 3.8.1.1.b inoperable, demonstrate the OPERABILITY of the A.C. off-site sources by performing Surveillance Requirement 4.8.1.1.1.a within 1 hour and at least once per 8 hours thereafter; and Surveillance Requirement 4.8.1.1.2.a.4 within 24 hours; restore the diesel generator to OPERABLE status within 72 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.
- c. With one off-site circuit and one diesel generator of the above required A.C. electrical power sources inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirement 4.8.1.1.1.a within one hour and at least once per 8 hours thereafter; and Surveillance Requirement 4.8.1.1.2.a.4 within 8 hours, restore one of the inoperable sources to OPERABLE status within 12 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours. Restore the other A.C. power source (offsite circuit or diesel generator) to OPERABLE status in accordance with the provisions of Section 3.8.1 Action Statement a or b, as appropriate, with the time requirement of that Action Statement based on the time of initial loss of the remaining inoperable A.C. power sources.

LIMITING CONDITION FOR OPERATION (Continued)

ACTION (Continued)

d.g. With one diesel generator of the above required A.C. electrical power sources inoperable, in addition to ACTION ~~a or b~~, above, verify ^{b or c} within 2 hours that all required systems, subsystems, trains, components and devices that depend on the remaining diesel generators as a source of emergency power are also OPERABLE; otherwise, be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.

e.g. With two of the above required offsite circuits inoperable, demonstrate the OPERABILITY of four diesel generators by performing Surveillance Requirement 4.8.1.1.2.a.4, for one diesel generator at a time, within ^{eight} ~~four~~ hours and ~~at least once per 8 hours thereafter~~, unless the diesel generators are already operating; restore at least one of the inoperable offsite circuits to OPERABLE status within 24 hours or be in at least HOT SHUTDOWN within the next 12 hours. With only one offsite circuit restored to OPERABLE status, restore at least two offsite circuits to OPERABLE status within 72 hours from time of initial loss or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.

f.g. With two or more of the above required diesel generators inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirement 4.8.1.1.1.a within one hour and ^{and} 4.8.1.1.2.a.4, for one diesel generator at a time, within 2 hours, and at least once per 8 hours thereafter; restore at least three of the diesel generators to OPERABLE status within 2 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours. Restore four diesel generators to OPERABLE status within 72 hours from time of initial loss or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.

at least once per 8 hours thereafter

ELECTRICAL POWER SYSTEMS

SURVEILLANCE REQUIREMENTS

4.8.1.1.1 Each of the above required independent circuits between the offsite transmission network and the onsite Class 1E distribution system shall be:

- a. Determined OPERABLE at least once per 7 days by verifying correct breaker alignments and indicated power availability, and
- b. Demonstrated OPERABLE at least once per 18 months during shutdown by transferring, manually and automatically, unit power supply from the normal circuit to the alternate circuit.

4.8.1.1.2 Each of the above required diesel generators shall be demonstrated OPERABLE:

- a. In accordance with the frequency specified in Table 4.8.1.1.2-1 on a STAGGERED TEST BASIS by:
 1. Verifying the fuel level in the engine-mounted day fuel tank.
 2. Verifying the fuel level in the fuel storage tank.
 3. Verifying the fuel transfer pump starts and transfers fuel from the storage system to the engine-mounted day fuel tank.
 4. Verifying the diesel starts from ambient condition and accelerates to at least 600 rpm in less than or equal to 10 seconds. The generator voltage and frequency shall be 4160 ± 400 volts and 60 ± 3.0 Hz within 10 seconds after the start signal. The diesel generator shall be started for this test by using one of the following signals:
 - a) Manual.
 - b) Simulated loss of offsite power by itself.
 - c) Simulated loss of offsite power in conjunction with an ESF actuation test signal.
 - d) An ESF actuation test signal by itself.
 5. Verifying the diesel generator is synchronized, loaded to greater than or equal to 4000 kw in less than or equal to 90 seconds, and operates with this load for at least 60 minutes.
 6. Verifying the diesel generator is aligned to provide standby power to the associated emergency busses.
 7. Verifying the pressure in all diesel generator air start receivers to be greater than or equal to 240 psig.
- b. At least once per 31 days and after each operation of the diesel where the period of operation was greater than or equal to 1 hour by checking for and removing accumulated water from the engine-mounted day fuel tanks.

ELECTRICAL POWER SYSTEMS

SURVEILLANCE REQUIREMENTS (Continued)

- c. At least once per 92 days and from new fuel oil prior to addition to the storage tanks by verifying that a sample obtained in accordance with ASTM-D270-1975 has a water and sediment content of less than or equal to .05 volume percent and a kinematic viscosity @ 40°C of greater than or equal to 1.3 but less than or equal to 2.4 for 1D oil or >1.9 but <4.1 for 2D oil when tested in accordance with ASTM-D975-77, and an impurity level of less than 2 mg. of insolubles per 100 ml. when tested in accordance with ASTM-D2274-70.
- d. At least once per 18 months by:
1. Subjecting the diesel to an inspection in accordance with procedures prepared in conjunction with its manufacturer's recommendations for this class of standby service.
 2. Verifying the diesel generator capability to reject a load of greater than or equal to 1425 kw while maintaining voltage at 4160 ± 400 volts and frequency at 60 ± 3.0 Hz.
 3. Verifying the diesel generator capability to reject a load of 4000 kw without tripping. The generator voltage shall not exceed ~~4360~~ volts during and following the load rejection.
 4. ~~Simulating a loss of offsite power by itself, and:~~
 - ~~a) Verifying deenergization of the emergency busses and load shedding from the emergency busses.~~
 - ~~b) Verifying the diesel generator starts on the auto-start signal, energizes the emergency busses with permanently connected loads within 10 seconds and operates for greater than or equal to 5 minutes while its generator is loaded with the shutdown loads. After energization, the steady state voltage and frequency of the emergency busses shall be maintained at 4160 ± 200 volts and 60 ± 0.5 Hz during this test.~~
 5. ~~Verifying that on an ECCS actuation test signal, without loss of offsite power, the diesel generator starts on the auto-start signal and operates on standby for greater than or equal to 5 minutes. The generator voltage and frequency shall be 4160 ± 200 volts and 60 ± 0.5 Hz within 10 seconds after the auto-start signal; the steady state generator voltage and frequency shall be maintained within these limits during this test.~~

4560

ELECTRICAL POWER SYSTEMS

SURVEILLANCE REQUIREMENTS (Continued)

4.8. Simulating a loss-of-offsite power in conjunction with an ECCS actuation test signal, and: |29

- a) Verifying deenergization of the emergency busses and load shedding from the emergency busses.
- b) Verifying the diesel generator starts on the auto-start signal, energizes the emergency busses with permanently connected loads within 10 seconds, energizes the auto-connected loads through the load timers and operates for greater than or equal to 5 minutes while its generator is loaded with the emergency loads. After energization, the steady state voltage and frequency of the emergency busses shall be maintained at 4160 ± 400 volts and 60 ± 3.0 Hz during this test.
- c) Verifying that all automatic diesel generator trips, except engine overspeed, generator differential and engine low lube oil pressure, are automatically bypassed upon loss of voltage on the emergency bus concurrent with an ECCS actuation signal.
- d) SEE INSERT C

5.7. Verifying the diesel generator operates for at least 24 hours. During the first 2 hours of this test, the diesel generator shall be loaded to greater than or equal to 4700 kW and during the remaining 22 hours of this test, the diesel generator shall be loaded to 4000 kW. The generator voltage and frequency shall be 4160 ± 400 volts and 60 ± 3.0 Hz within 10 seconds after the start signal; the steady state generator voltage and frequency shall be maintained within these limits during this test. ~~Within 5 minutes after completing this 24-hour test, perform Surveillance Requirement 4.8.1.1.2.d.4.b).~~ |29
|29

6. ~~SEE INSERT D~~ by calculation
7.8. Verifying that the auto-connected loads to each diesel generator do not exceed the 2000-hour rating of 4700 kW. |29

8.8. Verifying the diesel generator's capability to:

- a) Synchronize with the offsite power source while the generator is loaded with its emergency loads upon a simulated restoration of offsite power,
- b) Transfer its loads to the offsite power source, and
- c) Be restored to its standby status.

~~If Surveillance Requirement 4.8.1.1.2.d.4.b) is not satisfactorily completed, it is not necessary to repeat the preceding 24 hour test. Rather, the diesel generator may be operated at 4000 kW for 1 hour or until operating temperature has stabilized.~~ |29

INSERT C

- d) Individually simulate a loss-of-offsite power signal and an ECCS actuation test signal and verify actuation of the diesel start relays 4 LOCA 1 and 4 LOCA 2 for each signal.

INSERT D

6. Verify the hot restart capability of the diesel by verifying the diesel generator starts on the auto-start signal, energizes the emergency busses with permanently connected loads within 10 seconds and operates for greater than or equal to 5 minutes while its generator is loaded with the shutdown loads. After energization, the steady state voltage and frequency of the emergency busses shall be maintained at 4160 ± 400 volts and 60 ± 3.0 Hz during this test. This test shall be performed within 5 minutes of completing a one hour run at 4000 KW or within 5 minutes after operating temperatures have stabilized at a load of 4000 KW.

ELECTRICAL POWER SYSTEMS

SURVEILLANCE REQUIREMENTS (Continued)

- 9.10. Verifying that with the diesel generator operating in a test mode and connected to its bus, a simulated ECCS actuation signal overrides the test mode by (1) returning the diesel generator to standby operation, and (2) automatically energizes the emergency loads with offsite power.
- ~~11. Verifying that the fuel transfer pump transfers fuel from each fuel storage tank to the engine-mounted day tank of each diesel via the installed cross-connection lines.~~
- 10.12. Verifying that each diesel generator loading sequence timer shown in Table 4.8.1.1.2-2 is OPERABLE with its setpoint within $\pm 10\%$ of its design setpoint.
- 11.13. Verifying that the following diesel generator lockout features ^{do not} prevent diesel generator starting and/or operation ^{only} when ^{not} required:
- a) Engine overspeed.
 - b) Generator differential.
 - c) Engine low lube oil pressure.
- e. At least once per 10 years or after any modifications which could affect diesel generator interdependence by starting all diesel generators simultaneously, during shutdown, and verifying that all diesel generators accelerate to at least 600 rpm in less than or equal to 10 seconds.
- f. At least once per 10 years by:
- 1. Draining each fuel oil storage tank, removing the accumulated sediment and cleaning the tank using a sodium hypochlorite or equivalent solution, and
 - 2. Performing a pressure test of those portions of the diesel fuel oil system designed to Section III, subsection ND of the ASME Code in accordance with ASME Code Section XI Article IWD-5000. 1a9

4.8.1.1.3 Reports - All diesel generator failures, valid or non-valid, shall be reported to the Commission in a Special Report pursuant to Specification 6.9.2 within 30 days. Reports of diesel generator failures shall include the information recommended in Regulatory Position C.3.b of Regulatory Guide 1.108, Revision 1, August 1977. If the number of failures in the last 100 valid tests, on a per nuclear unit basis, is greater than or equal to 7, the report shall be supplemented to include the additional information recommended in Regulatory Position C.3.b of Regulatory Guide 1.108, Revision 1, August 1977. 1a6

diesel generator

Microsoft

TABLE 4.8.1.1.2-1

DIESEL GENERATOR TEST SCHEDULE

<u>Number of Failures in Last 100 Valid Tests*</u>	<u>Test Frequency</u>
≤ 1	At least once per 31 days
2	At least once per 14 days
≥ 3	At least once per 7 days
4	At least once per 3 days

*Criteria for determining number of failures and number of valid tests shall be in accordance with Regulatory Position C.2.e of Regulatory Guide 1.108, Revision 1, August 1977, where the last 100 tests are determined on a per nuclear unit basis. For the purposes of this test schedule, only valid tests conducted after the OL issuance date shall be included in the computation of the "last 100 valid tests." Entry into this test schedule shall be made at the 31 day test frequency.

diesel generator

3/4.8 ELECTRICAL POWER SYSTEMS

3/4.8.1 A.C. SOURCES

A.C. SOURCES - OPERATING

LIMITING CONDITION FOR OPERATION

3.8.1.1 As a minimum, the following A.C. electrical power sources shall be OPERABLE:

- a. Two physically independent circuits between the offsite transmission network and the onsite Class 1E distribution system, and
- b. Four separate and independent diesel generators*, each with:
 1. Separate engine mounted day fuel tanks containing a minimum of 325 gallons of fuel,
 2. A separate fuel storage system containing a minimum of 47,570 gallons of fuel, and
 3. A separate fuel transfer pump.

APPLICABILITY: OPERATIONAL CONDITIONS 1, 2, and 3.

ACTION: X

SEE
INSERT A

- ~~a. With either one offsite circuit or one diesel generator of the above required A.C. electrical power sources inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirements 4.8.1.1.1.a within 1 hour and 4.8.1.1.2.a.4, for one diesel generator at a time, within 4 hours and at least once per 8 hours thereafter; restore at least two offsite circuits and four diesel generators to OPERABLE status within 72 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.~~
- ~~b. With one offsite circuit and one diesel generator of the above required A.C. electrical power sources inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirements 4.8.1.1.1.a within 1 hour and 4.8.1.1.2.a.4, for one diesel generator at a time, within 3 hours and at least once per 8 hours thereafter; restore at least one of the inoperable A.C. sources to OPERABLE status within 12 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours. Restore at least two offsite circuits and four diesel generators to OPERABLE status within 72 hours from time of initial loss or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.~~

*Shared with Unit 1.

* Prior to but within 24 hours of removing any diesel generator from service in order to do work associated with tying in the additional diesel generator, Surveillance Requirement 4.8.1.1.2.a.4 shall be performed on the diesel generators which are to remain in service.

When any diesel generator is removed from service in order to do work associated with tying in the additional diesel generator, the ACTIONS shall read as follows:

- a. With one diesel generator of the above required A.C. electrical power sources inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirements 4.8.1.1.1.a within one hour and 4.8.1.1.2.a.4, within 72 hours and at least once per 72 hours thereafter; restore at least four diesel generators to OPERABLE status within 60 days of accumulated tie-in outage time for all four diesels or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours. The provisions of Specification 3.0.4 are not applicable.
- b. With one offsite circuit and one diesel generator of the above required A.C. electrical power sources inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirements 4.8.1.1.1.a within one hour and 4.8.1.1.2.a.4, within 24 hours and at least once per 72 hours thereafter; restore at least two offsite circuits to OPERABLE status within 12 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours. With the two offsite circuits restored to OPERABLE status, follow ACTION a.
- c. With one diesel generator of the above required A.C. electrical power sources inoperable, in addition to ACTION a or b, above, verify within 2 hours that all required systems, subsystems, trains, components and devices that depend on the remaining diesel generators as a source of emergency power are also OPERABLE except as noted in Specification 3.7.1.2; otherwise, be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.
- d. With two of the above required offsite circuits inoperable, demonstrate the OPERABILITY of four diesel generators by performing Surveillance Requirement 4.8.1.1.2.a.4, for one diesel generator at a time, within four hours and at least once per 8 hours thereafter, unless the diesel generators are already operating; restore at least one of the inoperable offsite circuits to OPERABLE status within 24 hours or be in at least HOT SHUTDOWN within the next 12 hours. With only one offsite circuit restored to OPERABLE status, restore at least two offsite circuits to OPERABLE status within 72 hours from time of initial loss or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.
- e. With two or more of the above required diesel generators inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirement 4.8.1.1.1.a within one hour and 4.8.1.1.2.a.4, for one diesel generator at a time, within 2 hours; restore at least three of the diesel generators to OPERABLE status within 2 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours. With three diesel generators restored to OPERABLE status, follow ACTION a.

INSERT A

- a. With one off-site circuit of the above 3.8.1.1.a required A.C. electrical power sources inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirement 4.8.1.1.1.a within one hour and at least once per 8 hours thereafter and Surveillance Requirement 4.8.1.1.2.a.4 within 24 hours sequentially on four diesel generators unless previously and successfully tested within the last 24 hours; restore at least two off-site circuits to OPERABLE status within 72 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.
- b. With one diesel generator of 3.8.1.1.b inoperable, demonstrate the OPERABILITY of the A.C. off-site sources by performing Surveillance Requirement 4.8.1.1.1.a within 1 hour and at least once per 8 hours thereafter; and Surveillance Requirement 4.8.1.1.2.a.4 within 24 hours; restore the diesel generator to OPERABLE status within 72 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.
- c. With one off-site circuit and one diesel generator of the above required A.C. electrical power sources inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirement 4.8.1.1.1.a within one hour and at least once per 8 hours thereafter; and Surveillance Requirement 4.8.1.1.2.a.4 within 8 hours, restore one of the inoperable sources to OPERABLE status within 12 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours. Restore the other A.C. power source (offsite circuit or diesel generator) to OPERABLE status in accordance with the provisions of Section 3.8.1 Action Statement a or b, as appropriate, with the time requirement of that Action Statement based on the time of initial loss of the remaining inoperable A.C. power sources.

ELECTRICAL POWER SYSTEMS

LIMITING CONDITION FOR OPERATION (Continued)

ACTION (Continued)

d. ~~g.~~ With one diesel generator of the above required A.C. electrical power sources inoperable, in addition to ACTION ~~a or b~~, above, verify within 2 hours that all required systems, subsystems, trains, components and devices that depend on the remaining diesel generators as a source of emergency power are also OPERABLE; otherwise, be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.

bor C

e. ~~d.~~ With two of the above required offsite circuits inoperable, demonstrate the OPERABILITY of four diesel generators by performing Surveillance Requirement 4.8.1.1.2.a.4, for one diesel generator at a time, within ~~four hours and at least once per 8 hours thereafter~~, unless the diesel generators are already operating; restore at least one of the inoperable offsite circuits to OPERABLE status within 24 hours or be in at least HOT SHUTDOWN within the next 12 hours. With only one offsite circuit restored to OPERABLE status, restore at least two offsite circuits to OPERABLE status within 72 hours from time of initial loss or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.

eight

f. ~~e.~~ With two or more of the above required diesel generators inoperable, demonstrate the OPERABILITY of the remaining A.C. sources by performing Surveillance Requirement 4.8.1.1.a within one hour and ~~and~~ 4.8.1.1.2.a.4, for one diesel generator at a time, within 2 hours, and at least once per 8 hours thereafter; restore at least three of the diesel generators to OPERABLE status within 2 hours or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours. Restore four diesel generators to OPERABLE status within 72 hours from time of initial loss or be in at least HOT SHUTDOWN within the next 12 hours and in COLD SHUTDOWN within the following 24 hours.

and

at least once per 8 hours thereafter

ELECTRICAL POWER SYSTEMS

SURVEILLANCE REQUIREMENTS

4.8.1.1.1 Each of the above required independent circuits between the offsite transmission network and the onsite Class 1E distribution system shall be:

- a. Determined OPERABLE at least once per 7 days by verifying correct breaker alignments and indicated power availability, and
- b. Demonstrated OPERABLE at least once per 18 months during shutdown by transferring, manually and automatically, unit power supply from the normal circuit to the alternate circuit.

4.8.1.1.2 Each of the above required diesel generators shall be demonstrated OPERABLE:

- a. In accordance with the frequency specified in Table 4.8.1.1.2-1 on a STAGGERED TEST BASIS by:
 1. Verifying the fuel level in the engine-mounted day fuel tank.
 2. Verifying the fuel level in the fuel storage tank.
 3. Verifying the fuel transfer pump starts and transfers fuel from the storage system to the engine-mounted day fuel tank.
 4. Verifying the diesel starts from ambient condition and accelerates to at least 600 rpm in less than or equal to 10 seconds. The generator voltage and frequency shall be 4160 ± 400 volts and 60 ± 3.0 Hz within 10 seconds after the start signal. The diesel generator shall be started for this test by using one of the following signals:
 - a) Manual.
 - b) Simulated loss of offsite power by itself.
 - c) Simulated loss of offsite power in conjunction with an ESF actuation test signal.
 - d) An ESF actuation test signal by itself.
 5. Verifying the diesel generator is synchronized, loaded to greater than or equal to 4000 kw in less than or equal to 90 seconds, and operates with this load for at least 60 minutes.
 6. Verifying the diesel generator is aligned to provide standby power to the associated emergency busses.
 7. Verifying the pressure in all diesel generator air start receivers to be greater than or equal to 240 psig.
- b. At least once per 31 days and after each operation of the diesel where the period of operation was greater than or equal to 1 hour by checking for and removing accumulated water from the engine-mounted day fuel tanks.

ELECTRICAL POWER SYSTEMS

SURVEILLANCE REQUIREMENTS (Continued)

- c. At least once per 92 days and from new fuel oil prior to addition to the storage tanks by verifying that a sample obtained in accordance with ASTM-D270-1975 has a water and sediment content of less than or equal to 0.05 volume percent and a kinematic viscosity @ 40°C of greater than or equal to 1.3 but less than or equal to 2.4 for 1D oil or >1.9 but <4.1 for 2D oil when tested in accordance with ASTM-D975-77, and an impurity level of less than 2 mg of insolubles per 100 mL when tested in accordance with ASTM-D2274-70.
- d. At least once per 18 months by:
1. Subjecting the diesel to an inspection in accordance with procedures prepared in conjunction with its manufacturer's recommendations for this class of standby service.
 2. Verifying the diesel generator capability to reject a load of greater than or equal to 1425 kW while maintaining voltage at 4160 ± 400 volts and frequency at 60 ± 3.0 Hz.
 3. Verifying the diesel generator capability to reject a load of 4000 kW without tripping. The generator voltage shall not exceed 4560 volts during and following the load rejection.
 - ~~4. Simulating a loss of offsite power by itself, and:
 - ~~a) Verifying deenergization of the emergency busses and load-shedding from the emergency busses.~~
 - ~~b) Verifying the diesel generator starts on the auto-start signal, energizes the emergency busses with permanently connected loads within 10 seconds and operates for greater than or equal to 5 minutes while its generator is loaded with the shutdown loads. After energization, the steady state voltage and frequency of the emergency busses shall be maintained at 4160 ± 400 volts and 60 ± 3.0 Hz during this test.~~~~
 - ~~5. Verifying that on an ECCS actuation test signal, without loss of offsite power, the diesel generator starts on the auto start signal and operates on standby for greater than or equal to 5 minutes. The generator voltage and frequency shall be 4160 ± 400 volts and 60 ± 3.0 Hz within 10 seconds after the auto start signal; the steady state generator voltage and frequency shall be maintained within these limits during this test.~~

ELECTRICAL POWER SYSTEMS

SURVEILLANCE REQUIREMENTS (Continued)

- 4.8. Simulating a loss-of-offsite power in conjunction with an ECCS actuation test signal, and:
- a) Verifying deenergization of the emergency busses and load shedding from the emergency busses.
 - b) Verifying the diesel generator starts on the auto-start signal, energizes the emergency busses with permanently connected loads within 10 seconds, energizes the auto-connected loads through the load timers and operates for greater than or equal to 5 minutes while its generator is loaded with the emergency loads. After energization, the steady state voltage and frequency of the emergency busses shall be maintained at 4160 ± 400 volts and 60 ± 3.0 Hz during this test.
 - c) Verifying that all automatic diesel generator trips, except engine overspeed, generator differential and engine low lube oil pressure, are automatically bypassed upon loss of voltage on the emergency bus concurrent with an ECCS actuation signal.

SGG
INSERT C

5.7.

- d) Verifying the diesel generator operates for at least 24 hours. During the first 2 hours of this test, the diesel generator shall be loaded to greater than or equal to 4700 kw and during the remaining 22 hours of this test, the diesel generator shall be loaded to 4000 kw. The generator voltage and frequency shall be 4160 ± 400 volts and 60 ± 3.0 Hz within 10 seconds after the start signal; the steady state generator voltage and frequency shall be maintained within these limits during this test. ~~Within 5 minutes after completing this 24-hour test, perform Surveillance Requirement 4.8.1.1.2.d.4.b).~~*

SGG
INSERT D

6.
7.8.

- Verifying that the auto-connected loads to each diesel generator do not exceed the 2000-hour rating of 4700 kw. by calculation

- 8.8. Verifying the diesel generator's capability to:
- a) Synchronize with the offsite power source while the generator is loaded with its emergency loads upon a simulated restoration of offsite power.
 - b) Transfer its loads to the offsite power source, and
 - c) Be restored to its standby status.

~~*If Surveillance Requirement 4.8.1.1.2.d.4.b) is not satisfactorily completed, it is not necessary to repeat the preceding 24-hour test. Rather, the diesel generator may be operated at 4000 kw for 1 hour or until operating temperature has stabilized.~~

INSERT C

- d) Individually simulate a loss-of-offsite power signal and an ECCS actuation test signal and verify actuation of the diesel start relays 4 LOCA 1 and 4 LOCA 2 for each signal.

INSERT D

6. Verify the hot restart capability of the diesel by verifying the diesel generator starts on the auto-start signal, energizes the emergency busses with permanently connected loads within 10 seconds and operates for greater than or equal to 5 minutes while its generator is loaded with the shutdown loads. After energization, the steady state voltage and frequency of the emergency busses shall be maintained at 4160 ± 400 volts and 60 ± 3.0 Hz during this test. This test shall be performed within 5 minutes of completing a one hour run at 4000 KW or within 5 minutes after operating temperatures have stabilized at a load of 4000 KW.

ELECTRICAL POWER SYSTEMS

SURVEILLANCE REQUIREMENTS (Continued)

9. 10. Verifying that with the diesel generator operating in a test mode and connected to its bus, a simulated ECCS actuation signal overrides the test mode by (1) returning the diesel generator to standby operation, and (2) automatically energizes the emergency loads with offsite power.
- ~~11. Verifying that the fuel transfer pump transfers fuel from each fuel storage tank to the engine mounted day tank of each diesel via the installed cross connection lines.~~
10. 12. Verifying that each diesel generator loading sequence timer shown in Table 4.8.1.1.2-2 is OPERABLE with its setpoint within $\pm 10\%$ of its design setpoint.
11. 13. Verifying that the following diesel generator lockout features ^{do not} prevent diesel generator starting and/or operation _{only} when ^{not} required:
- a) Engine overspeed.
 - b) Generator differential.
 - c) Engine low lube oil pressure.
- e. At least once per 10 years or after any modifications which could affect diesel generator interdependence by starting all diesel generators simultaneously, during shutdown, and verifying that all diesel generators accelerate to at least 600 rpm in less than or equal to 10 seconds.
- f. At least once per 10 years by:
- 1. Draining each fuel oil storage tank, removing the accumulated sediment and cleaning the tank using a sodium hypochlorite or equivalent solution, and
 - 2. Performing a pressure test of those portions of the diesel fuel oil system designed to Section III, subsection ND of the ASME Code in accordance with ASME Code Section XI Article IWB-5000.

4.8.1.1.3 Reports - All diesel generator failures, valid or nonvalid, shall be reported to the Commission in a Special Report pursuant to Specification 6.9.2 within 30 days. Reports of diesel generator failures shall include the information recommended in Regulatory Position C.3.b of Regulatory Guide 1.108, Revision 1, August 1977. If the number of failures in the last 100 valid tests, on a per-nuclear-unit basis, is greater than or equal to 7, the report shall be supplemented to include the additional information recommended in Regulatory Position C.3.b of Regulatory Guide 1.108, Revision 1, August 1977.


diesel generator

TABLE 4.8.1.1.2-1

DIESEL GENERATOR TEST SCHEDULE

<u>Number of Failures in Last 100 Valid Tests*</u>	<u>Test Frequency</u>
≤ 1	At least once per 31 days
2	At least once per 14 days
≥ 3	At least once per 7 days
$\rightarrow 4$	At least once per 3 days

*Criteria for determining number of failures and number of valid tests shall be in accordance with Regulatory Position C.2.e of Regulatory Guide 1.108, Revision 1, August 1977, where the last 100 tests are determined on a per nuclear unit basis. For the purposes of this test schedule, only valid tests conducted after the OL issuance date shall be included in the computation of the "last 100 valid tests." Entry into this test schedule shall be made at the 31 day test frequency.



1944

100