



- LEGEND**  
 [ ] REPRESENTS MFR CABLE SERIAL NO.  
 \* THIS SHEET
- NOTES**
- CONTACT CLOSURE STARTS RECORDER CHART DRIVE FR-HV4982BS (SH. 2988).
  - RECORDER FR-HV4982BS (SH. 2988) HAS INPUT FROM CHANNEL F-HV5037BS (THIS SH.).
  - RECORDER PDR-HV5039BS HAS INPUT FROM CHANNEL PD-HV5039BS (THIS SHEET) & PD-HV4906BS (SH. 2983).
  - CONTACT 42X/CU-5B (SH. 2983) CLOSURE STARTS RECORDER CHART DRIVES (PDR-HV4900BS & FR-HV4902BS (THIS SHEET), PDR-HV4904BS (SH. 2983) & PDR-HV5039BS (THIS SH.)).
  - RECORDER PR-HV4900BS HAS INPUT FROM CHANNEL PD-HV4900B2S & PD-HV4901B2S.
  - CONTACT OPENS ON HIGH DIFF. PRESS.
  - CONTACT OPENS ON LOW FLOW.
  - CONTACT CLOSURE STARTS RECORDER CHART DRIVE PDR-HV5039BS (THIS SHEET) & BLOCKS CHART DRIVES PDR-HV4900BS & FR-HV4902BS.
  - FIELD TO WIRE.

PRO APERTURE CARD

NUCLEAR SAFETY RELATED WPPSS QUALITY CLASS I

EBASCO SERVICES INCORPORATED			
7-23-82	VA	DD	
12-15-81	VA	DD	
8-7-81	VA	DD	
6-27-79	VA	DD	
REV	DATE	BY	APPROVED
			DATE JUN 9, 1978

WASHINGTON PUBLIC POWER SUPPLY SYSTEM  
 NUCLEAR PROJECTS NO. 3 & 5  
 CONTROL WIRING DIAGRAM  
 HVAC 3B INSTRUMENTATION SH. I

WPPS-3240  
 D-6001  
 SHEET 2982

RIDS

8303930560

